C1417 (GY)

14B527

Alternate fuel injector 2



F02351

Pin	Circuit	Circuit function
1	2100 (DG/OG)	Alternate fuel injector 2, control
2	2107 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C1418 (GY)

14B527

Alternate fuel injector 3



F02351

Pin	Circuit	Circuit function
1	2101 (LB/BK)	Alternate fuel injector 3, control
2	2107 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C1419 (GY)

14B527

Alternate fuel injector 4



F02351

Pin	Circuit	Circuit function
1	2102 (DG/WH)	Alternate fuel injector 4, control
2	2107 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C1420 (GY)

14B527

Alternate fuel injector 5



F02351

Pin	Circuit	Circuit function
1	2103 (LB/OG)	Alternate fuel injector 5, control
2	2107 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C1421 (GY)

14B527

Alternate fuel injector 6



F02351

Pin	Circuit	Circuit function
1	2104 (DG/YE)	Alternate fuel injector 6, control
2	2107 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C1422 (GY)

14B527

Alternate fuel injector 7



F02351

Pin	Circuit	Circuit function
1	2105 (LB/PK)	Alternate fuel injector 7, control
2	2107 (RD/LG)	Voltage supplied in Start and Run (overload protected)