C2234

14401

K509
Autolamp dimmer relay



F05064

Pin	Circuit	Circuit function
1	14 (BN)	Power, Exterior lamps
2	57 (BK)	Ground
3	192 (BN/WH)	Autolamp dimmer relay, switched output
4	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
5	235 (RD/BK)	Instrument illumination, input

C3002 (GY)

14B079

M130
Blower motor, rear (18456)



F02073

Pin	Circuit	Circuit function
1	1132 (YE)	Blower motor, feed
2	1133 (BN)	Blower motor, return

C3003

14B079

R78
Heater blower motor resistor, rear (19A706)



F04187

Pin	Circuit	Circuit function
1	1135 (LB/OG)	Blower motor, to switch
2	1133 (BN)	Blower motor, return
3	–	not used
4	1134 (OG/BK)	Blower motor, to switch – High

C3006

14B079

P83
Function selector switch assembly, rear



F08167

Pin	Circuit	Circuit function
1	–	not used
2	–	not used
3	–	not used
4	–	not used
5	1134 (OG/BK)	Blower motor, to switch – High
6	1135 (LB/OG)	Blower motor, to switch
7	57 (BK)	Ground
8	–	not used