C2256 (BK)

14401

Barometric Absolute Pressure (BAP) sensor



F04195

Pin	Circuit	Circuit function
1	359 (GY/RD)	Signal return
2	351 (BN/WH)	Reference voltage
3	356 (DB/LG)	Sensor signal
4	–	not used

C2257

Reversing lamps relay



F05139

Pin	Circuit	Circuit function
1	–	PCM power relay, switched power
2	324 (YE/LG)	Switched ground, Coil
3	140 (BK/PK)	Switched power, output
4	–	not used
5	–	Voltage supplied at all times (overload protected), Contact

C2259

Fuel heater relay



F05107

Pin	Circuit	Circuit function
30	–	Voltage supplied at all times (overload protected), Contact
85	57 (BK)	Ground, Coil
86	1044 (WH/YE)	Voltage supplied in Start and Run (overload protected), Coil
87	16 (RD/LG)	Switched power, output
87A	–	not used

C3002

14A504

Blower motor, rear (18456)



F02329

Pin	Circuit	Circuit function
1	371 (PK/WH)	Blower motor relay, switched output
2	536 (BK/LG)	Blower motor relay, Blower motor