-8

Wiper/Washer Switch

COMPONENT TESTING PROCEDURE

TO TEST	Connect Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Rheostat (variable intermittent wipe)	e and f	1	1 kΩ
		2	10 kΩ
		3	20 kΩ
		4	30 kΩ
		5	40 kΩ
		6	47 kΩ
Single Wipe Front Wiper	h and a	Single wipe	Closed Circuit
		Off	Open Circuit
		Intermittent	Open Circuit
		Normal	Open Circuit
		Fast	Open Circuit
Intermittent Wipe Front Wiper	d and a	Single wipe	Open Circuit
		Off	Closed Circuit
		Intermittent	Closed Circuit
		Normal	Open Circuit
		Fast	Open Circuit
	h and e	Single wipe	Open Circuit
		Off	Open Circuit
		Intermittent	Closed Circuit
		Normal	Open Circuit
		Fast	Open Circuit
	h and f	Single wipe	Open Circuit
		Off	Open Circuit
		Intermittent	Refer to Rheostat
		Normal	Open Circuit
		Fast	Open Circuit
Normal Wipe Front Wiper	h and a	Single wipe	Open Circuit
		Off	Open Circuit
		Intermittent	Open Circuit
		Normal	Closed Circuit
		Fast	Open Circuit
Fast Wipe Front Wiper	h and b	Single wipe	Open Circuit
		Off	Open Circuit
		Intermittent	Open Circuit
		Normal	Open Circuit
		Fast	Open Circuit
Front and Rear Washer	h and k	Off	Closed Circuit
		Front washer on	Closed Circuit
		Rear washer on	Open Circuit
	j and i	Off	Open Circuit
		Front washer on	Closed Circuit
		Rear washer on	Open Circuit
	h and i	Off	Closed Circuit
		Front washer on	Open Circuit
		Rear washer on	Closed Circuit
	j and k	Off	Open Circuit
		Front washer on	Open Circuit
		Rear washer on	Closed Circuit
Rear Wiper	h and g	Off	Open Circuit
		Rear wiper on	Closed Circuit
	i and g	Off	Closed Circuit
		Rear wiper on	Open Circuit