C102c

14A280

Generator



F01085

Pin	Circuit	Circuit function
1	36 (YE/WH)	Voltage supplied at all times (overload protected)

C103

12A522 (WH–ZETEC)
9H589 (BK–DURATEC)

Oil pressure switch
(9278)



F01016

Pin	Circuit	Circuit function
1	253 (DG/WH)	Oil pressure switch (9278), input

C109 (BK)

12A522

Knock sensor
(12A699)



F02066

Pin	Circuit	Circuit function
1	310 (YE/RD)	Knock sensor (12A699)
2	311 (DG/VT)	Knock sensor (12A699)

C110 (BK)

12A522–DURATEC
9H589–ZETEC



F16091

DURATEC

(1) 296 (WH/VT)
(2) 351 (BN/WH)
(3) –
(4) 57 (BK)
(5) –
(6) 100 (WH/RD)
(7) –
(8) 1202 (BN/LG)
(9) –
(10) 253 (DG/WH)
(11) 354 (LG/RD)
(12) 330 (YE/LG)
(13) 138 (BK/PK)
(14) 139 (GY/YE)
(15) 282 (DB/OG)
(16) 355 (GY/WH)

9H589–DURATEC
12A522–ZETEC



F16020

ZETEC

(1) –
(2) 558 (BN/LB)
(3) 89 (OG)
(4) 355 (GY/WH)
(5) –
(6) 557 (BN/YE)
(7) –
(8) 351 (BN/WH)
(9) –
(10) 556 (WH)
(11) 264 (WH/LB)
(12) 282 (DB/OG)
(13) 354 (LG/RD)
(14) 555 (TN)
(15) 361 (RD)
(16) 1202 (BN/LG)