## C270e

**14401**

Central Junction Box
(CJB)




97BG-14489-ZTB (F)

| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 1266 (RD/YE) | Passive anti-theft tranceiver module - RF power |
| 2 | — | not used |
| 3 | 1001 (WH/YE) | Fused battery feed to module, GEM-input |
| 4 | 1001 (WH/YE) | Fused battery feed to module, GEM-input |
| 5 | 1001 (WH/YE) | Fused battery feed to module, GEM-input |
| 6 | 1001 (WH/YE) | Fused battery feed to module, GEM-input |
| 7 | — | not used |
| 8 | 705 (LG/OG) | Battery saver lamp feed |
| 9 | — | not used |
| 10 | — | not used |
| 11 | 1009 (OG/YE) | Module, GEM to heated backlight relay-output |
| 12 | 295 (LB/PK) | Electronic cluster accessory feed |
| 13 | 1002 (BK/PK) | Fused ignition "run/accessory" to module, GEM-input |
| 14 | — | not used |
| 15 | 1004 (LB/RD) | Module, GEM to delayed accessory relay-output |
| 16 | — | not used |

## C270f

**14401**

Central Junction Box
(CJB)




97BG-14489-YTB (F)

| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 1003 (GY/YE) | Fused ignition "run" to module, GEM-input |
| 2 | — | not used |
| 3 | 645 (WH/LB) | Module, perimeter anti-theft - fused feed |
| 4 | — | not used |
| 5 | — | not used |
| 6 | — | not used |
| 7 | 1002 (BK/PK) | Fused ignition "run/accessory" to module, GEM-input |
| 8 | — | not used |
| 9 | — | not used |
| 10 | 1003 (GY/YE) | Fused ignition "run" to module, GEM-input |
| 11 | 1001 (WH/YE) | Fused battery feed to module, GEM-input |
| 12 | — | not used |
| 13 | — | not used |
| 14 | — | not used |
| 15 | 1003 (GY/YE) | Fused ignition "run" to module, GEM-input |
| 16 | — | not used |