C1004

14290

K317
Windshield washer relay



F05064

Pin	Circuit	Circuit function
1	686 (TN/RD)	Washer motor relay, control
2	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
3	941 (BK/WH)	Windshield washer pump motor (17618), feed
4	–	not used
5	950 (WH/BK)	Voltage in Run or Accessory (overload protected)

C1007

14290

K26
Fog lamp relay



F05064

Pin	Circuit	Circuit function
1	474 (LG/OG)	Fog lamp relay, control
2	477 (LB/BK)	Fog lamp switch, to front fog lamp, Relay
3	54 (LG/YE)	Voltage supplied at all times (overload protected)
4	–	not used
5	478 (TN/OG)	Fog lamp relay, output, to, fog lamps

C1008

14290

K107
A/C clutch relay



F05064

Pin	Circuit	Circuit function
1	331 (PK/YE)	A/C clutch relay, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)
3	883 (PK/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	321 (GY/WH)	A/C clutch relay, switched output

C1011

14290

K73
Blower motor relay



F05051

Pin	Circuit	Circuit function
87	181 (BN/OG)	Voltage supplied at all times (overload protected)
87A	–	not used
86	260 (RD/OG)	Blower motor relay, control
85	57 (BK)	Ground
30	371 (PK/WH)	Blower motor relay, switched output

C1016

14290

K163
PCM power relay



F05051

Pin	Circuit	Circuit function
87	361 (RD)	Voltage supplied in Start and Run (overload protected)
87A	–	not used
86	546 (DG/YE)	Voltage supplied in Start and Run (overload protected)
85	570 (BK/WH)	Ground
30	554 (YE/BK)	Voltage supplied at all times (overload protected)