COMPONENT TESTING: MULTIFUNCTION SWITCH 149-6

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Lamp or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Flash-To-Pass	5 and 7	Lever Stalk pull and hold toward Steering Wheel	Closed Circuit
Dimmer High Beam	2 and 5	Lever Stalk away from Steering Wheel	Closed Circuit
Dimmer Low Beam	2 and 3	Lever Stalk in detent closest to Steering Wheel	Closed Circuit
Turn Switch Circuit	1 and 10 Place Jumper Wire Between Pin 11 and Pin 6	Hazard Switch to Normal (OFF) and Turn Switch to Turn Left	Closed Circuit
	1 and 2 Place Jumper Wire Between Pin 11 and Pin 6	Hazard Switch to Normal (OFF) and Turn Switch to Turn Right	Closed Circuit
Cornering	2 and 7	Turn Switch to Turn Left	Closed Circuit
	2 and 3	Turn Switch To Turn Right	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Lamp or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Hazard Switch Circuit	4 and 11, 6 and 10, 2	Hazard Switch On (Button depressed then released to full out position)	Closed Circuit
	1 and 11	Hazard Switch OFF	Closed Circuit
Stop Circuit	9 and 2	Hazard Switch OFF	Closed Circuit
	9 and 10	Hazard Switch OFF	Closed Circuit