Wiper/washer switch (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Rheostat (variable intermittent wipe)	e and f	1	1 kΩ
		2	10 kΩ
		3	20 kΩ
		4	30 kΩ
		5	40 kΩ
		6	47 kΩ
Single wipe (front wiper)	h and a	Single wipe	Closed circuit
		Off	Open circuit
		Intermittent	Open circuit
		Normal	Open circuit
		Fast	Open circuit
Intermittent wipe front	d and a	Single wipe	Open circuit
		Off	Closed circuit
		Intermittent	Closed circuit
		Normal	Open circuit
		Fast	Open circuit
	h and e	Single wipe	Open circuit
		Off	Open circuit
		Intermittent	Closed circuit
		Normal	Open circuit
		Fast	Open circuit
	h and f	Single wipe	Open circuit
		Off	Open circuit
		Intermittent	Rheostat
		Normal	Open circuit
		Fast	Open circuit
Normal wipe front	h and a	Single wipe	Open circuit
		Off	Open circuit
		Intermittent	Open circuit
		Normal	Closed circuit
		Fast	Open circuit