C270b (GY)

14401

Central Junction
Box (CJB) (14A067)



F12137

Pin	Circuit	Circuit function
1	792 (TN/YE)	Voltage supplied at all times (overload protected)
2	10 (LG/RD)	Voltage supplied at all times (overload protected)
3	9 (LG/OG)	Turn lamps, feed, left rear
4	1266 (RD/YE)	Hot in Start or Run
5	14 (BN)	Power, Exterior lamps
6	785 (BK/LG)	Voltage supplied at all times (overload protected)
7	632 (GY/OG)	Power, Hot with High Beams on
8	1522 (DG)	Voltage supplied at all times (overload protected)
9	12 (LG/BK)	Power, Hot with High Beams on
10	195 (TN/WH)	Voltage supplied at all times (overload protected)
11	5 (OG/LB)	Turn lamps, feed, right rear
12	196 (DB/OG)	Voltage supplied at all times (overload protected)

C270c

* 6.0L Diesel
** all others

14401

Central Junction
Box (CJB) (14A067)



F06267

Pin	Circuit	Circuit function
1	1040 (RD/BK)	Voltage in Run (overload protected)
2	37 (YE)	Voltage supplied at all times (overload protected)
3	*544 (VT)	Voltage supplied at all times (overload protected)
3	**1050 (LG/VT)	Voltage supplied at all times (overload protected)
4	*1044 (WH/YE)	Voltage supplied in Start and Run (overload protected)
4	**16 (RD/LG)	Voltage supplied in Start and Run (overload protected)
5	687 (GY/YE)	Voltage in Run (overload protected)
6	964 (DB/LG)	fused feed, Accessory