C62 (BN)

14401



F11016

Pin	Circuit	Circuit Function
1	15-GL37 (GN/BK)	Voltage, ignition switch in Start or Run (not overload protected)
2	4-EC1 (GY/RD)	Data link, bus positive
3	5-EC1 (BU/RD)	Data link, bus negative
4	31S-AA43 (BK/WH)	Ground, switched
	49S-LG20 (BU/WH)	Pulsed power feed (overload protected), switched
5	–	not used
6	15S-TA38B (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected), switched
7	8-BB6 (WH)	Sensor signal
8	15S-RN2 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected), switched
9	9-BB6 (BN)	Sensor signal return (reference/ground)
10	29S-LK21 (OG/BK)	Voltage supplied at all times (overload protected), switched
11	91-GL37 (BK/GN)	Ground