C1041 (BK)

14290

Headlamp, right (13008)



F03169

Pin	Circuit	Circuit function
1	12 (LG/BK)	Power, Hot with High Beams on
2	57 (BK)	Ground
3	1056 (DB/LG)	Headlamp, right (13008) - fused feed – Low beams

C1043 (BN)

14290

Park/turn lamp, right front (13411)



F03099

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	14 (BN)	Power, Exterior lamps
3	2 (WH/LB)	Turn lamps, feed, right front

C1048 (BK)

14290

Engine cooling fan motor



F02395

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	228 (DB)	Engine cooling fan relay, switched output

C1051 (WH)

14290

Fuel pump relay



F05064

Pin	Circuit	Circuit function
1	926 (LB/OG)	Fuel pump relay, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)
3	1059 (LB/OG)	Voltage supplied at all times (overload protected)
4	–	not used
5	238 (DG/YE)	Fuel pump relay, switched power, output

C1055 (BK)

14290

Engine cooling fan relay



F05051

Pin	Circuit	Circuit function
30	1153 (RD/BK)	Voltage supplied at all times (overload protected)
85	3702 (OG/WH)	Engine cooling fan relay, control
86	361 (RD)	Voltage supplied in Start and Run (overload protected)
87	228 (DB)	Engine cooling fan relay, switched output
87A	–	not used

C1061 (BN)

12B637

Engine Coolant Temperature (ECT) sender



F02091

Pin	Circuit	Circuit function
1	39 (RD/WH)	Engine Coolant Temperature (ECT) sender, input
2	570 (BK/WH)	Ground