C290b

19B107

A220
Audio unit



F08187

Pin	Circuit	Circuit Function
1	172 (LB/RD)	Radio - Subwoofer, Low -
2	169 (LG/BK)	Radio - Subwoofer, Low +
3	1205 (BK)	Ground
4	174 (GY/BK)	Radio - Subwoofer, Low, mute
5	-	not used
6	-	not used
7	-	not used
8	-	not used

C294a

14401

P76
Function selector
switch assembly



F08181

Pin	Circuit	Circuit Function
1	399 (BN/YE)	Blower motor relay, control
2	41 (BK/LB)	Voltage supplied in Start and Run (overload protected)
3	-	not used
4	348 (VT)	A/C demand signal
5	-	not used
6	-	not used
7	-	not used
8	-	not used

C293

14401

M204
Front blower motor
resistor assembly



F04249

Pin	Circuit	Circuit Function
1	752 (YE/RD)	Blower switch speed control, to resistor
2	57 (BK)	Ground
3	261 (OG/BK)	Blower motor, to switch - High
4	754 (LG/WH)	Blower switch speed control, to resistor

C294b

14401

P76
Function selector
switch assembly



F04247

Pin	Circuit	Circuit Function
1	261 (OG/BK)	Blower motor, to switch - High
2	57 (BK)	Ground
3	752 (YE/RD)	Blower switch speed control, to resistor
4	754 (LG/WH)	Blower switch speed control, to resistor