C2013a

14401

A277
Belt minder module



F04143

Pin	Circuit	Circuit function
1	450 (DG/LG)	Safety belt indicator, control
2	85 (BN/LB)	Safety belt buckle switch (10B924), input
3	–	not used
4	257 (WH/RD)	Hot in Park or Head

C2013b

14401

A277
Belt minder module



F04143

Pin	Circuit	Circuit function
1	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	–	not used
3	–	not used
4	875 (BK/LB)	Ground

C2014

14401

E39
Ashtray illumination
lamp



F02071

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	19 (LB/RD)	Instrument illumination, feed

C2015

14631/14A005

N63
Parking brake
switch (15A851)

F01029

Pin	Circuit	Circuit function
1	162 (LG/RD)	Parking brake switch (15A851)

C2017

14401

K73
Blower motor relay



F05016

Pin	Circuit	Circuit function
30	399 (BN/YE)	Blower motor relay, switched power
85	57 (BK)	Ground
	461 (OG)	Blower motor relay, control
86	181 (BN/OG)	Function selector switch assembly, output
	296 (WH/VT)	Voltage in Run (overload protected)
87	364 (BK/LG)	Voltage supplied at all times (overload protected)
87a	–	not used