C100

14A280

Y31
A/C clutch solenoid



F02245

Pin	Circuit	Circuit Function
1	321 (GY/WH)	A/C clutch relay, switched output
2	57 (BK)	Ground

C101

12B637

B43
Crankshaft position sensor

2.3L



4.0L



Pin	Circuit	Circuit Function
1	349 (DB)	Crankshaft position sensor –
2	350 (GY)	Crankshaft position sensor +

C102a

14A280/12B637

O5
Generator

2.3L



F03215

2.5L, 3.0L, 4.0L



F03074

Pin	Circuit	Circuit Function
1	904 (LG/RD)	Generator/Battery indicator, control
2	4 (WH/BK)	Generator regulator 'S' terminal, to generator 'S' terminal
3	36 (YE/WH)	Voltage supplied at all times (overload protected)

C102b

14A280

O5
Generator



F01057

Pin	Circuit	Circuit Function
1	38 (BK/OG)	Voltage supplied at all times (not overload protected)

C102c

14A280/12B637

O5
Generator



F01053

Pin	Circuit	Circuit Function
1	4 (WH/BK)	Generator regulator 'S' terminal, to generator 'S' terminal

C103

14A280/12B637

N17
Oil pressure switch



F01016

Pin	Circuit	Circuit Function
1	253 (DG/WH)	Oil pressure switch, input

C107

12B637

B135
Cylinder–head temperature sensor



F02111

Pin	Circuit	Circuit Function
1	1102 (YE/LG)	Cylinder–head temperature sensor, to, Powertrain Control Module (PCM)
2	359 (GY/RD)	signal, return