C100 (BK)

* 3.8L
** Mach 1

12B637
***12A581**
****12B559**

A/C clutch field coil (19D798)



F02261

Pin	Circuit	Circuit function
1	347 (BK/YE)	A/C clutch relay, switched output
2	1205 (BK)	Ground

C101 (BK)

* 3.8L
** Mach 1

***9D930**
12B637
****12B559**

Crankshaft position sensor (6C315)



F02645

Pin	Circuit	Circuit function
1	350 (GY)	Crankshaft position sensor (6C315) –
2	349 (DB)	Crankshaft position sensor (6C315) +

C102a (GY)

* 3.8L
*** 4.6L 2V

****12B637**
***14305**
14B060

Generator



F03247

Pin	Circuit	Circuit function
1	904 (LG/RD)	Generator/Battery indicator, control
2	–	not used
3	36 (YE/WH)	Voltage supplied at all times (overload protected)

C102b (BK)

* 3.8L
‡ Cobra

12B637
***14305**
‡14B060

Generator


F01085

Pin	Circuit	Circuit function
1	38 (BK/OG)	Voltage supplied at all times (overload protected)

C102c (BK)

12B637

Generator



F03074

Pin	Circuit	Circuit function
1	904 (LG/RD)	Generator/Battery indicator, control
2	4 (WH/BK)	not used
3	36 (YE/WH)	Voltage supplied at all times (overload protected)

C103

* 3.8L

***9D930**
14B060

Oil pressure switch (9278)


F01016

Pin	Circuit	Circuit function
1	31 (WH/RD)	engine Oil pressure switch (9278) signal