C1016

14290

K163
PCM power relay



F05078

Pin	Circuit	Circuit Function
30	30-RH9 (RD/BU)	Voltage supplied at all times (not overload protected)
85	31-RH9 (BK)	Ground
86	15-RH9 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected)
87	15S-DB1 (GN/YE)	Voltage, ignition switch in Start or Run (not overload protected), switch
87A	–	not used

C1017

14290

K22
Starter relay (11450)



F05078

Pin	Circuit	Circuit Function
30	30-BB13 (RD/OG)	Voltage supplied at all times (not overload protected)
85	31S-BB12 (BK/YE)	Ground, Switched
86	50S-BB12 (GY)	Voltage, ignition switch in Start (not overload protected), Switched
87	50-BB10 (GY/BK)	Voltage, ignition switch in Start (not overload protected)
87A	–	not used

C1018

V34
PCM power diode



F02287

Pin	Circuit	Circuit Function
1	15-RD6 (GN/OG)	Voltage, ignition switch in Start or Run (not overload protected electronic module)
2	15-RH9 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected electronic module)