C2131a

14A005

A304
Air suspension module (3C142)



F13013

Pin	Circuit	Circuit function
1	418 (DG/YE)	Voltage supplied at all times (overload protected)
2	635 (YE)	Air suspension module (3C142)
3	428 (OG/PK)	Powertrain Control Module (PCM) (12A650), to, Air suspension module (3C142), signal
4	–	not used
5	–	not used
6	570 (BK/WH)	Ground
7	–	not used
15	–	not used
16	296 (WH/VT)	Fused accessory relay, switched power, output
17	427 (PK/BK)	Vehicle Dynamic Module (VDM), Module programming signal
18	633 (R)	Steering position sensor (18B015), to, Air suspension module (3C142), Terminal (+) A
19	634 (BR)	Steering position sensor (18B015), to, Air suspension module (3C142), Terminal (+) B
20	–	not used

C2131b

14A005

A304
Air suspension module (3C142)



F13015

Pin	Circuit	Circuit function
8	432 BK/PK)	Air suspension module (3C142), Ground
9	914 (TN/OG)	SCP Bus +
10	915 (PK/LB)	SCP Bus –
11	–	not used
12	–	not used
13	1114 (BR/BK)	Air suspension module (3C142), to, Left, rear, Solenoid
14	86 (GY/OG)	ZF gear solenoid +
21	–	not used
22	417 (P/OG)	Air suspension disable switch, feed
23	420 (DB/Y)	Air suspension module (3C142), to, Air suspension compressor relay, signal
24	421 (PK)	Air suspension compressor assembly, Vent solenoid, to,Air suspension module (3C142)
25	1115 (T/WH)	Air suspension module (3C142), to, Right, rear, Solenoid
26	87 (TN/YE)	Blower motor, feed

C2133

14401

A291
Cellular phone microphone



F04105

Pin	Circuit	Circuit function
1	714 (VT)	Microphone, audio
2	–	not used
3	48	Shield
4	713 (WH)	Microphone, Ground