• DRIVEABILITY—BI-FUEL WIRING CONNECTOR CROSS-REFERENCE CHART • ELECTRICAL—BI-FUEL WIRING CONNECTOR CROSS-REFERENCE CHART	Article No. 01-20-6

FORD: 1999-2000 CONTOUR
1999 E SERIES
1999-2002 F-150, SUPER DUTY F SERIES

ISSUE

The alt fuel wiring connectors are labeled with GFI/Bi-Fuel numbers and are shown in the Wiring Diagrams section of the Ford Workshop Manual information as Ford numbers.

ACTION

Use the following GFI to Ford Cross-Reference chart to identify the alt fuel wiring connectors to help aid in diagnosis.

SERVICE INFORMATION

GFI/FORD Electrical Connector Cross-Reference Chart		
GFI Connector Number and Description	**MY 1999-2001 Ford Number**	**MY 2002 Ford Number**
J/P 26 - Fuse & Relay Power	C4026 M/F	C495 M/F
J/P 19 - Fuel Pump Cutoff	C4019 M/F	C4001 M/F
J/P 35 - Compuvalve Power	C4035 M/F	C410 M/F
J 25 - Compuvalve Bulkhead	C4025	C1294
J/P 13 - High Flow Injectors	C4013 M/F	C1297 M/F
J/P 14 - Low Flow Injectors	C4014 M/F	C1289 M/F
J/P 3 - Vaporizer/Regulator Power	C4003 M/F	C4002 M/F
J/P 30 - Sensor/Fuel Gauge	C4030 M/F	C406 M/F
J/P 36 - Communication/Tach	C4036 M/F	C421 M/F
J/P 37 - Switch/O2 Sensor	C4037 M/F	C422 M/F
J8 - GFI Communication	C4008 M/F	C4004
J/P 10 - Alt Fuel Selector Switch	C4010 M/F	C4013 M/F
J/P 303 - Tank Sender/Sensor	C4303 M/F	C4125
J/P 120 - Tank Valve	C4120	C4129
J/P 21 - Cold Start Heater	C4021 M/F	C1295
J/P 302 - Fuel Pump Intercept	C4302 M/F	C4131
J/P 200 - 914/915 Bus Lines	C4200 M/F	C423 M/F
J/P 201 - O2/CPP/CPK	C4201 M/F	C432
J/P 203 - Switched Power	C4203 M/F	C438
J/P 31 - Cold Start Heater Relay	C4031 M/F	C408

OTHER APPLICABLE ARTICLES: NONE
WARRANTY STATUS: INFORMATION ONLY
OASIS CODES: 203000, 203200, 290000, 490000, 790000

Copyright © 2001 Ford Motor Company