LIGHTOLIER

by (s) ignify

Downlighting

Commercial retrofit Downlight DualSelect

4", 6", 8" & 10" round aperture





The Lightolier Commercial retrofit Downlight DualSelect is an easy to install downlight with adjustable lumen and CCT output switch. This convenient downlight is ideal for retail store, residential and office application.

Project:		
Location:		
Cat.No:		
Туре:		
Notes:		

Fixture example: CR4RLMCCT

Family	Size/Lumens	сст	Voltage	Finish
CR		ССТ		
CR Commercial Retrofit Downlight DualSelect	4RLM 4" Round 500-1000lm, 90CRI, 0-10V Dimming 6RLM 6" Round 700-1500lm, 90CRI, 0-10V Dimming 8RLM 8" Round 1000-2000lm, 90CRI, 0-10V Dimming 10RLM 10" Round 2000-3000lm, 90CRI, 0-10V Dimming	CCT 3000K - 3500K - 4000K	- 120/347V	- White

Features

- 1. Flange: Aluminum white painted with baffle.
- 2. **Power supply:** Integral class 1 driver. (see Electrical section for specifications)
- 3. **Lifetime:** L70 at 50,000 hours and backed with a 5-year warranty (see www.lightolier.com for details).
- 4. **LED board:** Light emitted source.
- 5. **Power connection:** Trim is supplied with quick connect metal conduit with connector inside.
- 6. Dimming: 0-10V Dimming

7. Lumen Selectable: Ability to switch to three different lumen package. Select the desired lumen output using the switch before installation. Lumen output can be changed after installation by un-installing the luminare from the ceiling.

Note: The default setting from Factory is set to the highest lumen value.

8. CCT Selectable: Select the desired CCT using the switch before installation. CCT can be changed after installation by un-installing the luminaire from the ceiling.

Electrical

Electronic power supply: RoHS compliant. Class 1 power unit for use in a dry and damp locations.

Labels

cULus listed. ENERGY STAR®.

Electrical Specs	Nominal Lumens	Input Volts	Input Freq.	Input Current	1	THD Factor		Minimum Operating Temp.	Maximum Operating Temp.		Efficacy @90CRI 3000K
CR4RLMCCT	500lm/700lm/1000lm	120-347V	50/60HZ	102-21mA	5.5/8/12W	<25%@120V	>0.9@120V	-20°C	40°C	IC	80lm/W
CR6RLMCCT	700lm/1000lm/1500lm	120-347V	50/60HZ	147-26mA	7/10/17W	<25%@120V	>0.9@120V	-20°C	40°C	IC	85lm/W
CR8RLMCCT	1000lm/1500lm/2000lm	120-347V	50/60HZ	174-36mA	10/15/21W	<25%@120V	>0.9@120V	-20°C	40°C	IC	90lm/W
CR10RLMCCT	2000lm/2500lm/3000lm	120-347V	50/60HZ	264-65mA	20/25/32W	<25%@120V	>0.9@120V	-20°C	40°C	NON-IC	90lm/W

Compatibility

	Frame Aperture Range				
Series	Minimum	Maximum			
4" Comm Retrofit	Ø4.0'' (Ø102mm)	Ø5.1'' (Ø130mm)			
6" Comm Retrofit	Ø6.3'' (Ø159mm)	Ø7.5'' (Ø190mm)			
8" Comm Retrofit	Ø7.9'' (Ø200mm)	Ø9.4'' (Ø240mm)			
9.5" Comm Retrofit	Ø9.0" (Ø229mm)	Ø10.6" (Ø270mm)			









LED Commercial Retrofit Downlight DualSelect

4", 6", 8" & 10" round aperture

Dimensions

Retrofit downlight 4"











Retrofit downlight 6"













Retrofit downlight 8"












Retrofit downlight 10"










LED Commercial Retrofit Downlight DualSelect

4", 6", 8" & 10" round aperture

Photometry

4-inch LED, 1000lm, 90CRI, 3000K



Angle	Mean CP	Lumens
0	523	
5	510	48
10	501	
15	487	137
20	461	
25	425	195
30	382	
35	333	208
40	282	470
45	238	178
50 55	181 135	121
60	96	121
65	66	67
70	50	0,
75	34	36
80	21	
85	8	9
90	0	
	l	l

CR4RLMCCT

Output lumens:	1000 lm	Efficacy:	83.0 lm/w
Spacing Criterion:	1.14	CCT3:	3000K
Input Watts ² :	12.0 W	CRI:	90 min

Single unit data

	Initial center beam foot-candles	Beam dia. (ft)*
5'	21	5.7'
6'	14	6.8'
7'	10	8.0'
8'	8	9.1'
9'	6	10.3'

* Beam diameter is where foot-candles drop to 50% of maximum.

Multiple unit data - RCR 2

Spacing on center	Initial center bear foot-candles	n Watts persq.ft
5'	40.0	0.53
6'	26.0	0.35
7'	19.0	0.25
8'	16.0	0.21
9'	13.0	0.17

38'x38'x10' Room, Workplane 2.5' above floor, 80/50/20% Reflectances


Coefficients of utilization

Ceiling	80%		70%		50%		30%		0%		
Wall	70	50	30	10	50	10	50	10	50	10	0
RCR	Zor	nal ca	vity m	ethod	d – Eff	ectiv	e floo	r refle	ectan	ce = 2	20%
Room Cavity Ratio 0 6 8 2 9 5 7 8 5 1 0	119 111 102 94 87 81 75 70 66 62 58	119 107 95 85 77 70 63 58 53 49	119 103 89 78 69 62 55 50 46 42 38	119 100 84 72 63 56 50 44 40 37 34	116 104 93 84 75 68 62 57 53 49	116 98 83 72 63 55 49 44 40 37 34	111 100 90 81 73 66 61 56 51 48 44	111 95 81 71 62 55 49 44 40 36 33	106 96 87 78 71 65 59 54 50 47	106 92 80 69 61 54 49 44 40 36 33	100 87 76 66 58 52 46 42 38 34 31

Zonal lumens & percentages

Zone	Lumens	%Luminaire	
0-30	381	38.1%	
0-40	589	58.9%	
0-60	887	88.7%	
0-90	1000	100.0%	

6-inch LED, 1500lm, 90CRI, 3000K



Angle	Mean CP	Lumens
0	736	
5	733	70
10	721	
15	701	197
20	674	
25	633	288
30	580	
35	515	
40	444	316
45	369	
50	293	
55	220	278
60	154	
65	98	191
70	64	
75	48	95
80	32	
85	16	16
90	0	

CR6RLMCCT

		1	
Output lumens:	1500 lm	Efficacy:	83.0 lm/w
Spacing Criterion:	1.14	CCT3:	3000K
Input Watts2:	12.0W	CRI:	90 min

Single unit data

	Initial center beam foot-candles	Beam dia. (ft)*
5'	21	5.7'
6'	14	6.8'
7'	10	8.0'
8'	8	9.1'
9'	6	10.3'

* Beam diameter is where foot-candles drop to 50% of maximum.

Multiple unit data - RCR 2

Spacing on center	Initial center beam Watts foot-candles per sq.f.				
5' 6' 7' 8'	40.0 26.0 19.0 16.0	0.53 0.35 0.25 0.21 0.17			

38'x38'x10' Room, Workplane 2.5' above floor, 80/50/20% Reflectances

Coefficients of utilization

Ceiling		80)%		70)%	50)%	30)%	0%
Wall	70	50	30	10	50	10	50	10	50	10	0
RCR	Zoi	Zonal cavity method - Effective floor reflectance = 20						:0%			
Room Cavity Ratio 0 6 8 2 9 9 5 7 8 5 7 0	119 111 102 94 87 81 75 70 66 62 58	119 107 95 85 77 70 63 58 53 49	119 103 89 78 69 62 55 50 46 42 38	119 100 84 72 63 56 50 44 40 37 34	116 104 93 84 75 68 62 57 53 49	116 98 83 72 63 55 49 44 40 37 34	111 100 90 81 73 66 61 56 51 48 44	111 95 81 71 62 55 49 44 40 36 33	106 96 87 78 71 65 59 54 50 47	106 92 80 69 61 54 49 44 40 36 33	100 87 76 66 58 52 46 42 38 34 31

Zonal lumens & percentages

Zone	Lumens	%Luminaire
0-30	381	38.1%
0-40	589	58.9%
0-60	887	88.7%
0-90	1000	100.0%


- 1. Tested using absolute photometry as specified in LM79: IESNA Approved Method for the Electrical and Photometric Measurements of Solid-State Lighting Products.
- 2. Wattage: controlled to within 5%
- 3. Correlated Color Temperature: within specs as defined in ANSI_NEMA_ANSLG C78.377-2008: Specifications for the Chromaticity of Solid State Lighting Products.

LED Commercial Retrofit Downlight DualSelect

4", 6", 8" & 10" round aperture

Photometry - continued

8-inch LED, 2000lm, 90CRI, 3000K



Angle	Mean CP	Lumens
0	977	
5	972	92
10	957	
15	930	261
20	893	000
25 30	845 777	386
35	692	429
40	596	429
45	492	376
50	386	0,0
55	295	254
60	192	
65	116	121
70	57	
75	60	60
80	38	
85	20	21
90	0	

CR8RLMCCT

Output lumens:		Efficacy:	90.9 lm/w
Spacing Criterion:	1.2		3000K
Input Watts ² :	22.0 W	CRI:	90 min

Single unit data

	Initial center beam foot-candles	Beam dia. (ft)*
5' 6' 7' 8' 9'	39 27 20 15	6.0' 7.2' 8.4' 9.6' 10.8'

* Beam diameter is where foot-candles drop to 50% of maximum.

Multiple unit data - RCR 2

Spacing on center	Initial center beam Watts foot-candles per sq.f			
5'	67.0	0.98		
6'	44.0	0.64		
7'	32.0	0.46		
8'	26.0	0.38		
9'	20.0	0.30		

38'x38'x10' Room, Workplane 2.5' above floor, 80/50/20% Reflectances

Coefficients of utilization

Ceiling		80)%		70)%	50	1%	30)%	0%
Wall	70	50	30	10	50	10	50	10	50	10	0
RCR	Zona	al cav	ity me	ethod	- Eff	ectiv	e floc	r refl	lecta	nce =	20%
Room Cavity Ratio 0 6 8 2 9 9 7 8 7 0 0 1 0 0 1 0 0 1 0 0 0 0 0 0 0 0 0 0	119 111 102 94 87 81 75 70 66 62 58	119 107 95 85 77 70 63 58 53 49	119 103 89 78 69 62 55 50 46 42 38	119 100 84 72 63 56 50 44 40 37 34	116 104 93 84 75 68 62 57 53 49 45	116 98 83 72 63 55 49 44 40 37 34	111 100 90 81 73 66 61 56 51 48	111 95 81 71 62 55 49 44 40 36 33	106 96 87 78 71 65 59 54 50 47	106 92 80 69 61 54 49 44 40 36 33	100 87 76 66 58 52 46 42 38 34 31

Zonal lumens & percentages

Zone	Lumens	%Luminaire
0-30	740	37.0%
0-40	1169	58.5%
0-60	1799	90.0%
0-90	2000	100.0%

9.5-inch LED, 3000lm, 90CRI, 3000K

Candela Curve

700

1050

1400

	Angle	Mean CP	Lumens
	0	1442	
	5	1436	136
/	10	1409	
. /	15	1370	386
\times	20	1317	
	25	1250	573
/	30	1156	
	35	1034	643
	40	894	
	45	742	572
	50	584	
	55	431	391
	60	290	
	65	173	182
	70	107	
	75	81	87
	80	55	
	85	29	30
	90	0	

CR10RLMCCT

Output lumens:	3000 lm	Efficacy:	93.8 lm/w
Spacing Criterion:		CCT3:	3000K
Input Watts ² :	32.0 W	CRI:	90 min

Single unit data

	Initial center beam foot-candles	Beam dia. (ft)*
5'	58	6.0'
6'	40	7.2'
7'	29	8.4'
8'	23	9.6'
9'	18	10.8'

* Beam diameter is where foot-candles drop to 50% of maximum.

Multiple unit data - RCR 2

Spacing on center	Initial center bear foot-candles	
5'	94.0	1.42
6'	62.0	0.93
7'	44.0	0.66
8'	37.0	0.55
9'	29.0	0.44

38'x38'x10' Room, Workplane 2.5' above floor, 80/50/20% Reflectances

Coefficients of utilization

Ceiling		80%		70%		50%		30%		0%		
Wal		70	50	30	10	50	10	50	10	50	10	0
RCR Zonal cavity method - Effective floor reflectance				nce =	20%							
Room Cavity Ratio	0 1 2 3 4 5 6 7 8 9	119 111 102 94 87 81 75 70 66 62 58	119 107 95 85 77 70 63 58 53 49	119 103 89 78 69 62 55 50 46 42 38	119 100 84 72 63 56 50 44 40 37 34	116 104 93 84 75 68 62 57 53 49	116 98 83 72 63 55 49 44 40 37 34	111 100 90 81 73 66 61 56 51 48	111 95 81 71 62 55 49 44 40 36 33	106 96 87 78 71 65 59 54 50 47 43	106 92 80 69 61 54 49 44 40 36 33	100 88 76 66 58 52 46 42 38 34 31

Zonal lumens & percentages

Zone	Lumens	%Luminaire
0-30	1095	36.5%
0-40	1738	57.9%
0-60	2701	90.0%
0-90	3000	100.0%

- 1. Tested using absolute photometry as specified in LM79: IESNA Approved Method for the Electrical and Photometric Measurements of Solid-State Lighting Products.
- 2. Wattage: controlled to within 5%
- 3. Correlated Color Temperature: within specs as defined in ANSI_NEMA_ANSLG C78.377-2008: Specifications for the Chromaticity of Solid State Lighting Products.



© 2020 Signify Holding. All rights reserved. The information provided herein is subject to change, without notice. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify.

Signify North America Corporation 200 Franklin Square Drive, Somerset, NJ 08873 Telephone 855-486-2216 ignify Canada Ltd. 81 Hillmount Road, larkham, ON, Canada L6C 2S3 elephone 800-668-9008

All trademarks are owned by Signify Holding or their respective owners.