

CUBOT

SERVICE MANUAL

CUBOT ONE

CONTENTS



1. GENERAL SPECIFICATION

2. GSM TX POWER CLASS

3. REPORTED SAR

4. MAIN FUNCTION

Notice: All functionality, features, specifications and other product information provided in this document including, but not limited to, the benefits, design, pricing, components, performance, availability, and capabilities of the product are subject to change without notice or obligation. Cubot reserves the right to make changes to this document and the product described herein, at anytime, without obligation on Cubot to provide notification of such change.

General Specification

Technical Parameters	GSM 850	EGSM 900	DCS 1800	PCS 1900	WCDMA 2100	WCDMA 850
Frequency Band [Mhz] Uplink/Downlink	824 ~ 849	880 ~ 915	1710 ~ 1785	1850 ~ 1910	1922 ~ 1977	824 ~ 849
	869 ~ 894	925 ~ 960	1805 ~ 1880	1930 ~ 1990	2112 ~ 2167	869 ~ 894
ARFCN Range	128 ~ 251	0 ~ 124 & 975 ~ 1023	512 ~ 885	512 ~ 810	UL: 9612 ~ 9888	UL: 4132 ~ 4233
					DL: 10562 ~ 10838	DL: 4357 ~ 4458
Tx/Rx Spacing	45 Mhz	45 Mhz	95 Mhz	80 Mhz	190 Mhz	45 Mhz
Mod. Bit Rate/Bit Period	270.833 kbps	270.833 kbps	270.833 kbps	270.833 kbps	3.84 Mcps	3.84 Mcps
	3.692 us	3.692 us	3.692 us	3.692 us		
Time Slot Period/Frame Period	576.9 us	576.9 us	576.9 us	576.9 us	FrameLength: 10ms	FrameLength: 10ms
	4.615 ms	4.615 ms	4.615 ms	4.615 ms	Slotlength: 0.667ms	Slotlength: 0.667ms
Modulation	0.3 GMSK	0.3 GMSK	0.3 GMSK	0.3 GMSK	QPSKHQPSK	QPSKHQPSK
MS Power	33 dBm ~ 5 dBm	33 dBm ~ 5 dBm	33 dBm ~ 5 dBm	33 dBm ~ 5 dBm	24 dBm ~ -50 dBm	24 dBm ~ -50 dBm
Power Class	5 pcl ~ 19 pcl	5 pcl ~ 19 pcl	0 pcl ~ 15 pcl	0 pcl ~ 15 pcl	3(max+ 24dBm)	3(max+ 24dBm)
Sensitivity	- 102 dBm	- 102 dBm	- 100 dBm	- 100 dBm	- 106.7 dBm	- 106.7 dBm
TDMA Mux	8	8	8	8	8	8
Cell Radius	35 Km	35 Km	2 Km	2 Km	2 Km	2 Km

Confidential and proprietary-the contents in this service guide subject to change without prior notice.

Distribution, transmission, or infringement of any content or data from this document without CUBOT's written authorization is strictly prohibited.

A-LINK TELECOM INTERNATIONAL CO., LIMITED
 SHENZHEN HUA FURUI TECHNOLOGY CO., LIMITED
 Email: support@a-link.com, support@cubot.com

GSM Tx Power Class

Tx Power Control	GSM 850	Tx Power Control	EGSM 900	Tx Power Control	DCS 1800	Tx Power Control	PCS 1900
5	33 ± 2 dBm	5	33 ± 2 dBm	0	30 ± 3 dBm	0	30 ± 3 dBm
6	31 ± 2 dBm	6	31 ± 2 dBm	1	28 ± 3 dBm	1	28 ± 3 dBm
7	29 ± 2 dBm	7	29 ± 2 dBm	2	26 ± 3 dBm	2	26 ± 3 dBm
8	27 ± 2 dBm	8	27 ± 2 dBm	3	24 ± 3 dBm	3	24 ± 3 dBm
9	25 ± 2 dBm	9	25 ± 2 dBm	4	22 ± 3 dBm	4	22 ± 3 dBm
10	23 ± 2 dBm	10	23 ± 2 dBm	5	20 ± 3 dBm	5	20 ± 3 dBm
11	21 ± 2 dBm	11	21 ± 2 dBm	6	18 ± 3 dBm	6	18 ± 3 dBm
12	19 ± 2 dBm	12	19 ± 2 dBm	7	16 ± 3 dBm	7	16 ± 3 dBm
13	17 ± 2 dBm	13	17 ± 2 dBm	8	14 ± 3 dBm	8	14 ± 3 dBm
14	15 ± 2 dBm	14	15 ± 2 dBm	9	12 ± 4 dBm	9	12 ± 4 dBm
15	13 ± 2 dBm	15	13 ± 2 dBm	10	10 ± 4 dBm	10	10 ± 4 dBm
16	11 ± 3 dBm	16	11 ± 3 dBm	11	8 ± 4 dBm	11	8 ± 4 dBm
17	9 ± 3 dBm	17	9 ± 3 dBm	12	6 ± 4 dBm	12	6 ± 4 dBm
18	7 ± 3 dBm	18	7 ± 3 dBm	13	4 ± 4 dBm	13	4 ± 4 dBm
19	5 ± 3 dBm	19	5 ± 3 dBm	14	2 ± 5 dBm	14	2 ± 5 dBm
				15	0 ± 5 dBm	15	0 ± 5 dBm

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without CUBOT's written authorization is strictly prohibited.

A-LINK TELECOM INTERNATIONAL CO., LIMITED
SHENZHEN HUA FURUI TECHNOLOGY CO., LIMITED
Email: support@a-link.com, support@cubot.com

Reported SAR

WCDMA/GSM/EDGE	WLAN
The highest reported SAR values are:	The highest reported SAR values are:
• Head: 0.36 W/kg	• Head: 0.19 W/kg
• Body-worn accessory: 0.78 W/kg	• Body-worn accessory: 0.12 W/kg
• Product Specific Use: 0.90 W/kg	• Product Specific Use: 0.11 W/kg

Main Function

Processor Mediatek Strong Quad-Core Cortex-A7 MT6589 (1.2 GHz)
4.7 inch high-end IPS retina screen
1GB RAM + 8GB ROM
Dual cards dual stay
Cameras: <ul style="list-style-type: none">▫ 13 Mega pixels Auto-Focus Rear Camera with Flashlight▫ 5 Mega pixels Front Camera (able to video chat)

Confidential and proprietary-the contents in this service guide subject to change without prior notice.
Distribution, transmission, or infringement of any content or data from this document without CUBOT's written authorization is strictly prohibited.