

Product data sheet

Specifications



APC Smart-UPS Step-Down Transformer, 5kVA, rackmount, 2U, 12x NEMA 5-20R outlets

SRT5KRMTF

Product availability : Stock - Normally stocked in distribution facility

Overview

Lead time	Usually in Stock
-----------	------------------

Main

Main Input Voltage	208 V
Main Output Voltage	120 V
Input Connection Type	NEMA L6-30P
Number of rack unit	2U
Number of cables	1
Provided Equipment	Mounting Hardware Rack Mounting brackets User Manual Warranty card

Physical

Color	Black
Height	3.50 in (8.9 cm)
Width	17.01 in (43.2 cm)
Depth	25.08 in (63.7 cm)
Product Weight	95.00 lb(US) (43.09 kg)
Mounting Location	Front
Mounting preference	No preference
Mounting Mode	Rack-mounted
Mounting position	Horizontal

Input

Max line current	24 A
Input current limits	30 A
Load Capacity	5000 VA

Output

Maximum Total Current Draw per Phase	24 A
--------------------------------------	------

Number of power socket outlets	12
	12 NEMA 5-20R

Conformance

Product Certifications	CSA
Standards	UL 1778

Environmental

Ambient Air Temperature for Operation	32...104 °F (0...40 °C)
Relative Humidity	0...95 % non-condensing
Operating altitude	0...10000 ft
Ambient Air Temperature for Storage	5...113 °F (-15...45 °C)
Storage Relative Humidity	0...95 % non-condensing
Storage altitude	0...50000 ft (0.00...15240.00 m)

Ordering and shipping details

Category	80230-IG SEBA TO SEUSA
Discount Schedule	BMS1
GTIN	731304318866
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	10.00 in (25.4 cm)
Package 1 Width	37.48 in (95.2 cm)
Package 1 Length	24.49 in (62.2 cm)
Package 1 Weight	110.01 lb(US) (49.9 kg)

Offer Sustainability

REACH Regulation	REACH Declaration
EU RoHS Directive	Compliant EU RoHS Declaration
Mercury free	Yes
RoHS exemption information	Yes
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.
Take-back	Take-back program available

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Recommended replacement(s)