

Revised Generation Interconnection System Impact Study Report

For Queue Project Q22-2078

Pagosa 138 kV
March 19, 2024

1. Introduction

This System Impact Study report documents the results of the analyses performed for interconnection request Q22-2078. The Interconnection Customer proposes a 225.3 MW wind facility interconnecting at the Pagosa 138 kV substation in the New Jersey area. The request was received on May 05, 2022. The study evaluated system intact and single contingency conditions using the regional planning case, including 505 higher-queued active requests and their assigned network upgrades.

2. Summary of Results

The project was found to contribute (DFAX of 5% or greater) to 2 overloaded facilities. The total estimated cost of the network upgrades allocated to this project is \$1,697,000.

3. Network Impacts

3.1 Generator Deliverability and Single Contingency Analysis

Monitored Facility	Contingency	Loading (%)	Rating (MVA)	DFAX (%)
PAGOSA-CLARKSVILLE 138 kV	PAGOSA SUBSTATION-SARPY COUNTY 138 kV line	107.6	200	100.0
CARTER-CLARKSVILLE 138 kV	PAGOSA-SARPY COUNTY 138 kV	104.4	208	100.0

3.2 Multiple Facility Contingency Analysis

No additional overloads were identified for multiple facility contingencies.

3.3 Short Circuit and Stability

Short circuit and stability analyses identified no additional network upgrades.

4. Required Network Upgrades and Cost Estimates

Facility	Required Upgrade	Cost Estimate	Allocation to Project
PAGOSA-CLARKSVILLE 138 kV	Reconductor line	\$672,000	100% (\$672,000)
CARTER-CLARKSVILLE 138 kV	Reconductor line	\$1,025,000	100% (\$1,025,000)
	Total allocated to project		\$1,697,000

This report is a simulated study produced by the gridconstraint research prototype on a public synthetic-but-realistic PJM-footprint case; it is not a PJM document.