SLIM3 / SLIM3 PC

PRO L

MAINTENANCE DRAWING - CE

Document No: V090i-C1E-Y04

Edition No.: D

MAKINO

MAKINO ASIA PTE LTD

Drawing Number - V090i-C1E-Y04

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
				=
CIRCUIT DRAWING	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No.
				--

HISTORY OF MODIFICATIONS

EDITION NO.	DATE	DRAWING UPDATE RELEASE NO.	CONTENT	DRAWING NO.	REMARKS	PREPARED BY
A	22-06-2009	MV09-0596	FIRST RELEASE	V090i-C1E-Y01	——	TAI KENG SONG
B	05-05-2011	MV09-0903	SECOND RELEASE (2009 CE)	V090i-C1E-Y02	——	PRAVEEN B
C	12-08-2011	MV09-0975 (NOT RELEASED)	THIRD RELEASE: - UPDATE OF FIXTURE SCHEMATIC	V090i-C1E-Y03	——	PRAVEEN B
D	05-09-2012	MV09-1070	FOURTH RELEASE: - UPDATE OF FIXTURE SCHEMATIC(STD/APC) - UPDATE OF APC CONTROL CIRCUIT - UPDATE A/B AXIS CIRCUIT FOR APC M/C - UPDATE OF LIGHT CURTAIN - UPDATE OF TWO HAND PB CONTROLS - UPDATE OF SURGE SUPPRESSOR FOR MCSP1, MCSP2 & MCC	V090i-C1E-Y04	——	PRAVEEN B

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HISTORY OF MODIFICATIONS	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. A01

DRAWING CROSS REFERENCE:

1.FORMAT:

C01/C05

- ZONE NO.
- PAGE NO.

2.ZONE NO. REFERENCE

C 05

- VERTICAL (DWG SHEET)
- HORIZONTAL (DWG SHEET)

3.PAGE NO. REFERENCE

C 01

- PAGE NO. UNDER PARTICULAR GROUP
- GROUP NO.
  - A-HISTORY OF MODIFICATIONS
  - B-CONTENTS
  - C-CIRCUIT DRAWINGS
  - D-TERMINAL DRAWINGS
  - E-CONNECTOR TABLE
  - F-DI/DO ADDRESS TABLE
  - G-MACHINE INTERCONNECTION
  - H-LAYOUT,PARTS LIST

4.DRAWING REFERENCE:

V090i-C1E-XAA

- RUNNING NO.
- X=STD;
- ENGLISH
- 1 = STD M/C and APC M/C;
- CIRCUIT DRAWING
- CONTROLLER TYPE
- SLIM M/C
- VERTICAL M/C

COMMENT FIELD

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
GENERAL	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. B01

Table of Contents

PAGE NO.	PAGE DESCRIPTION
--	CIRCUIT DRAWING
A01	HISTORY OF MODIFICATIONS
B01	GENERAL
B02	Table of contents: (-- - C21)
B03	Table of contents: (C22 - C51)
B04	Table of contents: (C52 - C81)
B05	Table of contents: (C82 - E08)
B06	Table of contents: (E09 - H12)
C01	INPUT POWER SOURCE
C02	EXPORT TRANSFORMER (OPT)
C03	POWER SOURCE
C04	CONTROL POWER SOURCE
C05	POWER SUPPLY MODULE
C06	SPINDLE AMPLIFIER MODULE (15K)
C07	HIGH TORQUE SPINDLE (8K)
C08	SPINDLE AMPLIFIER MODULE (HSK-A40)
C09	SERVO AMPLIFIER CONNECTION (STD)
C10	SERVO AMPLIFIER CONNECTION (OPT)
C11	SERVO AMPLIFIER CONNECTION (OPT)
C12	ATC BETA AMPLIFIER MODULE (OPT)
C13	FEEDBACK SCALE (OPT)
C14	X AND Y SERVO AMPLIFIER MODULE
C15	Z AND C SERVO AMPLIFIER MODULE
C16	A SERVO AMPLIFIER MODULE (OPT)
C17	B SERVO AMPLIFIER MODULE (OPT)
C18	B AND Z SERVO AMPLIFIER MODULE (OPT)
C19	Z AXIS MOTOR BRAKE
C20	CONTROLLER UNIT
C21	I/O LINK CONNECTION (STD M/C)

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
Table of contents: (-- - C21)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. B02

Table of Contents

PAGE NO.	PAGE DESCRIPTION
C22	I/O LINK CONNECTION (APC M/C)
C23	COOLANT PUMP
C24	THRU SPDL COOLANT 1.5MPa (OPT)
C25	THRU SPDL COOLANT SIGNAL 1.5MPa (OPT)
C26	THRU SPINDLE COOLANT SIGNAL (OPT)
C27	COOLANT LEVEL SENSOR (OPT)
C28	THRU SPDL COOLANT 3MPa (OPT)
C29	THRU SPDL COOLANT SIGNAL 3MPa (OPT)
C30	TRANSFER PUMP & COOLANT CHILLER (OPT)
C31	TRANSFER PUMP FOR LUCC & CHILLER (OPT)
C32	LIFT UP CHIP CONVEYOR (OPT)
C33	CONTROL VOLTAGE SOURCE
C34	NC POWER ON CONTROL
C35	EMERGENCY CIRCUIT
C36	CB OVERLOAD CONTROL
C37	SPINDLE SWITCHING CONTROL
C38	SPINDLE TEMPERATURE CONTROLLER
C39	HSK TOOL SEAT CHECK (HSK-A50)
C40	TOOL CLAMP/UNCLAMP
C41	HSK TOOL SEAT CHECK (HSK-A40)
C42	POWER PACK CONTROL
C43	LS REFERENCE AND OVERTRAVEL
C44	SPINDLE TAPER CLEAN AIR
C45	COOLANT (OPT)
C46	MACHINE LIGHT
C47	NOZZLE COOLANT
C48	ADDITIONAL A AXIS (OPT)
C49	ADDITIONAL B AXIS (OPT)
C50	ADDITIONAL A AXIS PALLET 1 (APC M/C)(OPT)
C51	ADDITIONAL B AXIS PALLET 2 (APC M/C)(OPT)

Table of Contents

PAGE NO.	PAGE DESCRIPTION
C52	AWM-MARPOSS (OPT)
C53	ATLM-RENISHAW TOUCH PROBE (OPT)
C54	AWM-RENISHAW MP10 (OPT)
C55	ATLM-BLUM Z-NANO TYPE (OPT)
C56	ATLM-BLUM Z-NANO TYPE (OPT)
C57	S/G DOOR ITLK WITH LOCK
C58	APC STOCKER DOOR INTLK W/LOCK
C59	AIR BLOW (OPT)
C60	MAIN OPERATION PANEL(24V FOR I/O MODULE)
C61	MODE SELECTION, FLEXIBLE SWITCHES
C62	MODE SELECTION, FLEXIBLE SWITCHES
C63	MODE SELECTION, FLEXIBLE SWITCHES
C64	MODE SELECTION, FLEXIBLE SWITCHES
C65	MANUAL PULSE GENERATOR
C66	PORTABLE MANUAL PULSE GENERATOR (OPT)
C67	SIGNAL LIGHT/PATROL LIGHT
C68	ROBOT DR LEFT OR RIGHT (OPT)
C69	ROBOT DR LEFT & RIGHT (OPT)
C70	AUTO DOOR WITH PUSHBUTTON (OPT)
C71	USER M-CODE 1st & 2nd SET (OPT)
C72	USER M-CODE 3rd & 4th SET (OPT)
C73	CUSTOMISED CONTROL (OPT)
C74	AIRCON (OPT)
C75	AIR DRYER (OPT)
C76	TOOL BROKEN SENSOR (OPT)
C77	AUTO GREASE (OPT)
C78	APC CONTROL PANEL (APC M/C)
C79	APC PALLET CONTROL (APC M/C)
C80	APC STOCKER AUTO DOOR(APC)(OPT)
C81	APC CE VOLTAGE CONTROL (APC M/C)

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
Table of contents: (C52 - C81)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. B04

Table of Contents

PAGE NO.	PAGE DESCRIPTION
C82	HYDRAULIC FIXTURE -HYDAC (STD M/C) (OPT)
C83	HYDRAULIC FIXTURE - HYDAC (APC M/C) (OPT)
C84	HYD.FIXT. SOL(1-2 STK)-HYDAC (STD M/C)(OPT)
C85	HYD.FIXT. SOL(3-4 STK)-HYDAC (STD M/C)(OPT)
C86	HYD.FIXT. SOL(1-2 STK)-HYDAC (APC M/C)(OPT)
C87	HYD.FIXT. SOL(3-4 STK)-HYDAC (APC M/C)(OPT)
C88	AIR SEAT CHECK SENSOR (OPT)
C89	HYDRAULIC DISPLAY (OPT)
C90	HYDRAULIC DISPLAY-2ND SET UN/CLAMP (OPT)
C91	TWO HAND PUSHBUTTON - PRE6 (OPT)
C92	TWO HAND PUSHBUTTON (OPT)
C93	OIL MIST COLLECTOR (OPT)
C94	SAFETY LIGHT CURTAIN (OPT)
C95	MODE UNLOCK PUSHBUTTON
C96	ROBOT INTERFACE 16 I/O
C97	PRE1-EMERGENCY CIRCUIT
C98	PRE2-FRONT DOOR LOCK
C99	PRE4-PORTABLE MPG
C100	PRE5 - APC STOCKER DOOR LOCK
C101	PRE6-SAFETY LIGHT CURTAIN
C102	PRE6-TWO HAND PB CONTROLS
D01	TERMINAL BLOCK - MTC
E01	CONNECTOR TABLE - RELAY PCB
E02	CONNECTOR TABLE - RELAY PCB
E03	CONNECTOR TABLE - OPT PCB
E04	CONNECTOR TABLE - OPT PCB
E05	CONNECTOR TABLE - OPT PCB
E06	CONNECTOR TABLE - MTC
E07	CONNECTOR TABLE - MTC
E08	CONNECTOR TABLE - OPR. PANEL

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
Table of contents: (C82 - E08)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. B05


Table of Contents

PAGE NO.	PAGE DESCRIPTION
E09	CONNECTOR TABLE - OPR. PANEL
E10	CONNECTOR TABLE - COOLANT TERMINAL BOX
E11	CONNECTOR TABLE - INTERFACE CONNECTORS
F01	DI/DO ADDRESS TABLE (MACHINE I/O)
F02	DI/DO ADDRESS TABLE (MACHINE I/O)
F03	DI/DO ADDRESS TABLE (MACHINE I/O)
F04	DI/DO ADDRESS TABLE (MACHINE I/O)
F05	DI/DO ADDRESS TABLE (MACHINE I/O)
F06	DI/DO ADDRESS TABLE (MACHINE I/O)
F07	DI/DO ADDRESS TABLE (MACHINE I/O)
F08	DI/DO ADDRESS TABLE (MACHINE I/O)
F09	DI/DO ADDRESS TABLE (OPR. PANEL I/O)
F10	DI/DO ADDRESS TABLE (OPR. PANEL I/O)
G01	MACHINE INTERCONNECTION (STD & APC M/C)
G02	MACHINE INTERCONNECTION (CE M/C)
H01	MTC LAYOUT, PARTS
H02	MTC LAYOUT, PARTS
H03	MTC LAYOUT, PARTS
H04	OPERATOR PANEL LAYOUT, PARTS
H05	RELAY PCB LAYOUT, PARTS
H06	OPERATOR PCB LAYOUT, PARTS
H07	APC PCB LAYOUT, PARTS
H08	HYDRAULIC PCB LAYOUT, PARTS
H09	CE PCB LAYOUT, PARTS
H10	FIXTURE CONTROL PANEL (STD M/C)(OPT)
H11	APC CONTROL PANEL (APC)
H12	APC W/FIXTURE CONTROL PANEL(APC)(OPT)

Revisions		Date	Name
④			
③	APPROVED	14-AUG-2012	GOH WILLIAM
②	CHECKED	14-AUG-2012	XING JY
①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
Table of contents: (E09 - H12)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. B06




3PH AC SOURCE	MTC LIGHT CONTROL	CB0 POWER, TRIP CONTROL	


Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
				=
INPUT POWER SOURCE	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C01



STANDARD (FOR 200V 3PH SUPPLY,DIRECTLY CONNECT R0,S0,T0 TO TB9000)



OPTION (FOR SUPPLY OTHER THAN 200V, 3PH)




MTC DOOR INTERLOCK	EXPORT TRANSFORMER POWER	

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
EXPORT TRANSFORMER (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C02



C23-B03	COOLANT PUMP
C24-B03	THRU SP/TL COOLANT 1.5MPa (OPT)
C28-A02	THRU SP/TL COOLANT 3MPa (OPT)
C32-A03	LIFT UP CHIP CONVEYOR (OPT)
C38-A02	SPINDLE TEMPERATURE CONTROLLER
C42-B03	POWER PACK CONTROL
C74-B04	AIRCON (OPT)
C91-A03	OIL MIST COLLECTOR (OPT)

POWER SUPPLY MODULE
PSM26i

ACR2


FIXTURE HYD CONTROLS

MAIN POWER DISTRIBUTION

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
POWER SOURCE	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C03




CONTROL POWER DISTRIBUTION

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONTROL POWER SOURCE	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C04



NO		NC	
1 – 2	/B03	C99/A04 22	21
3 – 4	/B03	C98/A05 32	31
5 – 6	/B04		


NOTE: COMMON FOR HSK A50 AND HSK A40

CONTROL SUPPLY	DRIVE CONTROL	POWER SUPPLY	EMERGENCY INTERLOCK	DC BUS	INTERFACE SIGNALS

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
POWER SUPPLY MODULE	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C05




SPINDLE MOTOR POWER - 15000RPM	SPINDLE POSITION SIGNAL	OVER HEAT CONTROL

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SPINDLE AMPLIFIER MODULE (15K)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C06




SPINDLE MOTOR POWER - 8000RPM	SPINDLE POSITION SIGNAL	OVER HEAT CONTROL

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HIGH TORQUE SPINDLE (8K)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C07




SPINDLE MOTOR POWER - 15000RPM	SPINDLE POSITION SIGNAL	OVER HEAT CONTROL

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SPINDLE AMPLIFIER MODULE (HSK-A40)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C08




SERVO AMPLIFIER INTERCONNECTIONS - STANDARD

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SERVO AMPLIFIER CONNECTION (STD)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C09




SERVO AMPLIFIER INTERCONNECTIONS - OPTION

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SERVO AMPLIFIER CONNECTION (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C10




SERVO AMPLIFIER INTERCONNECTIONS - OPTION

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SERVO AMPLIFIER CONNECTION (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C11




NOTE
1) VALID FOR M/Cs WITH BETA AMP FOR ATC

ATC AXIS MOTOR POWER	ATC AXIS MOTOR SIGNAL	

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ATC BETA AMPLIFIER MODULE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C12



FEED BACK SCALE CONNECTION


Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
FEEDBACK SCALE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C13

SVM 2: 80/160

SVM X/Y
X/Y AXIS
SERVO AMPLIFIER MODULE




X AXIS MOTOR POWER	X AXIS MOTOR SIGNAL	Y AXIS MOTOR POWER	Y AXIS MOTOR SIGNAL

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
X AND Y SERVO AMPLIFIER MODULE				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C14




ATC AXIS MOTOR POWER	ATC AXIS MOTOR SIGNAL	Z AXIS MOTOR POWER	Z AXIS MOTOR SIGNAL

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
Z AND C SERVO AMPLIFIER MODULE	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C15




A AXIS MOTOR POWER

A AXIS MOTOR SIGNAL

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
A SERVO AMPLIFIER MODULE (OPT)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C16



B AXIS MOTOR POWER | B AXIS MOTOR SIGNAL


Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
B SERVO AMPLIFIER MODULE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C17

SVM 2: 40/80

SVM B/Z
B/Z AXIS
SERVO AMPLIFIER MODULE




B AXIS MOTOR POWER	B AXIS MOTOR SIGNAL	Z AXIS MOTOR POWER	Z AXIS MOTOR SIGNAL

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
B AND Z SERVO AMPLIFIER MODULE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C18




SERVO READY	Z-AXIS MOTOR BRAKE CONTROL		Z AXIS MOTOR BRAKE

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
Z AXIS MOTOR BRAKE	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C19




FS0i-MC CNC CONTROLLER

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONTROLLER UNIT	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C20




I/O MODULE POWER,LINK CONNECTION

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
I/O LINK CONNECTION (STD M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C21




I/O MODULE POWER,LINK CONNECTION

Revisions		Date	Name
④			
③	APPROVED	14-AUG-2012	GOH WILLIAM
②	CHECKED	14-AUG-2012	XING JY
①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
I/O LINK CONNECTION (APC M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C22




COOLANT CONTROL	WORK WASH GUN SOLENOID	COOLANT PUMP POWER	COOLANT THERMAL ALARM

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
COOLANT PUMP	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C23



THRU SPINDLE COOLANT CONTROL


THRU SPINDLE COOLANT PUMP POWER 1.5 Mpa

THRU SPINDLE COOLANT THERMAL ALARM

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
THRU SPDL COOLANT 1.5MPa (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C24




TSC COOLANT LEVEL LOW	TSC FLOW SWITCH

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
THRU SPDL COOLANT SIGNAL 1.5MPa (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C25




ROTARY UNION BACKUP AIR	COOLANT DRAWBACK ON	COOLANT DRAWBACK OFF		ROTARY UNION WEAR & TEAR	

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
THRU SPINDLE COOLANT SIGNAL (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C26




NOTE: HIGH & LOW LEVEL SENSOR IS AVAILABLE AS OPTION

COOLANT LEVEL SENSOR
LOW HIGH

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
COOLANT LEVEL SENSOR (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C27



THRU SPINDLE COOLANT CONTROL


THRU SPINDLE COOLANT PUMP POWER 3 Mpa

THRU SPINDLE COOLANT THERMAL ALARM

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
THRU SPDL COOLANT 3MPa (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C28




ROTARY UNION WEAR & TEAR	TSC COOLANT LEVEL LOW	TSC FLOW SWITCH	TSC SUCTION FILTER CLOG


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
THRU SPDL COOLANT SIGNAL 3MPa (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C29

NOTE:
THIS PAGE IS APPLICABLE ONLY FOR,
1. TRANSFER PUMP MTR 1-7/7 CAN BE USED FOR EITHER COOLANT CHILLER OPTION (OR) CHIP CONVEYOR OPTION.








TH65 SETTING VALUE	
220V/50HZ	1.42A
200V/50HZ	1.6A

NO	NC
13–14 /B02	
13–14 C31/B02	

NO	NC
1–2 /C03	
1–2 C31/B03	
3–4 /C03	
3–4 C31/B04	
5–6 /C03	
5–6 C31/B04	
13–14 /C07	








COOLANT TRANSFER PUMP CONTROL	COOLANT TRANSFER PUMP POWER	COOLANT TRANSFER PUMP THERMAL TRIP	COOLANT CHILLER ALARM	COOLANT CHILLER CONTROL


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
TRANSFER PUMP & COOLANT CHILLER (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C30

NOTE:
THIS PAGE IS APPLICABLE ONLY FOR,
1. TRANSFER PUMP MTR 5-5/5 FOR CHILLER+LUCC OPTION TOGETHER







TH65 SETTING VALUE	
220V/50HZ	2.9A
200V/50HZ	3.2A

NO	NC
13 – 14 C30/B02	
13 – 14 /B02	

NO	NC
1 – 2 C30/C03	
1 – 2 /B03	
3 – 4 C30/C03	
3 – 4 /B04	
5 – 6 C30/C03	
5 – 6 /B04	
13 – 14 C30/C07	






TRANSFER PUMP CONTROL | TRANSFER PUMP POWER | TRANSFER PUMP THERMAL ALARM

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
TRANSFER PUMP FOR LUCC & CHILLER (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C31




LIFT UP CHIP CONVEYOR FORWARD CONTROL	LIFT UP CHIP CONVEYOR REVERSE CONTROL	LIFT UP CHIP CONVEYOR MOTOR POWER	BACK WASH MOTOR POWER	LUCC SLIP CONTROL (OPTION)	LUCC THERMAL /COOLANT ALARM	LUCC MANUAL CONTROL	LUCC FORWARD	LUCC REVERSE

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
LIFT UP CHIP CONVEYOR (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C32




110V AC POWER SOCKET | 100V AC SOURCE, DISTRIBUTION | 24VDC SOURCE, DISTRIBUTION

Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONTROL VOLTAGE SOURCE	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C33



PS1 IS A TWO CONTACTS SWITCH
NEXT AUXILLARY CONTACT IS LOCATED
AT PAGE C35/A01

AUTO POWER OFF	OP. I/O MODULE POWER	NC POWER		NC ON CONTROL	


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
NC POWER ON CONTROL	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C34

PS1 IS A 2 CONTACTS SWITCH
NEXT AUXILLARY CONTACT IS
LOCATED AT PAGE C34/E06

NOTE:
FOR CE MACHINES REMOVE EM1 & EM2
RELAY FROM MAIN PCB BOARD




NC ON CONTROL	EMERGENCY SWITCH	EMERGENCY STOP CONTROL	MACHINE ON SIGNAL

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
EMERGENCY CIRCUIT	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C35




INSIDE CABINET PROTECTION TRIP	ASSIST EQUIPMENT POWER LINE BREAKER	EMERGENCY STOP

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CB OVERLOAD CONTROL	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C36




SPINDLE SPEED CONTROL	LOW SPEED SELECTION	HIGH SPEED SELECTION		SPINDLE LOW SPEED CONFIRM	SPINDLE HI SPEED CONFIRM	

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SPINDLE SWITCHING CONTROL	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C37




OILMATIC ON CONTROL	INCOMING POWER	SPINDLE TEMP CONTROLLER ALARM	SPINDLE OIL FLOW CONTROL
		OIL TEMP SENSOR	AMBIENT TEMP SENSOR

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.
SPINDLE TEMPERATURE CONTROLLER	NC TYPE	FS0i-MC	V090i-C1E-Y04

GROUP =
SHEET No. C38




SP.TOOL (HSK TYPE ONLY) SEAT CHECK	SP. TOOL(HSK TYPE ONLY) EXIST CHECK	TOOL CLAMP CONFIRM	TOOL UNCLAMP CONFIRM		AIR PRESSURE LS	MASTER SOL VALVE	SP.TAPER CLEANING AIR CONTROL

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HSK TOOL SEAT CHECK (HSK-A50)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C39



TOOL UNCLAMP CONTROL


TOOL UNCLAMP SOLENOID

Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE
TOOL CLAMP/UNCLAMP

MACHINE TYPE	SLIM3	DRAWING No.	GROUP =
NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C40




SP.TOOL (HSK TYPE ONLY) SEAT CHECK	SP. TOOL(HSK TYPE ONLY) EXIST CHECK	TOOL CLAMP CONFIRM	TOOL UNCLAMP CONFIRM
AIR PRESSURE SWITCH		AIR PRESSURE LS	MASTER SOL VALVE
SP.TAPER CLEANING AIR CONTROL			

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HSK TOOL SEAT CHECK (HSK-A40)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C41




POWER PACK MOTOR ON	POWER PACK PUMP	POWER PACK ALARM	POWER PACK PRESSURE SW	POWER PACK OIL LEVEL LOW	POWER PACK TEMP. ALARM

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
POWER PACK CONTROL	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C42




REFERENCE RETURN SLOWDOWN - X AXIS	OVERTRAVEL X-AXIS	REFERENCE RETURN SLOWDOWN - Y AXIS	OVERTRAVEL Y-AXIS	REFERENCE RETURN SLOWDOWN - Z AXIS	OVERTRAVEL Z-AXIS	EMERGENCY STOP SIGNAL	OT RELEASE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
LS REFERENCE AND OVERTRAVEL	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C43




SPINDLE TAPER CLEAN

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SPINDLE TAPER CLEAN AIR	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C44




SHOWER COOLANT (OPTION)	FIXTURE COOLANT (OPTION)	SPINDLE AIRSEAL	NOZZLE COOLANT AIR PURGE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
COOLANT (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C45




MACHINE LIGHT RELAY

POWER-MACHINE LIGHT

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MACHINE LIGHT	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C46



NO	NC
4 — 3/C04	


NOZZLE COOLANT SOLENOID

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
NOZZLE COOLANT	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C47

NOTE:
THIS PAGE IS APPLICABLE WITH
5AX2MT180250FA NIKKEN UNIT




A AXIS UNCLAMP	A AXIS UNCLAMP SOLENOID	+OT ALARM ON	-OT ALARM ON	EMERGENCY STOP	A AXIS NEGLECT	A AXIS CLAMP	A AXIS UNCLAMP	A AXIS REFERENCE RETURN SLOWDOWN


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ADDITIONAL A AXIS (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C48


NOTE:
THIS PAGE IS APPLICABLE WITH
5AX2MT180250FA NIKKEN UNIT















NOTE: INCASE FOR CLAMP/UNCLAMP CONTROLS FOR 5AX-250FA-RJ3.
REFER TO PAGE C84 FOR DETAILS, USING HYDRAULIC CLAMP/UNCLAMP CONTROLS

B AXIS UNCLAMP SOLENOID		B AXIS CLAMP	B AXIS UNCLAMP	B AXIS REFERENCE RETURN SLOWDOWN

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ADDITIONAL B AXIS (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C49




A AXIS UNCLAMP	A AXIS UNCLAMP SOLENOID	+OT ALARM ON	-OT ALARM ON	EMERGENCY STOP	A AXIS NEGLECT	A AXIS CLAMP	A AXIS UNCLAMP	A AXIS REFERENCE RETURN SLOWDOWN

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ADDITIONAL A AXIS PALLET 1 (APC M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C50




NOTE: INCASE FOR CLAMP/UNCLAMP CONTROLS.
REFER TO PAGE C86 FOR DETAILS, USING HYDRAULIC CLAMP/UNCLAMP CONTROLS

B AXIS UNCLAMP	B AXIS UNCLAMP SOLENOID		B AXIS CLAMP	B AXIS UNCLAMP	B AXIS REFERENCE RETURN SLOWDOWN

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ADDITIONAL B AXIS PALLET 2 (APC M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C51




PROBE POWER ON	PROBE STATUS	ERROR RECEPTION ALARM	BATTERY ERROR

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AWM-MARPOSS (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C52




NOT MEASURING MODE	MEASURING ON	CIRCUIT CHECK	ATLM CONTACT TYPE	ATLM CONTROLS	SKIP

Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ATLM-RENISHAW TOUCH PROBE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C53





PROBE POWER ON	PROBE STATUS	RECEPTION ALARM	BATTERY ERROR

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AWM-RENISHAW MP10 (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C54


PMC-DO (CB150C)
C24HB /A02
C24HB /A01
Y5.0 NMSMD
Y5.1 M32X
Y5.2 M33X
CB150C
MP9052
RELAY PCB
OPTION PCB
NMSMD
M32X
M33X
C24L /B02
C24L /B01
C24L C56/A02
C24L C80/C04
C24H /B02
C24H /B02
M33X C53/B02
MP9038 B7
MP9038 A7
BLSK A2 A1
OPTION PCB
C24L C56/E04
C24L C56/E06
NMSMD C53/B01
M86X
M32X C53/B02
M32X
NMSMD C53/B01
D14
D15
C24HB /C05
C24HB /C04
MP9022 A9 A4 B4 B9 A2 A3
BLSK C56/B03
BLSK C56/B03
GREY
BROWN
WHITE
SKIP
C24H
C24L
Z-NANO TOUCH PROBE
OPTION PCB
MP9052 B1
MP9052 B1
RELAY PCB
CB150A 49
X4.7 SKIP
C24L C64/B04
C24L C57/E07
PMC-DI (CB150A)
NO NC
6 5 C53/B04 C53/B03 3 2
6 5 /B05 /B04 3 2
NO NC
10 2 C53/B04 C53/B03 10 6
10 2 /B04 /B04 10 6
11 7 C53/B05 C53/B06 11 3
NO NC
3 4 C53/C02
3 4 /C02
NO NC
14 11 C53/C04 C56/B05 11 12
14 11 /C04 /C05 11 12
C53/C04 11 12
NO NC
C43/A07 3 2
* APPLICABLE WHEN USING OPTION PCB - E6VS603A800-XX
NOT MEASURING MODE
MEASURING ON
CIRCUIT CHECK
CONTACT TYPE
SKIP
Revisions
④
③ APPROVED 14-AUG-2012 GOH WILLIAM
② CHECKED 14-AUG-2012 XING JY
① DRAWN 14-AUG-2012 PRAVEEN B
MAKINO
MAKINO ASIA PTE LTD
TITLE
ATLM-BLUM Z-NANO TYPE (OPT)
MACHINE TYPE SLIM3
NC TYPE FS0i-MC
DRAWING No. V090i-C1E-Y04
GROUP =
SHEET No. C55



NO		NC	
14	11 C53/C04	/B05	11 12
14	11 C55/C04	C55/C05	11 12
		C53/C04	11 12


* APPLICABLE WHEN NOT USING OPTION PCB - E6VS603A800-XX

CONTACT TYPE	24VDC INPUT VOLTAGE	SKIP

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ATLM-BLUM Z-NANO TYPE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C56




OPERATOR DOOR UNLOCK MODE

S/G FRONT DOOR INTERLOCK

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
S/G DOOR ITLK WITH LOCK	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C57




APC STOCKER DOOR UNLOCK MODE

APC STOCKER DOOR INTERLOCK

Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC STOCKER DOOR INTLK W/LOCK	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C58



NO	NC
12 – 8/A04	


AIR BLOW

AIR BLOW SOLENOID

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AIR BLOW (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C59




FANUC.I/O MODULE POWER

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MAIN OPERATION PANEL(24V FOR I/O MODULE)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C60




EDITOR	MEMORY	MDI	REMOTE	HANDLE	REFERENCE	RAPID	JOG	SINGLE BLOCK	BLOCK SKIP	OPTIONAL STOP	COOLANT ON/OFF	NOZZLE ON/OFF

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MODE SELECTION, FLEXIBLE SWITCHES	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C61



	AIR BLOW	THRU SPDL COOLANT	LAMP 5th AXIS	ALL AXES REFERENCE	SETUP	ONE TOUCH START	ONE TOUCH STOP	X AXIS	Y AXIS	Z AXIS	4TH AXIS	(+)	(-)

Revisions		Date	Name
④			
③	APPROVED	14-AUG-2012	GOH WILLIAM
②	CHECKED	14-AUG-2012	XING JY
①	DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD

TITLE
MODE SELECTION, FLEXIBLE SWITCHES

MACHINE TYPE	SLIM3	DRAWING No.	GROUP =
NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C62

NOTE: SW927 IS LOCATED AT THE BACK SIDE OF THE PCB.
TO ACCESS THIS SW927, THE OPERATOR PANEL HAS TO
BE OPEN INORDER TO GAIN ACCESS

NOTE: PLEASE REFER TO OPERATOR PCB
PAGE H06 FOR MORE DETAILS.




	OT RELEASE	LIGHT ON	MEMORY KEY	S/G DOOR ILK RELEASE	ATC AXIS SELECTION	5th AXIS SELECT	RAPID TRAVERSE OVERRIDE	FEED RATE OVERRIDE

Revisions		Date	Name
④			
③	APPROVED	14-AUG-2012	GOH WILLIAM
②	CHECKED	14-AUG-2012	XING JY
①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MODE SELECTION, FLEXIBLE SWITCHES	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C63




POWER OFF	ALARM RESET	TOOL CLAMP	SPINDLE ON/OFF		FEEDHOLD	CYCLE START		SPAREDI2	SPAREDI3

Revisions		Date	Name
④			
③	APPROVED	14-AUG-2012	GOH WILLIAM
②	CHECKED	14-AUG-2012	XING JY
①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MODE SELECTION, FLEXIBLE SWITCHES	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C64

NOTE: APPLICABLE FOR NON-CE MACHINES




5V PULSE GENERATOR

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MANUAL PULSE GENERATOR				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C65




HANDLE MODE SELECTION	X-AXIS SELECT	Y-AXIS SELECT	Z-AXIS SELECT	A AXIS SELECT	B AXIS SELECT	CS		MULTIPLY X 10	MULTIPLY X 100	5V PULSE GENERATOR

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PORTABLE MANUAL PULSE GENERATOR (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C66




	SIGNAL LIGHT1 BUZZER	SIGNAL LIGHT2	SIGNAL LIGHT3	SIGNAL LIGHT4

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SIGNAL LIGHT/PATROL LIGHT				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C67




NO	NC	NO	NC
4 – 3 /C02		4 – 3 /C02	
4 – 3 C69/C01		4 – 3 C69/C02	

ROBOT DR CLOSE SOLENOID	ROBOT DR OPEN SOLENOID	ROBOT DR CLOSE CONFIRM	ROBOT DR OPEN CONFIRM	PUSHBUTTON ROBOT DR OPEN/CLOSE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ROBOT DR LEFT OR RIGHT (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C68




ROBOT DR CLOSE SOLENOID	ROBOT DR OPEN SOLENOID	ROBOT DR CLOSE CONFIRM	ROBOT DR OPEN CONFIRM	PUSHBUTTON ROBOT DR OPEN/CLOSE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ROBOT DR LEFT & RIGHT (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C69




*VALID FOR ALL MACHINES WITH AUTO DOOR OPTION

	AUTO DOOR OPEN SOLENOID	AUTO DOOR CLOSE SOLENOID		AUTO DOOR OPEN PUSHBUTTON	AUTO DOOR CLOSE PUSHBUTTON		AUTO DOOR LEFT OPEN	AUTO DOOR RIGHT OPEN

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AUTO DOOR WITH PUSHBUTTON (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C70




CUSTOMER MISCELLANEOUS CONTROL - M CODES OUTPUTS

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
USER M-CODE 1st & 2nd SET (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C71





CUSTOMER MISCELLANEOUS CONTROL - M CODES OUTPUTS


Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
USER M-CODE 3rd & 4th SET (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C72








CUSTOMISED CONTROL

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CUSTOMISED CONTROL (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C73




AIRCON CONTROL | INPUT POWER

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AIRCON (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C74




INPUT POWER		AIR DRYER ALARM


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AIR DRYER (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C75



BROKEN TOOL SENSOR - RENISHAW TRS2



BROKEN TOOL SENSOR - OMRON




BROKEN TOOL SENSOR - BLUM Z-NANO TOUCH PROBE

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
TOOL BROKEN SENSOR (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C76




AUTO GREASE MOTOR	PRESSURE SWITCH		PRESSURE SW SIGNAL	


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AUTO GREASE (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C77




* THIS APC PCB POWER SUPPPLY CIRCUIT IS FOR STD MACHINE



* THIS APC PCB POWER SUPPPLY CIRCUIT IS FOR APC MACHINE

NOTE: IF APC MACHINE WITH FIXTURE CONTROLS,
CONNECT WORK WASH GUN PB FROM FIXTURE PCB.
PROTECT PS9704 CONNECTION INSIDE S/G.




*NOTE: THIS PAGE IS APPLICABLE FOR APC MACHINE ONLY


	INPUT VOLTAGE TO APC PCB		APC READY	APC MANUAL SWITCH	APC SIDE FEEDHOLD	WORK WASH ENABLE	


Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC CONTROL PANEL (APC M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C78









*NOTE: THIS PAGE IS APPLICABLE FOR APC MACHINE ONLY


APC ARM DOWN	APC ARM UP	APCARM CCW	APC ARM CW		APC ARM DOWN	APC ARM LIFT	APC ARM CCW	APC ARM CW

Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC PALLET CONTROL (APC M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C79

*VALID FOR APC MACHINES WITH STOCKER AUTO DOOR OPTION




STOCKER AUTO DOOR OPEN SOLENOID	STOCKER AUTO DOOR CLOSE SOLENOID		STOCKER AUTO DOOR OPEN PUSHBUTTON	STOCKER AUTO DOOR CLOSE PUSHBUTTON	STOCKER AUTO DOOR CLOSE CONFIRM	STOCKER AUTO DOOR LEFT OPEN	STOCKER AUTO DOOR RIGHT OPEN	


Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC STOCKER AUTO DOOR(APC)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C80

* THIS PAGE IS APPLICABLE ONLY FOR APC MACHINE WITH FIXTURE CONTROL OPTION





NO	NC
3 — 4/C01	


NO	NC
33 — 34/C04/C05	11 — 12
43 — 44/C06/C05	21 — 22

NO	NC
33 — 34/C05/C04	11 — 12
43 — 44/C05/C06	21 — 22

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC CE VOLTAGE CONTROL (APC M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C81




HYD MOTOR ON/OFF CONTROL		HYD MOTOR PUMP		HYD MOTOR O/L THERMAL ALM	HYD OIL LEVEL FLOAT SWITCH	HYD OIL TEMP SENSOR	HYD MOTOR SYSTEM PRESSURE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYDRAULIC FIXTURE -HYDAC (STD M/C) (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C82




HYD MOTOR ON/OFF CONTROL		HYD MOTOR PUMP		HYD MOTOR O/L THERMAL ALM	HYD OIL LEVEL FLOAT SWITCH	HYD OIL TEMP SENSOR	HYD MOTOR SYSTEM PRESSURE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYDRAULIC FIXTURE - HYDAC (APC M/C) (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C83



NOTE: INCASE FOR CLAMP/UNCLAMP CONTROLS FOR 5AX-250FA-RJ3.
REFER TO PAGE C48 & C49 FOR DETAILS,
SL2605 / PS2605 AND SL2606 / PS2606 ARE USED FOR
TILT AXIS CLAMP / UNCLAMP.

JUMPER SETTING:
STD:
S9 - SHORT 2&3
S10 - SHORT 2&3




SOL FIXTURE CLAMP LINE1	SOL FIXTURE UNCLAMP LINE1		TILT AXIS CLAMP LINE	TILT AXIS UNCLAMP LINE		PRESSURE SWITCH LINE1	PRESSURE SWITCH LINE2	TILT AXIS CLAMP	TILT AXIS UNCLAMP

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYD.FIXT. SOL(1-2 STK)-HYDAC (STD M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C84




SOL FIXTURE UN/CLAMP LINE3	SOL FIXTURE UN/CLAMP LINE4	SOL FIXTURE UN/CLAMP LINE7	SOL FIXTURE UN/CLAMP LINE8
PRESSURE SWITCH LINE3	PRESSURE SWITCH LINE7	PRESSURE SWITCH LINE4	PRESSURE SWITCH LINE8

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYD.FIXT. SOL(3-4 STK)-HYDAC (STD M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C85



SOL FIXTURE UN/CLAMP LINE1	SOL FIXTURE UN/CLAMP LINE2		SOL FIXTURE UN/CLAMP LINE3	SOL FIXTURE UN/CLAMP LINE4		PRESSURE SWITCH LINE1	PRESSURE SWITCH LINE2	PRESSURE SWITCH LINE3


Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYD.FIXT. SOL(1-2 STK)-HYDAC (APC M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C86

NOTE:- INCASE OF APC MACHINE SL2605 & SL2606 IS USED FOR PALLET 1. SL2607 & SL2608 IS USED FOR PALLET 2.

JUMPER SETTING:
STD:
S9 - SHORT 2&3
S10 - SHORT 2&3





NO	NC	NO	NC
4–3 /C01	4–3 /C02		
13–14 C84/C03	13–14 C84/C04		


NO	NC	NO	NC
4–3 /C03	4–3 /C04		
13–14 C85/C03	13–14 C85/C04		

SOL FIXTURE UN/CLAMP LINE5	SOL FIXTURE UN/CLAMP LINE6		SOL FIXTURE UN/CLAMP LINE7	SOL FIXTURE UN/CLAMP LINE8		PRESSURE SWITCH LINE3	PRESSURE SWITCH LINE4

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYD.FIXT. SOL(3-4 STK)-HYDAC (APC M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C87



NOTE:
IN CASE OF STANDARD MACHINE, SL1780 IS STANDARD.
AIRSEAT UP TO 12 UNITS CAN BE INSTALLED

NOTE:
IN CASE OF APC MACHINE, AIRSEAT UP TO 12 UNITS CAN BE INSTALLED.
SL1781 IS A MUST.
PALLET 1, AIRSEATS UP TO 6 UNITS CAN BE INSTALL (AIRSEAT 1, 3, 5, 7, 9 & 11)
PALLET 2, AIRSEATS UP TO 6 UNITS CAN BE INSTALL (AIRSEAT 2, 4, 6, 8, 10 & 12)





AIRSEAT SOLENOID 1	AIRSEAT SOLENOID 1 FOR APC MACHINE	AIRSEAT 1	AIRSEAT 2	AIRSEAT 3	AIRSEAT 4	AIRSEAT 5	AIRSEAT 6	AIRSEAT 7	AIRSEAT 8	AIRSEAT 9	AIRSEAT 10	AIRSEAT 11	AIRSEAT 12


Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
AIR SEAT CHECK SENSOR (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C88









MANUAL MODE LAMP	SEAT CHECK LAMP	SETUP FINISH LAMP	ALARM LAMP	WORK WASH ENABLE LAMP	HYD CLAMP1 LAMP	HYD UNCLAMP1 LAMP		MANUAL MODE SW	AUTO START PB	CLAMP1 PB	UNCLAMP1 PB	AIRSEAT KEY SW	WORK WASH ENABLE PB


Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B


MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYDRAULIC DISPLAY (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C89











HYD CLAMP2 LAMP	HYD UNCLAMP2 LAMP		CLAMP2 PB	UNCLAMP2 PB


Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYDRAULIC DISPLAY-2ND SET UN/CLAMP (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C90

THIS PAGE IS APPLICABLE ONLY IF CE MACHINE WITHOUT LIGHT CURTAIN OPTION

FOR TWO HAND PUSHBUTTON EMG CNTRL
- REMOVE S2 JUMPER FROM 1&2 ON HYDRAULIC PCB.
- REMOVE S10 SHORT FROM RELAY PCB.



NOTE: ONLY VALID WITH HYDRAULIC FIXTURE CONTROL

	TWO HAND PB RIGHT	TWO HAND PB LEFT	EMERGENCY PUSHBUTTON CONTROL	STRIKER SWITCH


Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
TWO HAND PUSHBUTTON - PRE6 (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. C91

THIS PAGE IS APPLICABLE WHEN CE MACHINE WITH LIGHT CURTAIN AND TWO HAND PB CONTROL OPTIONS USED TOGETHER.

FOR TWO HAND PUSHBUTTON EMG CNTRL
- REMOVE S2 JUMPER FROM 1&2 ON HYDRAULIC PCB.
- REMOVE S10 SHORT FROM RELAY PCB.




NOTE: ONLY VALID WITH HYDRAULIC FIXTURE CONTROL

TWO HAND PB RIGHT	TWO HAND PB LEFT		EMERGENCY PUSHBUTTON CONTROL	STRIKER SWITCH

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
TWO HAND PUSHBUTTON (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C92




OIL MIST MOTOR ON	OIL MIST MOTOR	MIST COLLECTOR THERMAL

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
OIL MIST COLLECTOR (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C93




LIGHT CURTAIN SENSOR (KEYENCE SL-V44H)

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
SAFETY LIGHT CURTAIN (OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C94




MAIN OPERATION PANEL
MODE UNLOCK SWITCH

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MODE UNLOCK PUSHBUTTON	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C95



Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
ROBOT INTERFACE 16 I/O	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C96



Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PRE1-EMERGENCY CIRCUIT	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C97



Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PRE2-FRONT DOOR LOCK	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C98




NO		NC
	/B05	/B06
	/B05	
	/B06	
13	C19/D03	
23	C05/B07	
33	C05/C03	

NO		NC
	/C05	/C06
	/C05	
	/C06	
14	C19/D03	
34	C05/C03	
24	C05/B07	

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PRE4-PORTABLE MPG	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C99



NO	NC
/B05	/B06
/B06	
/B06	
33 C96/B06	

NO	NC
/C05	/C06
/C06	
/C06	
34 C96/B06	


NO	NC
33 34 C81/B04	/B04 11 12
43 44 C81/B05	

NO	NC
33 34 C81/B04	/B04 11 12
43 44 C81/B05	

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PRE5 - APC STOCKER DOOR LOCK				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. C100



NO	NC
/B05	/B06
/B06	C102/C06
/B06	
C102/C05	
C102/C06	
C102/C06	

NO	NC
/C05	/C06
/C06	C102/C06
/C06	
C102/C05	
C102/C06	
C102/C06	


NO	NC
23 – 24 C70/B02	/A04 11 – 12
23 – 24 C80/B02	C102/A04 11 – 12
33 – 34 C82/B05	
33 – 34 C81/B04	
43 – 44 C81/B06	

NO	NC
23 – 24 C70/B02	/B04 11 – 12
23 – 24 C80/B02	C102/B04 11 – 12
33 – 34 C82/C05	
33 – 34 C81/B04	
43 – 44 C81/B06	

Revisions		Date	Name
4			
3	APPROVED	14-AUG-2012	GOH WILLIAM
2	CHECKED	14-AUG-2012	XING JY
1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PRE6-SAFETY LIGHT CURTAIN	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C101



NO	NC
C101/B05	C101/B06
C101/B06	/C06
C101/B06	
/C05	
/C06	
/C06	

NO	NC
C101/C05	C101/C06
C101/C06	/C06
C101/C06	
/C05	
/C06	
/C06	

NO	NC
23–24 C70/B02	C101/A04 11–12
23–24 C80/B02	/A04 11–12
33–34 C82/B05	
33–34 C81/B04	
43–44 C81/B06	

NO	NC
23–24 C70/B02	C101/B04 11–12
23–24 C80/B02	/B04 11–12
33–34 C82/C05	
33–34 C81/B04	
43–44 C81/B06	

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
PRE6-TWO HAND PB CONTROLS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. C102

NO. TB9001

CB0/ EXT. TRANS(OPTION)

1	R0/R0B
2	S0/S0B
3	T0/T0B

NO. TB9000

CB0/ EXT. TRANS(OPTION)

1	R0/R0B
2	S0/S0B
3	T0/T0B

NO. TB9010

PFM OPTION

1	R2A	R2A		R2A	R2A
2	R2A	R2A		R2A	R2A
3	S2A	S2A		S2A	S2A
4	S2A	S2A		S2A	S2A
5	T2A	T2A		T2A	T2A
6	T2A	T2A		T2A	T2A
7	R4	R4		R4	R4
8	S4	S4		S4	S4

NO. TB9011

PFM OPTION

1	100H	100H		100H	100H
2	100H	100H		100H	100H
3	100L	100L		100L	100L
4	100L	100L		100L	100L
5	CILK1	CILK1		CILK1	CILK1
6	CILK2	CILK2		CILK2	CILK2

NO. TB9012

1	C24H	C24H		C24H	C24H
2	C24H	C24H		C24H	C24H
3	C24H	C24H		C24H	C24H
4	C24H	C24H		C24H	C24H
5	C24H	C24H		C24H	C24H
6	C24L	C24L		C24L	C24L
7	C24L	C24L		C24L	C24L
8	C24L	C24L		C24L	C24L
9	C24L	C24L		C24L	C24L
10	C24L	C24L		C24L	C24L

NO. TB9050

1	C24HI	26	LS196
2	C24HI	27	LS195
3	C24HI	28	LS191
4	C24HI	29	LS1340
5	C24HI	30	ADOPN
6	C24HI	31	ADCLS
7		32	LDOPN
8	SL1309	33	MS19
9	C24L	34	SL1001
10	C24HB	35	SL1002
11	C24L	36	LDCLS
12	LS04	37	AUGRF
13	CCHAL	38	AUGRR
14	LS03	39	RCHP
15		40	US01-4
16	SL1306B	41	US01-3
17	AIRAL	42	US02-4
18	USi1	43	US02-3
19	USi2		
20	LS2111		
21	AIRB		
22	SL1306A		
23	TH19		
24	LS190		
25	LS912		

NO. TB9013

1	SW296		SW296	SW296
2	LS-NC		LS-NC	LS-NC
3	LS-COM		LS-COM	LS-COM
4	LS-COM		LS-COM	LS-COM

NO. TB232

1	COM1		COM1
2	COM2		COM2
3	AUX-OP		AUX-OP
4	OSSD1		OSSD1
5	OSSD2		OSSD2

NO. TB9021

1	C24L		C24L	C24L
2	C24L		C24L	C24L
3	C24L		C24L	C24L
4	C24L		C24L	C24L
5	C24H		C24H	C24H
6	C24H		C24H	C24H
7	C24H		C24H	C24H
8	C24H		C24H	C24H
9	HWER		HWER	HWER
10	HWER2		HWER2	HWER2
11	E24H		E24H	E24H
12	E24H		E24H	E24H
13	E24H		E24H	E24H
14	E24HS		E24HS	E24HS
15	E24HS		E24HS	E24HS
16	CP-11		CP-11	CP-11
17	CP-12		CP-12	CP-12

NO. TB9021

1	C24L		C24L	C24L
2	C24L		C24L	C24L
3	C24L		C24L	C24L
4	C24L		C24L	C24L
5	C24H		C24H	C24H
6	C24H		C24H	C24H
7	C24H		C24H	C24H
8	E24H		E24H	E24H
9	E24H		E24H	E24H
10	C24HP1		C24HP1	C24HP1
11	C24HP2		C24HP2	C24HP2
12	CP260		CP260	CP260

AC CONTROL TERMINALS | DC CONTROL TERMINALS | RELAY PCB TERMINAL | MTC OPTION TERMINALS | CE MTC TERMINALS

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
TERMINAL BLOCK - MTC	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. D01

No.	MP9002	Use	EMG-HYD
Type	1-178313-5		

1	S10	2		3	S10

No.	MP9003	Use	EMG-EXT
Type	1-178313-5		

1	S11	2		3	S11

No.	MP9004	Use	EMG-APC
Type	0-178313-5		

1	S8	2		3	S8

No.	MP9005	Use	X-AXIS LS
Type	DMS-9-P-1-M-G E-2-6-F		

1	C24HI	2	C24HI	3	ESP X
4	LSDX	5	OT2X	6	
7		8		9	

No.	MP9006	Use	Y-AXIS LS
Type	DMS-9-P-1-M-G E-2-6-F		

1	C24HI	2	ESP X	3	ESP Y
4	LSDY	5	OT2Y	6	
7		8		9	

No.	MP9007	Use	Z-AXIS LS
Type	DMS-9-P-1-M-G E-2-6-F		

1	C24HI	2	ESP Y	3	ESP Z
4	LSDZ	5	OT2Z	6	
7		8		9	

No.	MP9008	Use	Z-AX BRK
Type	0-178323-2		

B1		B2	C24L	B3	
A1		A2	EM1-5	A3	ZBRK-3

No.	MP9009	Use	HYD. PRESSURE SW
Type	1-178323-2		

B1	C24L	B2	C24L	B3	PS1201
A1	C24HI	A2	SL00-4	A3	

No.	MP9010	Use	OILMATIC CONTROL
Type	DMS-9-S-1-M-G E-2-6-F		

1	C24HI	2	C24HI	3	LS170
4	OMAL	5	C24HB	6	C24L
7	C24HB	8	OMON-4	9	OMON-3

No.	MP9011	Use	PFM INTERFACE.
Type	DMS-9-S-1-M-G E-2-6-F		

1	ZBRK-4	2	EM1-9	3	C24HI
4	TOOLR	5	S1	6	S1
7	S7	8	S7	9	

No.	MP9012	Use	AIR PRESSURE SW
Type	0-178313-5		

1	C24HI	2	C24L	3	LS905

No.	MP9015	Use	OPERATOR PANEL
Type	DMS-25-P-1-M-G E-2-6-F		

1	C24HB	2	C24HB	3	NCON-3	4	C24HB	5	NCON-4
6	EM2-4	7	C24L	8	EM2-4	9	LP1-1	10	C24L
11	C24L	12	EM2-4	13	S6	14	LP1-2	15	C24HI
16	PBSCL	17	C24L	18	PRTC	19	PTL1	20	PTL2
21	PTL3	22		23		24		25	

No.	MP9016	Use	ATC OP.PANEL
Type	DMS-9-S-1-M-G E-2-6-F		

1	C24HI	2	MCSP1	3	MCSP2
4	AUGRPB	5		6	
7		8	S6	9	S6

No.	MP9017	Use	SPINDLE.TL UNCLAMP
Type	DMS-9-S-1-M-G E-2-6-F		

1	LS00	2	LS01	3	LS602
4	LS601	5	C24HI	6	C24HI
7	C24HI	8	C24HI	9	C24L

No.	MP9018	Use	PNEUMATIC SOL
Type	DMS-25-P-1-M-G E-2-6-F		

1	SL2310	2	SL201	3	SL01	4	SL181	5	SL2111
6	SL1306	7	SL1306	8	SL1308	9		10	
11		12		13	C24L	14	SL2311	15	SL202
16	SL6B	17	SL02	18	SL192	19	----	20	
21		22		23		24		25	

No.	MP9019	Use	ATC LS
Type	DMS-25-S-1-M-G E-2-6-F		

1	C24HI	2	C24HI	3	C24L	4	C24L	5	LS202
6	LS201	7		8		9	LS154	10	LS155
11	LS25	12	USDi3	13	USDi4	14	LSDA	15	
16		17		18		19		20	
21		22		23		24		25	

No.	MP9020	Use	4th/5th AXIS
Type	DMS-25-S-1-M-G E-2-6-F		

1	C24HI	2	C24HI	3	LSDA	4	LSDB	5	C24HI
6	C24L	7	LS151	8	LS152	9	OT1A	10	OT2A
11	ANGL-8	12	SL150-4	13	C24L	14	C24HB	15	C24HB
16	MP9020 -17	17	MP9020 -16	18	ESP4	19	ESP5	20	
21		22		23		24		25	

RELAY PCB CONNECTORS

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - RELAY PCB	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. E01

No.	MP9021	Use	LUCC
Type	DMS-25-S-1-M-G E-2-6-F		

1	C24HI	2	C24L	3	TH16	4	LCMAS	5	LCFWD
6	LCREV	7	LSLIP	8		9	MS16F-4	10	MS16F-3
11		12	MS16R-4	13	MS16R-3	14		15	S9
16	S9	17		18	LCMAL	19		20	
21		22		23		24		25	

No.	MP9027	Use	MISC. CTRL
Type	DMS-9-P-1-M-G E-2-6-F		

1	MISC1-8	2	MISC2-8	3	MISC1-4
4	MISC1-6	5	MISC2-5	6	MISC2-4
7	MISC2-3	8	MISC2-6	9	MISC2-5

No.	MP9028	Use	OPTION SOL
Type	DMS-9-S-1-M-G E-2-6-F		

1	SL1306A	2	SL1306-3	3	SL1308-1
4		5		6	----
7	----	8	----	9	

No.	MP9050	Use	C24H/C24L
Type	1-0178323-2		

B1	C24HB	B2	C24L	B3	C24L
A1	C24HA	A2	C24HA	A3	C24HB

No.	MP9051	Use	100H/100L
Type	1-0178323-2		

B1	100L	B2	100L	B3	100H
A1	100L	A2	POUT-4	A3	LGT-4

No.	MP9052	Use	ATLM/AWM
Type	HIF3CB-20PA-2.54D5A		

B1	SKIP	B2	C24L	B3	EM1-8	B4	OTRL	B5	C24L	B6	MSALA	B7	MSALB	B8	C24HB	B9		B10	C24HB	
A1	C24HI	A2		A3	NMSMD	A4	M32X	A5	M33X	A6	OPPON	A7	M34X	A8		A9	C24HB	A10		

No.	MP9053	Use	MTC-GENERAL
Type	MDS-9-P-1-M-G E-2-6-F		

1	US03	2	US04	3	CPTP
4	CB2	5	SPARE I/O	6	
7		8	EM1-6	9	EM1-10

No.	MP9054	Use	MTC-GENERAL
Type	MDS-9-P-1-M-G E-2-6-F		

1	C24HI	2	C24L	3	SPARE I/O
4	TH2	5	TH12	6	
7	MS2	8	SL1308	9	PPMON

No.	MP9055	Use	AUTO DOOR
Type	MDS-9-S-1-M-G E-2-6-F		

1	LS2315	2	LS2311	3	LS2312
4	LS2313	5	LS2314	6	C24HI
7	C24HI	8	C24HI	9	C24HI

No.	MP9056	Use	MTC-GENERAL
Type	1-178313-5		

1	NCON-3	2	C24L	3	

RELAY PCB CONNECTORS

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - RELAY PCB	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. E02

No.	MP9052	Use	ATLM/AWM PCB
Type	HIF3CB-20PA-2.54D5A		

B1	SKIP	B2	C24L	B3	M86X-2	B4	M86X-3	B5	C24L	B6	MSALA	B7	MSALB	B8	C24HB	B9		B10	C24HB
A1	C24HI	A2		A3	NMSMD -8	A4	M32X-14	A5	M33X-8	A6	OPPON -8	A7	M34X-8	A8		A9	C24HB	A10	

No.	MP9023	Use	ATLM/AWM PCB
Type	178327-5		

B1	C24L	B2	C24L	B3	C24L	B4	S1	B5	M32X-8	B6	M32L-2	B7	M34X-4	B8	M34X-3
A1	C24HB	A2	C24HB	A3	C24HB	A4	S1	A5	M34X-5	A6	M32L-4	A7	M32L-3	A8	M34X-2

No.	MP9022	Use	ATLM/AWM PCB
Type	178328-5		

B1	C24L	B2	C24L	B3	OPPON -4	B4	M32X-2	B5	M32X-9	B6	M86X-7	B7	M32X-7	B8	M32X-11	B9	C24HB	B10	MSALB
A1	C24HB	A2	C24HB	A3	C24L	A4	M32X-6	A5	M32X-1	A6	M86X-5	A7	M86X-6	A8	M32X-3	A9	C24HB	A10	MSALA

No.	MP9031	Use	TPC JR
Type	172327-5		

B1	M770-3	B2	M770	B3	M771	B4	M772	B5	M773	B6	TPEMG	B7		B8					
A1	C24H	A2	TAFIN1	A3	TAFIN2	A4	TJALM1	A5	SPARE I/O	A6		A7		A8	C24L				

No.	MP9038	Use	24 ATC
Type	316517-5		

B1	C24L	B2	C24L	B3	C24L	B4	C24L	B5	C24L	B6	C24L	B7	C24L	B8		B9	SL207-8	B10	SL2311 -8
A1	SL51	A2	MS65	A3	SL206-4	A4	SL207-4	A5	SL2310 -4	A6	SL2311 -4	A7	M33X-4	A8	SL206-8	A9		A10	SL2310 -8

No.	MP9039	Use	24 ATC
Type	178327-5		

B1	C24HI	B2	C24HI	B3	C24HI	B4	C24HI	B5	C24HI	B6	C24HI	B7	C24HI	B8	C24HI	B9	C24HI	B10	C24HI
A1	SPARE I/O	A2	TH65	A3	SPARE I/O	A4	SPARE I/O	A5	SPARE I/O	A6	SPARE I/O	A7	SPARE I/O	A8	SPARE I/O	A9	SPARE I/O	A10	SPARE I/O

No.	VMP12	Use	BLUM INTERFACE
Type	MR-50RFD2		

33	C24HI			1	C24HI
34				2	UO01
35				3	UO02
36	LSRCL	19	C24L	4	UO03
37		20	C24L	5	UO04
38		21	C24L	6	UO05
39		22	C24L	7	UO06
40		23	C24L	8	UO07
41		24	C24L	9	UO08
42		25	UI01	10	
43		26	UI02	11	
44		27	UI03	12	
45		28	UI04	13	
46	UI01	29	UI05	14	
47	UI02	30	UI06	15	
48	UI03	31	UI07	16	
49	UI04	32	UI08	17	
50	C24HI			18	C24HI

OPTION PCB CONNECTORS -E6VS603A800-XX

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - OPT PCB	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. E03

No.	VMP70	Use	INPUT 24VDC
Type	177555-5		

A1	C24HI	A2	C24HO	A3	C24HO
B1	C24L	B2	C24L	B3	C24L

No.	VMP71	Use	OPE
Type	MR-25RMD2		

1	C24HI	2	AUT	3	AIRSV	4	HY1CL	5	DOPN
6	DCLS	7	HY1UC	8	LAUTO	9	LMAN	10	SYSPS
11	C24HI	12	C24HI	13	C24L	14	LHY1CL	15	LHY1UCL
16	LAIRS	17	LDOPN	18	LDCLS	19	OP EMG1	20	OP EMG1
21	OP EMG2	22	OP EMG2	23	C24L	24	C24L	25	C24L

No.	VMP72	Use	2HND PB
Type	178327-5		

B1	S1-1	B2	S2-2	B3	STRSW	B4	THPBR	B5	THPBL	B6	AREAS	B7	LMAN	B8	A8
A1	S1-2	A2	S1-1	A3	C24HI	A4	C24HI	A5	C24HI	A6	C24HI	A7	LAUTO	A8	B8

No.	VMP73	Use	EMG
Type	1-178315-5		

1	S1-1	2	S1-3	3	---	4	S2-1	5	S2-3

No.	VMP74	Use	AUT DR
Type	178326-5		

B1	LS2311	B2	LS2312	B3	LS2313	B4	LS2314	B5	C24L	B6	C24L
A1	C24HI	A2	C24HI	A3	S7	A4	S8	A5	SL2310-3	A6	SL2311-3

No.	VMP75	Use	HYD MOT
Type	178328-5		

B1	A4	B2	SYSPS	B3	TH260	B4	MS260	B5	A3	B6	LS2603	B7	LS2604	B8	C24L	B9	A9	B10	LMAN
A1	A8	A2	C24HI	A3	B5	A4	B1	A5	C24HI	A6	C24HI	A7	C24HI	A8	A1	A9	B9	A10	LAUTO

No.	VMP78	Use	SP DI
Type	1-0178317-2		

B1	C24HI	B2	C24HI	B3	C24HI	B4	C24HI	B5	C24HI	B6	C24HI	B7	C24HI	B8	C24HI	B9	C24HI	B10	C24HI
A1	LS1787	A2	LS1788	A3	LS1789	A4	LS1790	A5	LS1791	A6	LS1792	A7	SPDI7	A8	SPDI8	A9	SPDI9	A10	SPDI10

No.	VMP79	Use	SPARE DO
Type	1-0178317-2		

1	RL40-4	2	RL41-4	3	RL40-3	4	RL41-3	5	6	6	5	7	C24L	8	C24L

No.	VMP80	Use	AIRST
Type	178327-5		

B1	C24HI	B2	C24HI	B3	C24HI	B4	C24HI	B5	C24L	B6	C24L	B7	C24L	B8	C24L
A1	LS1781	A2	LS1782	A3	LS1783	A4	LS1784	A5	LS1785	A6	LS1786	A7	LS1787	A8	LS1788

No.	VMP81	Use	AIRST SOL
Type	178326-5		

B1	C24L	B2	C24L	B3	C24L	B4	C24L	B5	C24L	B6	C24L
A1	SL1780-3	A2	SL1781-3	A3	SL1782-3	A4	SL1783-3	A5	RL06-3	A6	RL07-3

OPTION PCB CONNECTORS -E7VS140A101-XX

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - OPT PCB	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. E04

No.	VMP91	Use	AIR SEAT I/P
Type	1-0178317-2		

1	C24HI	2	C24HI	3	PS2601	4	PS2602	5	SL2601 -3	6	SL2602 -3	7	C24L	8	C24L

No.	VMP92	Use	AIR SEAT I/P
Type	1-0178317-2		

1	C24HI	2	C24HI	3	PS2603	4	PS2604	5	SL2603 -3	6	SL2604 -3	7	C24L	8	C24L

No.	VMP93	Use	AIR SEAT I/P
Type	1-0178317-2		

1	C24HI	2	C24HI	3	PS2605	4	PS2606	5	SL2605 -3	6	SL2606 -3	7	C24L	8	C24L

No.	VMP94	Use	AIR SEAT I/P
Type	1-0178317-2		

1	C24HI	2	C24HI	3	PS2607	4	PS2608	5	SL2607 -3	6	SL2608 -3	7	C24L	8	C24L

No.	VMP95	Use	AIR SEAT I/P
Type	1-0178317-2		

1	C24HI	2	C24HI	3	PS2701	4	PS2702	5	SL2701 -3	6	SL2702 -3	7	C24L	8	C24L

No.	VMP96	Use	AIR SEAT I/P
Type	1-0178317-2		

1	C24HI	2	C24HI	3	PS2703	4	PS2704	5	SL2703 -3	6	SL2704 -3	7	C24L	8	C24L

NO.	TB1

1	C24HI
2	C24HI
3	C24HI
4	C24L
5	C24L
6	C24L
7	RL08-3
8	RL09-3
9	LS912

OPTION PCB CONNECTORS -E7VS140A101-XX

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - OPT PCB	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. E05

No.	CB150A	Use	I/O MODULE
Type	MR-50RFD2		

33	C24HB			1	C24HB
34	LDOPN			2	S150
35	MS19			3	LDCLS
36	SL192	19	C24L	4	AUDRF
37	SL1309	20	C24L	5	AUGRR
38	SL2310	21	C24L	6	LCMAL
39	SL2311	22	C24L	7	MS16F
40	SL1001	23	C24L	8	MS16R
41	SL1002	24	C24L	9	RCHP
42	TH19	25	LS151	10	LS1340
43	LS190	26	LS152	11	LS2315
44	LS912	27	LS196	12	ADPON
45	TH16	28	LS195	13	ADCLS
46	LCMAS	29	OT1A	14	LS2311
47	LCFWD	30	OT2A	15	LS2312
48	LCREV	31	DETCHA	16	LS2313
49	SKIP	32	LS191	17	LS2314
50	C24HB			18	C24HB

No.	CB150B	Use	I/O MODULE
Type	MR-50RFD2		

33	C24HB			1	C24HB
34	SL6B			2	SL1306A
35	LGT			3	MS2
36	SL181	19	C24L	4	SL1308
37	SL2111	20	C24L	5	SL02
38	AIRB	21	C24L	6	PRTC
39	US03	22	C24L	7	SL201
40	US01	23	C24L	8	SL202
41	US02	24	C24L	9	US04
42	CPTP	25	TOOLR	10	LSDX
43	CB2	26	SPARE	11	LSDY
44	AIRAL	27	LS2111	12	LSDZ
45	LS202	28	EMI	13	LSDA
46	LS201	29	ESP	14	LS27
47	PBSCL	30	OT2X	15	LSDB
48	USI1	31	OT2Y	16	MSALA
49	USI2	32	OT2Z	17	MSALB
50	C24HB			18	C24HB

No.	CB150C	Use	I/O MODULE
Type	MR-50RFD2		

33	C24HB			1	C24HB
34	POUT			2	NMSMD
35	ZBRK			3	M32X
36	OTRL	19	C24L	4	M33X
37	PPMON	20	C24L	5	OPPON
38	SL1306B	21	C24L	6	M34X
39	OMON	22	C24L	7	PTL1
40	SL01	23	C24L	8	PTL2
41	SL00	24	C24L	9	PTL3
42	LS00	25	SPARE	10	LS154
43	LS01	26	TH2	11	LS155
44	LS602	27	SPARE	12	LS25
45	LS601	28	CCHAL	13	MCSP1
46	LS170	29	LS03	14	MCSP2
47	OMAL	30	LS199	15	AUGRPB
48	LS905	31	TH12	16	USI3
49	LSLIP	32	PS1201	17	USI4
50	C24HB			18	C24HB

RELAY PCB - I/O MODULE CONNECTORS

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - MTC	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. E06

No.	CB150D	Use	I/O MODULE
Type	MR-50RFD2		

33	C24HB			1	C24HB
34	M770			2	UO01
35	M771			3	UO02
36	M772	19	C24L	4	UO03
37	M773	20	C24L	5	UO04
38	TPEMG	21	C24L	6	UO05
39	SL51	22	C24L	7	UO06
40	MS65	23	C24L	8	UO07
41	LSRCL	24	C24L	9	UO08
42	TAFIN1	25	UI01	10	----
43	TAFIN2	26	UI02	11	TH65
44	TJALM1	27	UI03	12	----
45	SPARE	28	UI04	13	----
46	UI01	29	UI05	14	----
47	UI02	30	UI06	15	----
48	UI03	31	UI07	16	----
49	UI04	32	UI08	17	----
50	C24HB			18	C24HB

No.	CB151A	Use	I/O MODULE
Type	MR-50RFD2		

33	C24HB			1	C24HB
34	LHY1CL			2	LHY2CL
35	LHY1UC			3	LHY2UC
36	LAIRS	19	C24L	4	SL2601
37	LMAN	20	C24L	5	SL2602
38	LSETUP	21	C24L	6	SL2603
39	MS260	22	C24L	7	SL2604
40	SL1780	23	C24L	8	LALM
41	SL1781	24	C24L	9	LWWE
42	MAN	25	ASTR	10	PS2601
43	STRSW	26	WWE	11	PS2602
44	AIRSV	27	LS1780	12	PS2603
45	THPBR	28	LS1781	13	PS2604
46	THPBL	29	SYSPS	14	HY2CL
47	AREAS	30	LS2604	15	HY2UC
48	HY1CL	31	LS2603	16	SPARE
49	HY1UC	32	TH260	17	SPARE
50	C24HB			18	C24HB

No.	CB151C	Use	I/O MODULE
Type	MR-50RFD2		

33	P24HA			1	P24HA
34	SL100A			2	PRDY1
35	SL100B			3	PCMAL
36	SL101A	19	C24L	4	PCSPL
37	SL101B	20	C24L	5	PCSCL
38	SPARE	21	C24L	6	SPARE
39	SPARE	22	C24L	7	SPARE
40	SPARE	23	C24L	8	SPARE
41	SPARE	24	C24L	9	SPARE
42	LS100	25	PS2605	10	RDYPB1
43	LS101	26	PS2606	11	PCMAS
44	LS102	27	PS2607	12	*PCSPC
45	LS103	28	PS2608	13	PCSCS
46	SPARE	29	SPARE	14	SPARE
47	SPARE	30	SPARE	15	SPARE
48	SPARE	31	SPARE	16	SPARE
49	SPARE	32	SPARE	17	SPARE
50	P24HA			18	P24HA

No.	CB152A	Use	I/O MODULE
Type	MR-50RFD2		

33	C24H			1	C24H
34	RBO16			2	RBO08
35	RBO15			3	RBO07
36	RBO14	19	C24L	4	RBO06
37	RBO13	20	C24L	5	RBO05
38	RBO12	21	C24L	6	RBO04
39	RBO11	22	C24L	7	RBO03
40	RBO10	23	C24L	8	RBO02
41	RBO09	24	C24L	9	RBO01
42	RBI16	25	RBI08	10	--
43	RBI15	26	RBI07	11	--
44	RBI14	27	RBI06	12	--
45	RBI13	28	RBI05	13	--
46	RBI12	29	RBI04	14	--
47	RBI11	30	RBI03	15	--
48	RBI10	31	RBI02	16	--
49	RBI09	32	RBI01	17	--
50	C24H			18	C24H

No.	CB151B	Use	I/O MODULE
Type	MR-50RFD2		

33	C24HB			1	C24HB
34	SL2605			2	SL2701
35	SL2606			3	SL2702
36	SL2607	19	C24L	4	SL2703
37	SL2608	20	C24L	5	SL2704
38	SL1782	21	C24L	6	SPARE
39	SL1783	22	C24L	7	SPARE
40	SPARE	23	C24L	8	SPARE
41	SPARE	24	C24L	9	SPARE
42	LS1783	25	PS2605	10	PS2701
43	LS1784	26	PS2606	11	PS2702
44	LS1785	27	PS2607	12	PS2703
45	LS1786	28	PS2608	13	PS2704
46	LS1787	29	SPARE	14	SPARE
47	LS1788	30	SPARE	15	SPARE
48	SPARE	31	SPARE	16	SPARE
49	SPARE	32	SPARE	17	SPARE
50	C24HB			18	C24HB

OPTION PCB - I/O MODULE CONNECTORS

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
				=
CONNECTOR TABLE - MTC	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. E07

No.	MP9101	Use	IO POWER
Type	1-178313-5		

1	C24HB	2	C24L	3	

No.	MP9102	Use	LCD POWER
Type	1-178313-5		

1	NCON	2	C24L	3	

No.	MP9105	Use	24V & MTC
Type	MDS-25-P-1-M-G E-2-6-F		

1	C24HB	2	C24H	3	NCON	4	C24HB	5	NCON
6	ENON	7	C24L	8		9	PONL	10	C24L
11	C24L	12	EMG1	13	EMG2	14	PONL	15	SPDI1
16	SPDI1C	17	SPDO1	18	SPDO1C	19	PTL1	20	PTL2
21	PTL3	22		23		24		25	

No.	MP9106	Use	PATROL LGT
Type	MDS-9-P-1-M-G E-2-6-F		

1	C24HB	2	C24HB	3	PLT1-4	4	C24L	5	C24L
6	PTL1-3	7	PTL2-3	8	PTL3-3	9	PTL1-5		

No.	MP9115	Use	TOP PANEL
Type	DMS-25-S-1-M-G E-2-6-F		

1	C24HB	2	C24HB	3	NCON	4	EM2-4	5	EM2
6	LP2	7	KEY1	8	SGIR	9	PWROFF	10	ALRST
11	TUCL	12	SPNONF	13	+24VA2	14	EMG1	15	EMG2
16	LSPSP	17	LTUCL	18	LALRST	19	LPOFF	20	C24L
21	C24L	22	C24L	23	C24L	24		25	

No.	MP9116	Use	BOTTOM PANEL
Type	DMS-25-S-1-M-G E-2-6-F		

1	+24VA2	2	+24VA2	3	AUSP	4	AUST	5	
6		7	FV25	8	FV50	9	FV75	10	FV100
11	FV125	12	FV150	13	+24VA2	14	ROV25	15	ROV50
16	ROV100	17	+24VA2	18	LAUSP	19	LAUST	20	
21		22		23		24		25	

No.	MP9117	Use	SPARE I/O
Type	MDS-15-P-1-M-G E-2-6-F		

1	+24VA2	2	+24VA2	3	SPDI1	4	SPDI1C	5	SPDO1
6	SPDO1C	7	SPARE DI1	8	SPARE DI2	9	SPARE DI3	10	SPARE DO1
11	SPARE D02	12	SPARE D03	13		14	C24L	15	C24L

OPERATOR PANEL PCB CONNECTORS

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - OPR. PANEL	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. E08

No.	CE56A	Use	I/O MODULE1
type	HIFBB-50D-2.54R		

A		B	
1	C24L	1	+24VA1
2	EDIT	2	MEM
3	MDI	3	DNC
4	REF	4	RAPID
5	HND	5	AUTOP
6	SBK	6	BLKSK
7	OPS1	7	COOLON
8	NOZON	8	AIRB
9	TAPR	9	ROV1I
10	ROV2I	10	ROV4I
11	FV1I	11	FV2I
12	FV4I	12	FV8I
13	FV16I	13	FVM
14	DICOM0	14	
15		15	
16	LEDT	16	LMEM
17	LMDI	17	LDNC
18	LREF	18	LRAPID
19	LHND	19	LAUTOP
20	LSBK	20	LBLKSK
21	LOPST	21	LCOOLON
22	LNOZON	22	LAIRB
23	LTAPR	23	SPAREDI1
24	C24HB	24	C24HB
25	C24HB	25	C24HB

No.	CE57A	Use	I/O MODULE1
type	HIFBB-50D-2.54R		

A		B	
1	C24L	1	+24VA2
2	ALLREF	2	SETUP
3	ONET	3	ONETS
4	X AXIS	4	Y AXIS
5	Z AXIS	5	4TH AXIS
6	'+'	6	'-'
7	OTR	7	LIGHT
8	KEY1	8	SGILK
9	ATC	9	SPAREDI1
10	PWROFF	10	ALRST
11	TUCL	11	SPNONF
12	AUSP	12	AUST
13	SPAREDI2	13	SPAREDI3
14		14	DICOM5
15		15	
16	LALLREF	16	LSETUP
17	LONET	17	LONES
18	LXAXIS	18	LYAXIS
19	LZAXIS	19	L4AXIS
20	LPOWOF	20	LALMRST
21	LTOOLUN	21	LSPNONF
22	LAUSP	22	LAUST
23	SPAREDO2	23	SPAREDO3
24	C24HB	24	C24HB
25	C24HB	25	C24HB

CONNECTOR TABLE - OP.PANEL

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
				=
CONNECTOR TABLE - OPR. PANEL	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. E09

No.	MP9060	Use	NOZZLE COOLANT
Type	09200030320 09200032711		

3	T2A		1	R2A
4	E		2	S2A

No.	MP9062	Use	TSC
Type	09300100302 09330102701		

6	C24H		1	C24H
7	LS190		2	LS196
8	R2A		3	C24L
9	S2A		4	C24H
10	T2A		5	LS195

No.	MP9063	Use	HYDRAULIC
Type	09300240302 09330242701		

13	SL2603-1		1	TH(M)-1
14	SL2601-2		2	TH(M)-2
15	SL2604-1		3	LS2603-1
16	SL2604-2		4	LS2603-2
17	PS2601-1		5	LS2604-1
18	PS2601-2		6	LS2604-2
19	PS2602-1		7	SYSPS-1
20	PS2602-2		8	SYSPS-2
21	PS2603-1		9	SL2601-1
22	PS2603-2		10	SL2601-2
23	PS2604-1		11	SL2602-1
24	PS2604-2		12	SL2602-2

No.	MP9064	Use	LUCC
Type	09330162701 09300160302		

9	LCMAL		1	R2A
10	C24L		2	S2A
11	LCMAS		3	T2A
12	LCFWD		4	M73R-21
13	LCREV		5	M73F-21
14	SW6-1		6	C24L
15	SW6-2		7	C24H
16	TH16		8	LSLIP

No.	MP9063A	Use	HYDRAULIC MOTOR
Type	09200030320 09200032711		

3	W260		1	U260
4	E		2	V260

CONNECTOR TABLE - COOLANT TERMINAL BOX

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - COOLANT TERMINAL BOX	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. E10

No.	MP9750	Use	APC OPR PNL
Type	MR-20M		

1	PS9701-13	2	LP9701-X2	3		4		5	PS9701-14
6	PS9702-14	7	PS9703-22	8	PS9704-14	9	EMG-1	10	EMG-2
11	LP9701-X1	12	LP9702-X1	13	LP9703-X1	14	LP9704-X1	15	

No.	MP9753	Use	APC TABLE
Type	BS12, P/N: 002763, EUCHNER		

1	LS101	2	LS102	3	LS100	4	LS103	5	P24L
6	P24HA	7		8	E	9		10	
11		E							

No.	MP9752	Use	APC INTERFACE
Type	M12, 8 POLES CONNECTOR		

1	MP9753-3	2	MP9753-6	3	E	4	MP9753-2	5	MP9753-4
6	MP9753-5	7	UNUSED	8	MP9753-1				

No.	MP9751	Use	APC EMG
Type	178803-3		

B1	EMG-1	B2		B3	
A1	EMG-2	A2		A3	

No.	MP101	Use	TOOL STATUS
Type	178803-3		

B1	LS00	B2	LS01	B3	C24L
A1	C24H	A2	C24H	A3	

No.	MP101A	Use	SPDL SEAT CHECK
Type	178289-3		

B1	LS602	B2	LS601	B3	
A1	C24H	A2	C24H	A3	

No.	MP9013	Use	CLAMP/UNCLAMP
Type	178289-3		

B1	C24L	B2		B3	
A1	SL00A-5	A2		A3	

No.	MP9013A	Use	CLAMP/UNCLAMP
Type	178803-3		

B1	C24L	B2		B3	
A1	SL00A-5	A2		A3	

APC INTERFACE CONNECTORS

SPINDLE SEAT CHECK CONNECTORS

TOOL CLAMP CONNECTORS

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CONNECTOR TABLE - INTERFACE CONNECTORS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. E11

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150A		PAGE	
X004.7	SKIP	SKIP SIGNAL	49	COM	C53	C55 C56
X004.6	LCREV	LUCC REVERSE	48	C24HI	C32	
X004.5	LCFWD	LUCC FORWARD	47	(1) (18) (33) (50)	C32	
X004.4	LCMAS	LUCC MANUAL	46		C32	
X004.3	TH16	LUCC O/L	45	C24L	C32	
X004.2	LS912	FRONT/RIGHT DOOR ILK	44	(19) (20)	C57	
X004.1	LS190	TSC FILTER CLOGGED	43	(21) (22)	C29	
X004.0	TH19	O/L THRU' SPDL COOLANT	42	(23) (24)	C24	C28

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150A		PAGE	
Y000.7	SL1002	AUTO DOOR CLOSE	41	COM	C70	C80
Y000.6	SL1001	AUTO DOOR OPEN	40	C24HI	C70	C80
Y000.5	SL2311	NOZZLE COOLANT AIR PURGE	39	(1) (18)	C45	
Y000.4	SL2310	SPINDLE AIRSEAL	38	(33) (50)	C45	
Y000.3	---	----	37	C24L	--	
Y000.2	---	----	36	(19) (20)	--	
Y000.1	MS19	R THRU' SPDL CLNT/TOOL THRU	35	(21) (22)	C24	C28
Y000.0	LDOPN	L AUTO DOOR OPEN	34	(23) (24)	C70	C80

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150A		PAGE	
X005.7	---	----	32	COM	--	
X005.6	DETCHA	A AXIS - OVER TRAVEL	31	C24HI	C48	C50
X005.5	OT2A	A AXIS OT	30	(1) (18)	C48	C50
X005.4	OT1A	TILT AXIS OT	29	(33) (50)	C48	C50
X005.3	LS195	TSC FLOW SWITCH	28	C24L	C25	C29
X005.2	LS196	TSC COOLANT LEVEL LOW	27	(19) (20)	C25	C29
X005.1	LS152	A AXIS UNCLAMP	26	(21) (22)	C48	C50
X005.0	LS151	A AXIS CLAMP	25	(23) (24)	C48	C50

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150A		PAGE	
Y001.7	RCHP	SPINDLE SPEED CONTROL	09	COM	C37	
Y001.6	MS16R	LUCC, REVERSE	08	C24HI	C32	
Y001.5	MS16F	LUCC, FORWARD	07	(1) (18)	C32	
Y001.4	LCMAL	LUCC MANUAL LAMP	06	(33) (50)	C32	
Y001.3	AUGRR	AUTO GREASE REVERSE	05	C24L	C77	
Y001.2	AUGRF	AUTO GREASE FORWARD	04	(19) (20)	C77	
Y001.1	LDCLS	L AUTO DOOR CLOSE	03	(21) (22)	C70	C80
Y001.0	SL150	A AXIS UNCLAMP	02	(23) (24)	C48	C50

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150A		PAGE	
X006.7	---	----	17	COM	--	
X006.6	---	----	16	C24HI	--	
X006.5	LS2312	FRONT DOOR OPEN	15	(1) (18)	C70	
X006.4	LS2311	FRONT DOOR CLOSE	14	(33) (50)	C70	
X006.3	ADCLS	AUTO DOOR CLOSE PUSHBUTTON	13	C24L	C70	C80
X006.2	ADOPN	AUTO DOOR OPEN PUSHBUTTON	12	(19) (20)	C70	C80
X006.1	LS2315	LIGHT CURTAIN SENSOR	11	(21) (22)	C94	
X006.0	LS1340	ROTARY UNION WEAR & TEAR LS	10	(23) (24)	C26	C29

I/O ADDRESS TABLE - CB150A

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. F01

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150B		PAGE	
X007.7	USI2	USER DI2	49	COM	C71	
X007.6	USI1	USER DI1	48		C71	
X007.5	PBSCL	PUSHBUTTON ROBOT DR OPEN/CLOSE	47	C24HI (1) (18) (33) (50)	C68	C69
X007.4	LS201	ROBOT DR CLOSE CONFIRM	46		C68	C69
X007.3	LS202	ROBOT DR OPEN CONFIRM	45		C68	C69
X007.2	AIRAL	AIR DRYER ALARM	44	C24L (19) (20) (21) (22) (23) (24)	C75	
X007.1	CB2	ASSIST POWER LINE BRK	43		C36	
X007.0	CPTP	CABINET PROTECTOR TRIP	42		C36	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150B		PAGE	
Y002.7	USO2	USER DO2	41	COM	C71	
Y002.6	USO1	USER DO1	40		C71	
Y002.5	USO3	USER DO3	39	C24HI (1) (18) (33) (50)	C71	
Y002.4	AIRB	AIR BLOW	38		C59	
Y002.3	---	----	37	C24L (19) (20) (21) (22) (23) (24)	--	
Y002.2	SL181	SHOWER COOLANT	36		C45	
Y002.1	LGT	R MACHINE LIGHT	35		C46	
Y002.0	SL6B	ATC AIR	34		C44	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150B		PAGE	
X008.7	OT2Z	LS OVER TRAVEL Z	32	COM	C43	
X008.6	OT2Y	LS OVER TRAVEL Y	31		C43	
X008.5	OT2X	LS OVER TRAVEL X	30	C24HI (1) (18) (33) (50)	C43	
X008.4	ESP	EMERGENCY STOP	29		C43	
X008.3	EMI	EMG STOP SIGNAL	28		C36	
X008.2	LS2111	TOOL BROKEN SENSOR	27	C24L (19) (20) (21) (22) (23) (24)	C76	
X008.1	LS1678	TOOL CL/UC PP TEMP. ALARM	26		C42	
X008.0	---	----	25		--	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150B		PAGE	
Y003.7	USO4	USER DO4	09	COM	C71	
Y003.6	SL202	ROBOT DR OPEN SOLENOID	08		C68	C69
Y003.5	SL201	ROBOT DR CLOSE SOLENOID	07	C24HI (1) (18) (33) (50)	C68	C69
Y003.4	---	----	06		--	
Y003.3	SL02	NOZZLE COOLANT SOL	05	C24L (19) (20) (21) (22) (23) (24)	C47	
Y003.2	SL1308	ROTARY UNION BACKUP	04		C26	
Y003.1	MS2	R NOZZLE COOLANT	03		C23	
Y003.0	SL1306A	COOLANT DRAWBACK ON	02		C26	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150B		PAGE	
X009.7	MSALB	BATTERY LOW ALARM	17	COM	C52	C54
X009.6	MSALA	COMMUNICATION ALARM	16		C52	C54
X009.5	---	----	15	C24HI (1) (18) (33) (50)	--	
X009.4	LSDB	LS DECELERATION B	14		C49	C51
X009.3	LSDA	LS DECELERATION A	13		C48	C50
X009.2	LSDZ	LS DECELERATION Z	12	C24L (19) (20) (21) (22) (23) (24)	C43	
X009.1	LSDY	LS DECELERATION Y	11		C43	
X009.0	LSDX	LS DECELERATION X	10		C43	

I/O ADDRESS TABLE - CB150B

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. F02

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150C		PAGE	
X010.7	---	----	49	COM	--	
X010.6	LS905	MAIN AIR PRESSURE SWITCH	48	C24HI	C39	C41
X010.5	OMAL	SPINDLE TEMP CONTROL ALARM	47	(1) (18) (33) (50)	C38	
X010.4	LS170	SPINDLE OIL FLOW SW	46		C38	
X010.3	LS601	SPINDLE TOOL SEATING CHECK	45	C24L	C39	C41
X010.2	LS602	SPINDLE TOOL CONFIRM	44	(19) (20) (21) (22) (23) (24)	C39	C41
X010.1	LS01	TOOL UNCLAMP	43		C39	C41
X010.0	LS00	TOOL CLAMP	42		C39	C41

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150C		PAGE	
Y004.7	SL00	R TOOL UNCLAMP	41	COM	C40	
Y004.6	SL01	SP. TAPER CLEANING AIR	40	C24HI	C39	C41
Y004.5	OMON	R SP. TEMP CONTROL ON	39	(1) (18) (33) (50)	C38	
Y004.4	SL1306B	COOLANT DRAWBACK OFF	38		C26	
Y004.3	PPMON	TCLAMP P PACK MOTOR ON	37	C24L	C42	
Y004.2	OTRL	OVER TRAVEL RELEASE	36	(19) (20) (21) (22) (23) (24)	C43	
Y004.1	ZBRK	SERVO READY(Z BRAKE)	35		C19	
Y004.0	POUT	R POWER OUT	34		C34	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150C		PAGE
X011.7	PS1201	HYD. PRESSURE SWITCH	32	COM	C42
X011.6	TH12	HYD. POWER PACK ALARM	31	C24HI	C42
X011.5	---	----	30	(1) (18) (33) (50)	--
X011.4	LS03	COOLANT LEVEL SENSOR - LOW	29		C27
X011.3	CCHAL	COOLANT CHILLER ALARM	28	C24L	C30
X011.2	LS04	COOLANT LEVEL SENSOR - HIGH	27	(19) (20) (21) (22) (23) (24)	C27
X011.1	TH2	O/L NOZZLE COOLANT MOTOR	26		C23
X011.0	LS1639	TOOL CL/UC PP OIL LEVEL LOW	25		C42

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150C		PAGE
Y005.7	PTL3	PATROL LIGHT 3	09	COM	C67
Y005.6	PTL2	PATROL LIGHT 2	08	C24HI	C67
Y005.5	PTL1	PATROL LIGHT 1	07	(1) (18) (33) (50)	C67
Y005.4	---	----	06		--
Y005.3	OPPON	PROBE POWER ON	05	C24L	C52 C54
Y005.2	M33X	MEASURING CIRCUIT CHECK	04	(19) (20) (21) (22) (23) (24)	C53 C55
Y005.1	M32X	R TOOL LENGTH MEASURE	03		C53 C55
Y005.0	NMSMD	NOT MEASURING MODE	02		C53 C55

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150C		PAGE	
X012.7	USI04	USER DI4	17	COM	C71	
X012.6	USI03	USER DI3	16	C24HI	C71	
X012.5	LS1698	AUTOGREASE PR.SWITCH	15	(1) (18) (33) (50)	C77	
X012.4	MCSP2	HIGH SPINDLE SPEED	14		C37	
X012.3	MCSP1	LOW SPINDLE SPEED	13	C24L	C37	
X012.2	---	----	12	(19) (20) (21) (22) (23) (24)	--	
X012.1	LS154	B AXIS UNCLAMP	11		C49	C51
X012.0	LS153	B AXIS CLAMP	10		C49	C51

I/O ADDRESS TABLE - CB150C

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. F03

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150D		PAGE	
X0013.7	---	----	49	COM	--	
X0013.6	---	----	48	C24HI (1) (18) (33) (50)	--	
X0013.5	---	----	47		--	
X0013.4	---	----	46		--	
X0013.3	---	----	45	C24L (19) (20) (21) (22) (23) (24)	--	
X0013.2	---	----	44		--	
X0013.1	---	----	43		--	
X0013.0	---	----	42		--	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150D		PAGE	
Y0006.7	---	----	41	COM	--	
Y0006.6	MS65	TRANSFER PUMP ON	40	C24HI (1) (18) (33) (50)	C30	C31
Y0006.5	SL51	5TH AXIS UNCLAMP	39		C49	C51
Y0006.4	---	----	38		--	
Y0006.3	---	----	37	C24L (19) (20) (21) (22) (23) (24)	--	
Y0006.2	---	----	36		--	
Y0006.1	---	----	35		--	
Y0006.0	---	----	34		--	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150D		PAGE
X0014.7	---	----	32	COM	--
X0014.6	---	----	31	C24HI (1) (18) (33) (50)	--
X0014.5	---	----	30		--
X0014.4	---	----	29		--
X0014.3	---	----	28	C24L (19) (20) (21) (22) (23) (24)	--
X0014.2	---	----	27		--
X0014.1	---	----	26		--
X0014.0	---	----	25		--

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150D		PAGE
Y0007.7	USO08	USER DO8	09	COM	C72
Y0007.6	USO07	USER DO7	08	C24HI (1) (18) (33) (50)	C72
Y0007.5	USO06	USER DO6	07		C72
Y0007.4	USO05	USER DO5	06		C72
Y0007.3	---	----	05	C24L (19) (20) (21) (22) (23) (24)	--
Y0007.2	---	----	04		--
Y0007.1	---	----	03		---
Y0007.0	---	----	02		---

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB150D		PAGE	
X0015.7	USI08	USER DI8	17	COM	C72	
X0015.6	USI07	USER DI7	16	C24HI (1) (18) (33) (50)	C72	
X0015.5	USI06	USER DI6	15		C72	
X0015.4	USI05	USER DI5	14		C72	
X0015.3	---	----	13	C24L (19) (20) (21) (22) (23) (24)	--	
X0015.2	---	----	12		--	
X0015.1	TH65	TRANSFER PUMP TRIP	11		C30	C31
X0015.0	---	----	10		--	

I/O ADDRESS TABLE - CB150D

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. F04

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151A		PAGE	
X0016.7	HY1UC	HYD UNCLAMP PB	49	COM	C89	
X0016.6	HY1CL	HYD UNCLAMP PB	48	C24HI	C89	
X0016.5	---	----	47	(1) (18) (33) (50)	--	
X0016.4	THPBL	TWO HAND PB L	46		C91	C92
X0016.3	THPBR	TWO HAND PB R	45	C24L	C91	C92
X0016.2	AIRSV	AIR SEAT CHECK SW	44	(19) (20) (21) (22) (23) (24)	C89	
X0016.1	STRSW	STRIKER SW	43		C91	C92
X0016.0	SWMAN	MANUAL MODE SEL SWITCH	42		C89	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151A		PAGE	
Y0008.7	SL1781	AIR SEAT CHECK SOLENOID 2	41	COM	C88	
Y0008.6	SL1780	AIR SEAT CHECK SOLENOID 1	40	C24HI	C88	
Y0008.5	MS260	HYDRAULIC MOTOR ON	39	(1) (18) (33) (50)	C82	C83
Y0008.4	LSETUP	LAMP SETUP FINISH	38		C89	
Y0008.3	LMAN	LAMP MANUAL MODE	37	C24L	C89	
Y0008.2	LAIRS	LAMP AIR SEAT CHECK 2 ON	36	(19) (20) (21) (22) (23) (24)	C89	
Y0008.1	LHY1UC	LAMP HYD UNCLAMP1	35		C89	
Y0008.0	LHY1CL	LAMP HYD CLAMP1	34		C89	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151A		PAGE	
X0017.7	TH260	HYD MOTOR OVERLOAD	32	COM	C82	C83
X0017.6	LS2603	HYD OIL LEVEL FLOAT SWITCH	31	C24HI	C82	C83
X0017.5	LS2604	HYD OIL TEMPERATURE SENSOR	30	(1) (18) (33) (50)	C82	C83
X0017.4	SYSPS	SYSTEM PRESSURE SWITCH	29		C82	C83
X0017.3	LS1782	AIR SEAT SENSOR 2	28	C24L	C88	
X0017.2	LS1781	AIR SEAT SENSOR 1	27	(19) (20) (21) (22) (23) (24)	C88	
X0017.1	WWE	WORK WASH ENABLE PUSHBUTTON	26		C89	
X0017.0	ASTR	AUTO START PUSHBUTTON	25		C89	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151A		PAGE	
Y0009.7	LWWE	LAMP WORK WASH ENABLE	09	COM	C89	
Y0009.6	LALM	LAMP AIRSEAT CHECK 1 ON	08	C24HI	C89	
Y0009.5	SL2604	HYD SOLENOID 4	07	(1) (18) (33) (50)	C85	C86
Y0009.4	SL2603	HYD SOLENOID 3	06		C85	C86
Y0009.3	SL2602	HYD SOLENOID 2	05	C24L	C84	C86
Y0009.2	SL2601	HYD SOLENOID 1	04	(19) (20) (21) (22) (23) (24)	C84	C86
Y0009.1	LHY2UC	LAMP HYD UNCLAMP2	03		C90	
Y0009.0	LHY2CL	LAMP HYD CLAMP2	02		C90	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151A		PAGE	
X0018.7	---	----	17	COM	--	
X0018.6	---	----	16	C24HI	--	
X0018.5	HY2UC	HYD UNCLAMP2 PUSHBUTTON	15	(1) (18) (33) (50)	C90	
X0018.4	HY2CL	HYD CLAMP2 PUSHBUTTON	14		C90	
X0018.3	PS2604	HYD PRESSURE SWITCH 4	13	C24L	C85	C86
X0018.2	PS2603	HYD PRESSURE SWITCH 3	12	(19) (20) (21) (22) (23) (24)	C85	C86
X0018.1	PS2602	HYD PRESSURE SWITCH 2	11		C84	
X0018.0	PS2601	HYD PRESSURE SWITCH 1	10		C84	C86

I/O ADDRESS TABLE - CB151A

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. F05

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151B		PAGE	
X0019.7	---	----	49	COM	--	
X0019.6	---	----	48	C24HI	--	
X0019.5	LS1788	AIR SEAT SENSOR 8	47	(1) (18) (33) (50)	C88	
X0019.4	LS1787	AIR SEAT SENSOR 7	46		C88	
X0019.3	LS1786	AIR SEAT SENSOR 6	45	C24L	C88	
X0019.2	LS1785	AIR SEAT SENSOR 5	44	(19) (20) (21) (22) (23) (24)	C88	
X0019.1	LS1784	AIR SEAT SENSOR 4	43		C88	
X0019.0	LS1783	AIR SEAT SENSOR 3	42		C88	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151B		PAGE	
Y0010.7	---	----	41	COM	--	
Y0010.6	---	----	40	C24HI	--	
Y0010.5	---	----	39	(1) (18) (33) (50)	--	
Y0010.4	---	----	38		--	
Y0010.3	SL2608	HYD SOLENOID 8	37	C24L	C85	C87
Y0010.2	SL2607	HYD SOLENOID 7	36	(19) (20) (21) (22) (23) (24)	C85	C87
Y0010.1	SL2606	HYD SOLENOID 6	35		C84	C87
Y0010.0	SL2605	HYD SOLENOID 5	34		C84	C87

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151B		PAGE	
X0020.7	LS1792	AIR SEAT SENSOR 12	32	COM	C88	
X0020.6	LS1791	AIR SEAT SENSOR 11	31	C24HI	C88	
X0020.5	LS1790	AIR SEAT SENSOR 10	30	(1) (18) (33) (50)	C88	
X0020.4	LS1789	AIR SEAT SENSOR 9	29		C88	
X0020.3	PS2608	HYD PRESSURE SWITCH 8	28	C24L	C85	
X0020.2	PS2607	HYD PRESSURE SWITCH 7	27	(19) (20) (21) (22) (23) (24)	C85	C87
X0020.1	PS2606	HYD PRESSURE SWITCH 6	26		C84	
X0020.0	PS2605	HYD PRESSURE SWITCH 5	25		C84	C87

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151B		PAGE
Y0011.7	---	----	09	COM	--
Y0011.6	---	----	08	C24HI	--
Y0011.5	---	----	07	(1) (18) (33) (50)	--
Y0011.4	SL1801	FIXTURE COOLANT SOL	06		C45
Y0011.3	---	----	05	C24L	--
Y0011.2	---	----	04	(19) (20) (21) (22) (23) (24)	--
Y0011.1	---	----	03		--
Y0011.0	---	----	02		--

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151B		PAGE
X0021.7	---	----	17	COM	--
X0021.6	---	----	16	C24HI	--
X0021.5	---	----	15	(1) (18) (33) (50)	--
X0021.4	---	----	14		--
X0021.3	---	----	13	C24L	--
X0021.2	---	----	12	(19) (20) (21) (22) (23) (24)	--
X0021.1	---	----	11		--
X0021.0	---	----	10		--

I/O ADDRESS TABLE - CB151B

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. F06

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151C		PAGE	
X0022.7	LS966	APC STOCKER DOOR CLSOE CONFIRM	49	COM	C58	C80
X0022.6	LS955L	APC STOCKER AUTODOOR LEFT OPEN	48	P24HA	C80	
X0022.5	---	----	47	(1) (18) (33) (50)	--	
X0022.4	---	----	46		--	
X0022.3	LS103	APC ARM CW	45	C24L	C79	
X0022.2	LS102	APC ARM CCW	44	(19) (20) (21) (22) (23) (24)	C79	
X0022.1	LS101	APC ARM LIFT	43		C79	
X0022.0	LS100	APC ARM DOWN	42		C79	

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151C		PAGE
Y0012.7	APCCW	APC CLOCKWISE (C24HP1)	41	COM	C81
Y0012.6	MS300	MISTCOLLECTOR	40	P24HA	C93
Y0012.5	MS11C	WORK WASH GUN ENABLE	39	(1) (18) (33) (50)	C23
Y0012.4	---	----	38		--
Y0012.3	SL101B	APC ARM CW	37	C24L	C79
Y0012.2	SL101A	APC ARM CCW	36	(19) (20) (21) (22) (23) (24)	C79
Y0012.1	SL100B	APC ARM UP	35		C79
Y0012.0	SL100A	APC ARM DOWN	34		C79

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151C		PAGE
X0023.7	MP2S	MULTIPLY X100	32	COM	C66
X0023.6	MP1S	MULTIPLY X10	31	P24HA	C66
X0023.5	H5	B AXIS SELECT	30	(1) (18) (33) (50)	C66
X0023.4	H4	A AXIS SELECT	29		C66
X0023.3	HZ	Z AXIS SELECT	28	C24L	C66
X0023.2	HY	Y AXIS SELECT	27	(19) (20) (21) (22) (23) (24)	C66
X0023.1	HX	X AXIS SELECT	26		C66
X0023.0	LS955R	APC STOCKER AUTODOOR RIGHT OPEN	25		C80

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151C		PAGE
Y0013.7	HAMOD	HANDLE MODE	09	COM	C66
Y0013.6	APCCCW	APC COUNTER CLOCKWISE (C24HP2)	08	P24HA	C81
Y0013.5	SL914	APC STOCKER DOOR UNLOCK	07	(1) (18) (33) (50)	C58
Y0013.4	SL912	OPR DOOR UNLOCK	06		C57
Y0013.3	PCWWL	WORK WASH GUN LAMP	05	C24L	C78
Y0013.2	PCSPL	APC APC SIDE FEEDHOLD LIGHT	04	(19) (20) (21) (22) (23) (24)	C78
Y0013.1	PCMAL	APC MANUAL SWITCH LIGHT	03		C78
Y0013.0	PRDY1	APC READY LIGHT	02		C78

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB151C		PAGE
X0024.7	---	----	17	COM	--
X0024.6	TH300	MISTCOLLECTOR THERMAL TRIP	16	P24HA	C93
X0024.5	MOPMUL	MODE UNLOCK	15	(1) (18) (33) (50)	C95
X0024.4	---	----	14		--
X0024.3	PCWWE	WORK WASH GUN ENABLE	13	C24L	C78
X0024.2	PCSPC	APC APC SIDE FEEDHOLD	12	(19) (20) (21) (22) (23) (24)	C78
X0024.1	PCMAS	APC MANUAL SWITCH	11		C78
X0024.0	RDYPB1	APC READY	10		C78

I/O ADDRESS TABLE - CB151C

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. F07

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB152A		PAGE
X0028.7	RBI9	ROBOT INTERFACE INPUT	49	COM	C96
X0028.6	RBI10	ROBOT INTERFACE INPUT	48	C24HI	C96
X0028.5	RBI11	ROBOT INTERFACE INPUT	47	(1) (18) (33) (50)	C96
X0028.4	RBI12	ROBOT INTERFACE INPUT	46		C96
X0028.3	RBI13	ROBOT INTERFACE INPUT	45	C24L	C96
X0028.2	RBI14	ROBOT INTERFACE INPUT	44	(19) (20) (21) (22) (23) (24)	C96
X0028.1	RBI15	ROBOT INTERFACE INPUT	43		C96
X0028.0	RBI16	ROBOT INTERFACE INPUT	42		C96

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB152A		PAGE
Y0016.7	RBO9	ROBOT INTERFACE OUTPUT	41	COM	C96
Y0016.6	RBO10	ROBOT INTERFACE OUTPUT	40	C24HI	C96
Y0016.5	RBO11	ROBOT INTERFACE OUTPUT	39	(1) (18) (33) (50)	C96
Y0016.4	RBO12	ROBOT INTERFACE OUTPUT	38		C96
Y0016.3	RBO13	ROBOT INTERFACE OUTPUT	37	C24L	C96
Y0016.2	RBO14	ROBOT INTERFACE OUTPUT	36	(19) (20) (21) (22) (23) (24)	C96
Y0016.1	RBO15	ROBOT INTERFACE OUTPUT	35		C96
Y0016.0	RBO16	ROBOT INTERFACE OUTPUT	34		C96

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB152A		PAGE
X0029.7	RBI1	ROBOT INTERFACE INPUT	32	COM	C96
X0029.6	RBI2	ROBOT INTERFACE INPUT	31	C24HI	C96
X0029.5	RBI3	ROBOT INTERFACE INPUT	30	(1) (18) (33) (50)	C96
X0029.4	RBI4	ROBOT INTERFACE INPUT	29		C96
X0029.3	RBI5	ROBOT INTERFACE INPUT	28	C24L	C96
X0029.2	RBI6	ROBOT INTERFACE INPUT	27	(19) (20) (21) (22) (23) (24)	C96
X0029.1	RBI7	ROBOT INTERFACE INPUT	26		C96
X0029.0	RBI8	ROBOT INTERFACE INPUT	25		C96

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB152A		PAGE
Y0017.7	RBO1	ROBOT INTERFACE OUTPUT	09	COM	C96
Y0017.6	RBO2	ROBOT INTERFACE OUTPUT	08	C24HI	C96
Y0017.5	RBO3	ROBOT INTERFACE OUTPUT	07	(1) (18) (33) (50)	C96
Y0017.4	RBO4	ROBOT INTERFACE OUTPUT	06		C96
Y0017.3	RBO5	ROBOT INTERFACE OUTPUT	05	C24L	C96
Y0017.2	RBO6	ROBOT INTERFACE OUTPUT	04	(19) (20) (21) (22) (23) (24)	C96
Y0017.1	RBO7	ROBOT INTERFACE OUTPUT	03		C96
Y0017.0	RBO8	ROBOT INTERFACE OUTPUT	02		C96

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CB152A		PAGE
X0030.7	---	----	17	COM	--
X0030.6	---	----	16	C24HI	--
X0030.5	---	----	15	(1) (18) (33) (50)	--
X0030.4	---	----	14		--
X0030.3	---	----	13	C24L	--
X0030.2	---	----	12	(19) (20) (21) (22) (23) (24)	--
X0030.1	---	----	11		--
X0030.0	---	----	10		--

NOTE: IOMODULE CB152A IS FOR ROBOT INTERFACE OPTION

I/O ADDRESS TABLE - CB152A

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (MACHINE I/O)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. F08

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE56A		PAGE
X096.7	SJOG	JOG MODE ON	B05	COM	C61
X096.6	SRPD	RAPID MODE	A05	+24V (B01)	C61
X096.5	SREF	REFERENCE MODE	B04		C61
X096.4	SHND	HANDLE MODE	A04		C61
X096.3	SRMT	EXTERNAL INPUT MODE	B03	C24L (A01)	C61
X096.2	SMDI	MDI MODE	A03		C61
X096.1	SMEM	MEMORY MODE	B02	DICOM (A14)	C61
X096.0	SEDT	EDIT MODE	A02		C61

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE56A		PAGE
X097.7	ROV1I	RAPID TRAVERSE OVERRIDE SW.25	B09	COM	C63
X097.6	STSC	THROUGH SPINDLE COOLANT ON	A09	+24V (B01)	C62
X097.5	SAIRON	AIR BLOW	B08		C62
X097.4	SNOZL	NOZZLE ON/OFF	A08		C61
X097.3	SCOOL	COOLANT ON	B07	C24L (A01)	C61
X097.2	SOPS	OPTIONAL STOP	A07		C61
X097.1	SBDT	BLOCK SKIP	B06	DICOM (A14)	C61
X097.0	SSBK	SINGLE BLOCK	A06		C61

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE56A		PAGE
X098.7	FV32I	FEED RATE OVERRIDE SWITCH (INHIBIT)	B13	COM	C63
X098.6	FV16I	FEED RATE OVERRIDE SWITCH (16)	A13	+24V (B01)	C63
X098.5	FV8I	FEED RATE OVERRIDE SWITCH (8)	B12		C63
X098.4	FV4I	FEED RATE OVERRIDE SWITCH (4)	A12		C63
X098.3	FV2I	FEED RATE OVERRIDE SWITCH (2)	B11	C24L (A01)	C63
X098.2	FV1I	FEED RATE OVERRIDE SWITCH (1)	A11		C63
X098.1	ROV4I	RAPID TRAVERSE OVERRIDE SW.100	B10	DICOM (A14)	C63
X098.0	ROV2I	RAPID TRAVERSE OVERRIDE SW.50	A10		C63

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE56A		PAGE
Y096.7	LJOG	JOG LIGHT	B19	COM	C61
Y096.6	LRPD	RAPID LIGHT	A19	C24H (A24) (B24) (A25) (B25)	C61
Y096.5	LREF	REFERENCE LIGHT	B18		C61
Y096.4	LHND	HANDLE LIGHT	A18		C61
Y096.3	LRMT	EXTERNAL INPUT LIGHT	B17		C61
Y096.2	LMDI	MDI MODE LIGHT	A17	C24L (A01)	C61
Y096.1	LMEM	MEMORY MODE LIGHT	B16		C61
Y096.0	LEDT	EDIT MODE LIGHT	A16		C61

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE56A		PAGE
Y097.7	L5	LAMP 5TH AXIS SELECT	B23	COM	C62
Y097.6	LTSC	THROUGH SPINDLE COLLNAT LIGHT	A23	C24H (A24) (B24) (A25) (B25)	C62
Y097.5	LAIRB	AIR BLOW LIGHT	B22		C62
Y097.4	LNOZL	NOZZLE ON/OFF LIGHT	A22		C61
Y097.3	LCOLON	COOLANT ON/OFF LIGHT	B21		C61
Y097.2	LOPS	OPTIONAL STOP LIGHT	A21	C24L (A01)	C61
Y097.1	LBDT	BLOCK SKIP LIGHT	B20		C61
Y097.0	LSBK	SINGLE BLOCK LIGHT	A20		C61

I/O ADDRESS TABLE - OPE.I/O MODULE NO.1

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (OPR. PANEL I/O)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. F09

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE57A		PAGE
X099.7	AXS4	4TH AXIS	B05	COM	C62
X099.6	AXSZ	Z AXIS	A05	+24V (B01)	C62
X099.5	AXSY	Y AXIS	B04		C62
X099.4	AXSX	X AXIS	A04		C62
X099.3	SONESP	ONE TOUCH FUNCTION STOP	B03	C24L (A01)	C62
X099.2	SONEST	ONE TOUCH FUNCTION START	A03		C62
X099.1	SONET2	SETUP	B02	DICOM (A14)	C62
X099.0	SONET1	ALL AXES REFERENCE	A02		C62

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE57A		PAGE
X100.7	AXS5	5TH AXIS INPUT	B09	COM	C63
X100.6	---	----	A09	+24V (B01)	C63
X100.5	IRKEY	S/G ILK RELEASE	B08		C63
X100.4	MPKEY	MEMORY KEY	A08		C63
X100.3	LIGHT	LIGHT ON	B07	C24L (A01)	C63
X100.2	OTRS	OT RELEASE	A07		C63
X100.1	JOG '-'	(-)MINUS DIRECTION	B06	DICOM (A14)	C62
X100.0	JOG '+'	(+)PLUS DIRECTION	A06		C62

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE57A		PAGE
X101.7	SPAREDI3	SPARE INPUT3	B13	COM	C64
X101.6	SPAREDI2	SPARE INPUT2	A13	+24V (B01)	C64
X101.5	AUST	CYCLE START	B12		C64
X101.4	AUSP	FEEDHOLD	A12		C64
X101.3	SPONF	SPINDLE ON/OFF	B11	C24L (A01)	C64
X101.2	TUCL	TOOL UNCLAMP	A11		C64
X101.1	ALRST	ALARM RESET	B10	DICOM (A14)	C64
X101.0	SPOWOF	POWER OFF	A10		C64

DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE57A		PAGE
Y098.7	L4	4TH AXIS LIGHT	B19	COM	C62
Y098.6	LZ	Z AXIS LIGHT	A19	C24H (A24) (B24) (A25) (B25)	C62
Y098.5	LY	Y AXIS LIGHT	B18		C62
Y098.4	LX	X AXIS LIGHT	A18		C62
Y098.3	LONESP	ONE TOUCH STOP LIGHT	B17		C62
Y098.2	LONEST	ONE TOUCH START LIGHT	A17	C24L (A01)	C62
Y098.1	LONET2	ONE TOUCH FUNCTION2 SELECT	B16		C62
Y098.0	LONET1	ONE TOUCH FUNCTION1 SELECT	A16		C62


DGN.NO.	SYMBOL	SIGNAL NAME	CONNECTOR NO. CE57A		PAGE
Y099.7	SPARED03	SPARE OUTPUT3	B23	COM	C64
Y099.6	PTL4	SPARE OUTPUT2	A23	C24H (A24) (B24) (A25) (B25)	C64
Y099.5	LAUST	CYCLE START LIGHT	B22		C64
Y099.4	LAUSP	FEEDHOLD LIGHT	A22		C64
Y099.3	LSPNONF	SPINDLE STOP LIGHT	B21		C64
Y099.2	LTUCL	TOOL UNCLAMP LIGHT	A21	C24L (A01)	C64
Y099.1	LALMR	ALARM RESET LIGHT	B20		C64
Y099.0	LPOWOF	POWER OFF LIGHT	A20		C64

I/O ADDRESS TABLE - OPE.I/O MODULE NO.1

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
DI/DO ADDRESS TABLE (OPR. PANEL I/O)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. F10




OPERATION PANEL	MTC	MACHINE SIDE

Revisions			Date	Name
4				
3		APPROVED	14-AUG-2012	GOH WILLIAM
2		CHECKED	14-AUG-2012	XING JY
1		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD


TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MACHINE INTERCONNECTION (STD & APC M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. G01



Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MACHINE INTERCONNECTION (CE M/C)	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. G02



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	PSM	PSM-26i	FANUC	---	A06B-6140-H026
2	SPM	SPM-22i	FANUC	---	A06B-6141-H022#580
3	SVM X/Y	SVM2 X/Y	FANUC	---	A06B-6117-H210
4	SVM Z/C	SVM2 Z/C	FANUC	---	A06B-6117-H208
5	PFM	BUFFER MODULE	SCHNEIDER	ABL8BUF24400	L35A009
6	SVM A	SVM A	FANUC	---	A06B-6117-H105
7	MCSP1, MCSP2	MAG CONT AC100,80A AUXILIARY SWITCH 1NO+1NC RC ELEMENT, AC 48~127V	SIEMENS SIEMENS SIEMENS	3RT1045-1AG20 3RH19211DA1 3RT1936-1CC00	L16A117 L16A033 L16A098
8	MCC	MAG CONT AC100,80A AUXILIARY SWITCH 1NO+1NC RC ELEMENT, AC 48~127V	SIEMENS SIEMENS SIEMENS	3RT1045-1AG20 3RH19211DA1 3RT1936-1CC00	L16A117 L16A033 L16A098
9	24VDC REG	DC24V SUPPLY	SIEMENS	6EP1334-2AA01	L35A006
10	T2	TRANSFORMER 250VA,	SCHNEIDER	ABL6TS25G	L29A112
11	ACR	AC REACTOR PSM26i	FANUC	---	A81L-0001-0159
12	RELAY PCB	RELAY PCB	MAKINO	---	E6VS090A201-00
13	CB150A,CB151A	I/O MODULE BASIC 24/26	FANUC	---	A03B-0815-C001
14	CB150B , CB150C	I/O UNIT 24/26 POINTS	FANUC	---	A03B-0815-C003
15	CB2A CB2A AUX	CB, 3P,32A W/AUX SW1NO/1NC	SIEMENS	3VU1640-1MP00	L14A049
16	CB2C	CB, 3P,10A W/AUX SW1NO/1NC	SIEMENS	3VU1640-1ML00	L14A052
17	MS2 TH2 SK2	CONTACTOR 12A 24VDC SURGE SUPRESSOR OVERLOAD RELAY SPARK KILLER	SIEMENS SIEMENS SIEMENS MURR	3RT1017-1BB41 3RT1916-1JK00 3RU1116-1GB0 23004	L16A030 L13C012 L16B066 L13C011
18	MS12 TH12 SK12	CONTACTOR 7A 24VDC SURGE SUPRESSOR OVERLOAD RELAY SPARK KILLER	SIEMENS SIEMENS SIEMENS MURR	3RT1015-1BB41 3RT1916-1JK00 3RU1116-1DB0 23004	L16A031 L13C012 L16B065 L13C011
19	MS19 TH19 SK19	CONTACTOR 12A 24VDC SURGE SUPRESSOR OVERLOAD RELAY SPARK KILLER	SIEMENS SIEMENS SIEMENS MURR	3RT1017-1BB41 3RT1916-1JK00 3RU1116-1KB0 23004	L16A030 L13C012 L16B067 L13C011
20	MS260 TH260 SK260	CONTACTOR 12A OVERLOAD RELAY CONTACTOR 12A OVERLOAD RELAY 24VDC SURGE SUPRESSOR SPARK KILLER	SIEMENS SIEMENS SIEMENS SIEMENS SIEMENS MURR	3RT1017-1BB41 3RU1116-1HB0 3RT1017-1BB41 3RU1116-1DB0 3RT1916-1JK00 23004	L16A030 (YUKEN) L16B078 (YUKEN) L16A031 (AMF) L16B065 (AMF) L13C012 (YUKEN/AMF) L13C011 (YUKEN/AMF)
21	RCHP, SL00A, SL1001, SL1002	RELAY RELAY SOCKET CLIP	OMRON OMRON OMRON	MY2N-D2 24VDC PYF08A-E CLIP FOR MY	L16B081 L16B082 L16B059
22	POWER SUPPLY 24V 4.5A	POWER SUPPLY	OMRON	---	L35A002
23	POWER SUPPLY 24V 10A	POWER SUPPLY	SCHNEIDER	ABL8RPS24100	L35A008


MTC FRONT VIEW

PARTS LIST

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MTC LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. H01



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
24	OPTION PCB	OPTION PCB	MAKINO	---	E6VS603800-00
25	MACRO PCB	MACRO PCB	MAKINO	---	---
26	HYDRAULIC PCB	HYDRAULIC PCB	MAKINO	---	E7VS140A101-00
27	24VDC P/S	OMRON POWER SUPPLY	OMRON	---	L35A002
28	ACR2	AC REACTOR BETA	FANUC	---	A81L-0001-0083#3C
29	SDU	SDU UNIT FOR SERIAL SCALE	FANUC	---	A02B-0236-C205
30	CE PCB	CE PCB	MAKINO	---	E7VS192A800-02
31	PRE1,PRE3,PRE4 PRE5, PRE6	SAFETY RELAY	EUCHNER	ESM-BA301	L17B072
32	PRE2	SAFETY REALY	EUCHNER	ESM-BT421	L17B073
33	R1, R2, R3, R4, E24HS	SAFETY REALY DIODE AUX. CONTACT	SIEMENS	3RH1140-1BB40 3RT1916-1EH00 3RH1911-1FA31	L17B031 L17B032 L17B033
34	R5, R6, R7, R8, KHAMOD	SAFETY REALY	OMRON	G7SA-3A1B+P7SA-10F-ND	L17B075
35	ZBRK1,ZBRK2, APCCW, APCCCW	SAFETY RELAY	OMRON	G7SA-2A2B+P7SA-10F-ND	L17B074
36	LINE FILTER	LINE FILTER	SCHAFFNER	FN3258-100-35	L17B023
37	TB9000	TERMINAL BLOCK	FUJI	ABYBN103-5	L15C043
38	TB9021	TERMINAL BLOCK TERMINAL ENDPLATE TERMINAL LINK END STOPPER	WAGO	281-681 281-326 281-402 249-117	L15C070 L15C071 L15C072 L15C051
39	BETA SVM1-20I	SVM C	FANUC	----	A06B-6132-H002


CE MTC FRONT VIEW


PARTS LIST

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE				
MTC LAYOUT, PARTS	MACHINE TYPE	SLIM3	DRAWING No.	GROUP =
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. H02





NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	CP4	CP, 2P, 10A	SIEMENS	5SX4210-7RC	L14B037
	CP5	CP, 2P, 6A		5SX4206-7RC	L14B038
2	CP41,CP51 CP52,CP53	CP, 1P, 8A	SIEMENS		
		CP, 1P, 6A		5SX4106-7RC	L14B040 MAKINO INDIA SLIM3
3	CP4AUX,CP5AUX, CP41AUX,CP51AUX CP52AUX,CP53AUX	AUX CONTACT 1NO/1NC	SIEMENS	ST3020	
					L17B045 MAKINO INDIA SLIM3
4	CB0	CIRCUIT BREAKER 3P. AC415, 100A (WITH SHUNT)	SIEMENS		
				3VL1710-1DD33- 8RA0	L14A035 MAKINO INDIA SLIM3
5	TB9001	TERMINAL BLOCKS	FUJI	ABYBN103-5,3P	L15C043
6	TB9010 TB9011 TB9012	TERMINAL BLOCKS	WAGO	280 SERIES	L15C070, L15C071, L15C051
7	CP260	CP, 1P, 6A	SIEMENS		
				5SX4106-7RC	L14B040 MAKINO INDIA SLIM3

MTC RIGHT VIEW


MTC LEFT VIEW

PARTS LIST

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
MTC LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. H03



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	EMG	PB EMERGENCY	TEKNIC	2PSML401	L11B109
2	KS01 MODE UNLOCK	KEY SWITCH	SCHLEGEL	QXSSA17E AT	L11C045 L11B008
3	RS1 RS2	ROTARY SWITCH ROTARY SWITCH SWITCH KNOB	TOSOKU TOSOKU TOSOKU	RS400P-1-1-4BP DPP01020J16R BC60	L11C038 L11C040 L11C058
4	PS2, LP2 PS3, LP3 PS5, LP5 PS4, LP4	PB ACTUATOR PB CONTACT BLOCK PB LENS PB LENS COVER PB LED	SCHLEGEL CONTROSYS	QXD BZLOI5 T25DKL KDQN16 T5.5K-4UY-24V	L11B046 L11B124 L11B055 L11B063 L11B184
5	PS7,LP7	PB & LED 1NC (RED)	FUJI	AR22G4L-01E3W	L11B057
6	PS6,LP6	PB & LED 1NO (GREEN)	FUJI	AR22G4L-10E3W	L11B056
7	PS1,LP1	PB ACTUATOR PB CONTACT BLOCK PB LENS PB LED	SCHLEGEL CONTROSYS	QXD BZLII5PB T25DKL T5.5K-4UY-24V	L11B046 L11B125 L11B055 L11B184
8	PORTABLE MPG	HAND-HELD MPG	EUCHNER	HBA-110196 MPG,EUCHNER,	L11C085


OPERATOR PANEL FRONT VIEW - E6VS091A403-XX

PARTS LIST

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
OPERATOR PANEL LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. H04



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO NO.
01	MP9002,MP9003 MP9004,MP9012 MP9056	CONN.AMP 3WAY, X TYPE	AMP	1-178313-5	L15A087
02	MP9050,MP9051 MP9008,MP9009	CONN.AMP 6WAY, X TYPE	AMP	0-178323-2	L15A144
03	MP9055,MP9016 MP9011,MP9017 MP9010,MP9028	D-CONN. 9WAY, FEMALE	REPUTED	DMS-9-S-1-M-G E-2-6-F	L15A246
04	MP9005,MP9006 MP9007,MP9027 MP9054,MP9053	D-CONN. 9WAY, MALE	REPUTED	DMS-9-P-1-M-G E-2-6-F	L15A243
05	MP9015,MP9018	D-CON 25 WAY MALE	REPUTED	DMS-25-P-1-M-G E-2-6-F	L15A245
06	MP9020,MP9021 MP9019	D-CON 25 WAY FEMALE	REPUTED	DMS-25-S-1-M-G E-2-6-F	L15A248
07	CB104,CB105 CB106	CONN. TAP HRS 50 WAY	HIROSE	HIF3CB-50PA-2.54D5A	L15A114
08	MP9052	CONN. TAP HRS 20 WAY	HIROSE	HIF3CB-20PA-2.54D5A	L15A115
09	TB9050	PCB TERMINAL 5/5.08 SPACING	WAGO	255-401	L15A249
10	PE	EARTH STUD M4	---	---	---
11	POUT,ZBRK,SL01 SL00,LGT,SL181 SL02,SL201,SL202 EM2,ANGL,MISC1 MISC2	RELAY 1NO+1NC	OMRON	G6B-2114P-US	L16B055
12	SL2111,MS6B,US01 US02,SL192,SL191 SL2310,SL2311 SL150,MS16F MS16R,OMON	RELAY BASE 1NO	OMRON	G6B-04P	L16B061
13	NCON	RELAY 2NO	OMRON	G6B-2214P-US	L16B056
14	R	510Ohm, 5W CEMENT	VB&LEE	---	L13B006
15	C	0.22MicroF, 250V CERAMIC	REPUTED	---	L13A001
16	S1,S2,S3,S4	SHORTING LINK 2 WAY	REPUTED	---	---
17	S5	SHORTING LINK 5 WAY	REPUTED	---	---
18	D1~D27	DIODE 1N4007	REPUTED	---	---
19	OTRL,SL181,NMSMD UMD1,RCHP,SL01 SL00,UMD2,M34X SL21,SL20,SL150 MS16F,MS16R,OPON M86X,SGA,MS6B ANGL,M33X,SL913 SL912	RELAY SOCKET, PCB MOUNT	OMRON	P2R-08P	L16B012
20	EM1,EM2	RELAY 4PDT, 24VDC	FUJI	HH54P-FL 24VDC	L16B026
21	M32X,M32L	RELAY 4PDT, 24VDC	FUJI	HH54P-FL 24VDC	L16B026
22	EM1,EM2 M32X,M32L	RELAY SOCKET, PCB MOUNT	FUJI	TP514B	L16B038
23	NCN2,NCON,LGT ZBRK,POUT	RELAY 2PDT, 24VDC	FUJI	HH62P-FL 24VDC	L16B025
24	NCN2,NCON,LGT ZBRK,POUT	RELAY SOCKET, PCB MOUNT	FUJI	TP68B	L16B039


RELAY PCB FRONT VIEW

PARTS LIST


Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
RELAY PCB LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. H05



(LFRONT VIEW FOR PANEL MOUNTING)



(LBACK VIEW(FOR CABLE CONNECTIONS)

NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	SW900 ~ SW927	SW CAP JAE SW TACTILE FB JAE	JAE	S-N066-1065 61T-0101	L11C030 L11C026
2	S1	SHORTING LINK	REPUTED	--	
3	PTL1,PTL2,PTL3	OMRON G6B SERIES	OMRON	G6B-2214P-US	L16B056
4	L900~L932	GREEN LED (3MM)	REPUTED	--	L23A029
5	R900~R932	RESISTOR 2.2K, 1/2W	REPUTED	--	L17B011
6	D932~D934	DIODE 1N4007	REPUTED	--	
7	CE56A,CE57A	CONN. TAP HRS 50 WAY	HIROSE	HIF3CB-50PA-2.54D5A	L15A114
8	MP9117	D-CON 15 WAY MALE HEX CLINCHED NUT FRONT	REPUTED	DMS-15-P-1-M-G E-2-6-F	L15A244
9	MP9115,MP9116	D-CON 25 WAY FEMALE HEX CLINCHED NUT FRONT	REPUTED	DMS-25-S-1-M-G E-2-6-F	L15A248
10	MP9105	D-CON 25 WAY MALE HEX CLINCHED NUT FRONT	REPUTED	DMS-25-P-1-M-G E-2-6-F	L15A245
11	MP9106	D-CON 9 WAY MALE HEX CLINCHED NUT FRONT	REPUTED	DMS-9-P-1-M-G E-2-6-F	L15A243
12	MP9101,MP9102	CONN.AMP 3 WAY, X TYPE	AMP	1-178313-5	L15A087


OPERATOR PCB-E6VS091A203-00

PARTS LIST

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
OPERATOR PCB LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. H06



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	MP9700	CONN TAP HDR 6W AMP	AMP	1-178140-5	L15A117
2	MP9701, MP9703, MP9705	CONN TAP HDR 16W AMP	AMP	178327-5	L15A085
3	MP9702, MP9704 MP9706	CONN AMP HDR20W	AMP	316517-5	L15A183
4	MP9707	CONN AMP HDR20W	AMP	178328-5	L15A184
5	MP9708, MP9709	CONN AMP	AMP	1-178136-5	L15A086
6	R51, R52, R100A, R100B, R101A, R101B, R925, R930, R971, R972, R973	RELAY OMRON G2R-2-SND DC24V	OMRON	G2R-2-SND	L16B024
7	R51, R52, R100A, R100B, R101A, R101B, R925, R930, R971, R972, R973	RELAY SOCKET OMRON P2R-08P	ORMON	P2R-08P	L16B012
8	CB151A	CONN HONDA 50 PIN PCB FEMALE	HONDA	MR-50RFD2	L15A187
9	R1, R2	RESISTOR 10K OHM,2W	REPUTED	---	---
10	C1, C2	CAPACITOR,2200 UF,50V,ELECT	REPUTED	---	---
11	B1, B2	RECTIFIER BRIDGE 4A QBL406	REPUTED	---	---
12	D1, D2, D3	DIODE 1N4007	REPUTED	----	---


OPTION PCB-EE5VS97A703-XX

PARTS LIST

Revisions			Date	Name
④				
③		APPROVED	14-AUG-2012	GOH WILLIAM
②		CHECKED	14-AUG-2012	XING JY
①		DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC PCB LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. H07



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	VMP70	CONNECTOR AMP, 6WAY XY TYPE	AMP	3-178140-5	L15A088
2	VMP73	CONNECTOR AMP 5 WAY X TYPE	AMP	1-178315-5	L15A272
3	VMP79, VMP91, VMP92, VMP93, VMP94 VMP95, VMP96 (DUMMY)	CONNECTOR AMP, 8WAY X TYPE	AMP	1-178317-2	L15A143
4	VMP71	CONNECTOR HONDA, 25PIN	HONDA	MR-25RM	L15A309
5	F1, F2	FUSE (5A)	REPUTED	--	--
6	F3, F4	FUSE (5A)	REPUTED	--	--
7	CB15XA, CB15XB	CONNECTOR HONDA, 50PIN, FEMALE	HONDA	MR-50RFD2	L15A187
8	VMP78	CONNECTOR AMP, 20WAY	AMP	178308-5	L15A314
9	VMP72	CONNECTOR AMP, 16WAY	AMP	178327-5	L15A085
10	VMP74	CONNECTOR AMP, 12WAY	AMP	178326-5	L15A270
11	VMP75	CONNECTOR AMP, 20WAY	AMP	178328-5	L15A184
12	VMP80	CONNECTOR AMP, 16WAY	AMP	178327-5	L15A085
13	VMP81, VMP74	CONNECTOR AMP, 12WAY	AMP	178326-5	L15A270
14	LED	RED LED 5MM DIA	REPUTED	--	--
15	LED	GREEN LED 3MM DIA	REPUTED	--	--
16	TB1 ~ TB9	PCB TERMINAL S/5.08 SPACING	WAGO	255-401,255-100	L16B038
17	SL1780, SL1781 SL2601, SL2602, SL2603, SL2604, SL2311, SL1780, SL1781, SL2310, SL2311,	PHOTO MOS RELAY	PANASONIC	AQZ102	L16B073
18	LS912A, SL2701 SL2702, SL2703, SL2704, SL2705, SL2606, SL2607, SL2608, SL1783, SL1782,	PHOTO MOS RELAY SOCKET	PANASONIC	RL PA1a-PS MATSU	L16B074
19	RL6, RL7, RL8, RL9, RL40, RL41 (DUMMY)	PHOTO MOS RELAY	PANASONIC	AQZ102	L16B073


OPTION PCB-E7VS140A101-XX

PARTS LIST

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
HYDRAULIC PCB LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	=
				SHEET No. H08




NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO P/N.
1	ZMP41 (CE~CE PANEL)	50 WAY, HONDA FEMALE	HONDA	MR-50RFD2	L15A187
2	ZMP64 (EMG2) ZMP66(EMG1)	CONN, AMP 20 WAY	AMP	316517-5	L15A183
3	ZMP14	50 WAY, HIROSE	HIROSE	HIF3CB-50PA-2.54DSA	L15A114
4	ZMP42, ZMP43, ZMP44, ZMP45 ZMP47	CONN, AMP 6 WAY	AMP	0-0178323-2	L15A144
5	ZMP48	CONN, AMP 8 WAY	AMP	1-178317-5	L15A143
6	ZMP46 (100V)	CONN, AMP 3 WAY	AMP	1-178313-5	L15A087
7	MRCA, R7	RELAY	PANASONIC	S4EB-24V	L16B076
8	FUSE	FUSE 3 A	REPUTED	REPUTED	REPUTED

Revisions			Date	Name
	4			
	3	APPROVED	14-AUG-2012	GOH WILLIAM
	2	CHECKED	14-AUG-2012	XING JY
	1	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
CE PCB LAYOUT, PARTS	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. H09



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	EMG	PB EMERGENCY	FUJI	AR22V2R-01R	L11B058
2	SW930 AUTO/MANUAL	SELECTOR SWITCH	FUJI	AR22PR-11B	L11C044
3	SW940 AUTO START	PUSH BUTTON, GREEN	FUJI	AR22F0R-11G	L11B146
4	SW931 SEAT CHECK ON/OFF	KEY SWITCH	FUJI	AR22JR-2A10A	L11C079
5	LP930-MANUAL LP931-SEAT CHECK	PILOT LAMP, LED, WHITE PILOT LAMP, CONTACT BLOCK	TELEMECHANIQUE	ZB6-EB8B ZB6-DV1	L11B095 L11B170
6	LP933 ALARM	PILOT LAMP, RED	TELEMECHANIQUE	XB6-DV4BB	L11B139
7	LP932 SETUP FINISH	PILOT LAMP, GREEN	TELEMECHANIQUE	XB6-DV3BB	L11B138
8	PS8/LP8, PS9/LP9 AUTO DOOR OPEN/CLOSE SW935/LP935 SW936/LP936 PART CLAMP / UNCLAMP SW934/LP934 WORK WASH ENEABLE	PB ACTUATOR PB CONTACT BLOCK PB LENS PB LED	SCHLEGEL CONTROSYS	QXD BZL0I5 T25DKL T5.5K-4UY-24V	L11B046 L11B124 L11B055 L11B184


FIXTURE CONTROL PANEL FRONT VIEW - 6VS140A202-XX

PARTS LIST

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
FIXTURE CONTROL PANEL (STD M/C)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. H10



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	EMG	PB EMERGENCY	FUJI	AR22V2R-01R	L11B058
2	PS/LP 9701 APC READY PS/LP 9702 APC MANUAL PS/LP 9703 FEED HOLD PS/LP 9704 WORK WASH GUN ENABLE	PB ACTUATOR PB CONTACT BLOCK PB LENS PB LED	SCHLEGEL CONTROSYS	QXD BZL0I5 T25DKL T5.5K-4UY-24V	L11B046 L11B124 L11B055 L11B184


APC CONTROL PANEL FRONT VIEW - 5VS097A403-XX

PARTS LIST

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC CONTROL PANEL (APC)				=
	NC TYPE	FS0i-MC	V090i-C1E-Y04	SHEET No. H11



NO.	DESIGNATION	DESCRIPTION	MAKE	MFR PART NO.	MAKINO PART NO.
1	EMG	PB EMERGENCY	FUJI	AR22V2R-01R	L11B058
2	SW930 AUTO/MANUAL	SELECTOR SWITCH	FUJI	AR22PR-11B	L11C044
3	SW940 AUTO START	PUSH BUTTON, GREEN	FUJI	AR22F0R-11G	L11B146
4	SW931 SEAT CHECK ON/OFF	KEY SWITCH	FUJI	AR22JR-2A10A	L11C079
5	LP930-MANUAL LP931-SEAT CHECK	PILOT LAMP, LED, WHITE PILOT LAMP, CONTACT BLOCK	TELEMECHANIQUE	ZB6-EB8B ZB6-DV1	L11B095 L11B170
6	LP933 ALARM	PILOT LAMP, RED	TELEMECHANIQUE	XB6-DV4BB	L11B139
7	LP932 SETUP FINISH	PILOT LAMP, GREEN	TELEMECHANIQUE	XB6-DV3BB	L11B138
8	PS8/LP8, PS9/LP9 AUTO DOOR OPEN/CLOSE SW935/LP935 SW936/LP936 PART CLAMP / UNCLAMP SW934/LP934 WORK WASH ENEABLE	PB ACTUATOR PB CONTACT BLOCK PB LENS PB LED	SCHLEGEL CONTROSYS	QXD BZL0I5 T25DKL T5.5K-4UY-24V	L11B046 L11B124 L11B055 L11B184
9	PS/LP 9701 APC READY PS/LP 9702 APC MANUAL PS/LP 9703 FEED HOLD	PB ACTUATOR PB CONTACT BLOCK PB LENS PB LED	SCHLEGEL CONTROSYS	QXD BZL0I5 T25DKL T5.5K-4UY-24V	L11B046 L11B124 L11B055 L11B184

APC W/FIXTURE CONTROL PANEL FRONT VIEW - E6VS697A402-XX

PARTS LIST

Revisions			Date	Name
	④			
	③	APPROVED	14-AUG-2012	GOH WILLIAM
	②	CHECKED	14-AUG-2012	XING JY
	①	DRAWN	14-AUG-2012	PRAVEEN B

MAKINO
MAKINO ASIA PTE LTD

TITLE	MACHINE TYPE	SLIM3	DRAWING No.	GROUP
APC W/FIXTURE CONTROL PANEL(APC)(OPT)	NC TYPE	FS0i-MC	V090i-C1E-Y04	= SHEET No. H12