


PedalBrainz Update Instructions for Macintosh

Step 1: Installing Arduino, Setting up Board and Port

- 1) Install Arduino software for Mac: <https://www.arduino.cc/en/software>
- 2) Open Arduino
- 3) Click on “Arduino” tab at the top of the screen ☐ “Preferences”
- 4) Next to “Additional Boards Manager URLs,” copy and paste the URL below into the text box and then click “OK”:

COPY this URL:

https://adafruit.github.io/arduino-board-index/package_adafruit_index.json



- 5) Go to “Tools” ☐ “Board” ☐ “Boards Manager”
- 6) In Boards Manager, type "Adafruit SAMD" in the search bar; next, "Adafruit SAMD Boards" will appear in the results
- 7) Select the latest version of Adafruit SAMD Boards and click on “Install” button (Note: Installation may take from 3- 5 minutes)
- 8) When installation is complete, close Boards Manager
- 9) Go to “Tools” ☐ “Board” ☐ “Adafruit SAMD Boards” ☐ and select “Adafruit Gemma M0”
- 10) Connect the PedalBrainz to your computer via USB (the lights should flash on the unit)
- 11) Go to “Tools” ☐ “Port” ☐ choose the selection that has “Adafruit Gemma M0” next to the name

Step 2: Downloading and Installing Libraries


- 1) Pedal Brainz also uses two libraries that need to be installed in Arduino using the Library Manager:

Click on “Tools” □ “Manage Libraries”


- 2) In the Library Manager, type “Adafruit DotStar” in the search bar, then install “**Adafruit DotStar**” file by clicking on “Install” button and wait until installation is complete
- 3) Staying in the Library Manager, next, type “Flashstorage SAMD” in the search bar, then install “**FlashStorage_SAMD**” file by clicking on the “Install” button; wait until installation is complete
- 4) After both these two library files are installed, close the Library Manager

Step 3: Downloading PedalBrainz Files/ Uploading to Unit

- 1) Download the PedalBrainz Software
- 2) After download is complete, right-click on files □ “Open With” □ “Arduino”
- 3) A windows for the file will pop up in Arduino
- 4) Click on the Upload Button (the arrow icon pointing right) to upload the software to PedalBrainz



- 5) Once upload is complete, there will be text at the bottom stating “Done uploading.”



- 6) After “Done Uploading” message appears, you can now disconnect USB cable from PedalBrainz, and you’re now ready to use the unit!