

Designator	Quantity	Value	Comment	Description	Supplier 1	Supplier 2	Footprint
C1, C2	2	150uF/35V	3SPZE150M8X9	High temp hybrid capacitor -55/125C 150uF/35V	Mouser	Digi-Key	PZF8x9
C3, C4, C5, C6	4	1u	C1206C105K5RACTU	Ceramic Capacitor X7R 50V	Mouser	Digi-Key	C1206_medium
C7, C9	2	220uF/25V	25PZF220M8X9	High temp hybrid capacitor -55/125C 220uF/25V	Mouser	Digi-Key	PZF8x9
C8, C14, C18	3	47p NP0	GCM1885C2A470JA16J	Ceramic Capacitor NP0 100V	Mouser	Farnell	C0603
C10, C17	2	220n	C1206C224J1RACAUTO	Ceramic Capacitor X7R 100V	Mouser	Digi-Key	C1206_thin
C11, C19, C21	3	100n	06035C104K42ZA	Ceramic Capacitor X7R 50V	Mouser	Farnell	C0603
C12	1	100n	GRT31C5C2A104JA12L	Ceramic Capacitor NP0 100V	Mouser	Digi-Key	C1206_thin
C13	1	22n NP0	AC0603KRX7R9BB223	Ceramic Capacitor NP0 50V	Mouser	Farnell	C0603
C15, C16	2	10n	C0603X103K1RAC3316	Ceramic Capacitor X7R 100V	Mouser	Digi-Key	C0603
C20, C22	2	4.7u	CL10B475KQ8NQNC	Ceramic Capacitor X7R 6.3V	Mouser		C0603
C23	1	4.7uF	GRM31CC72A475ME11L	Ceramic Capacitor X7S 100V	Mouser	Digi-Key	C1206_thick
D1, D2	2	PMEG6030EXE	PMEG6030EXE-QX	Schottky Diode 60V, 3A	Digikey	Mouser	SOD123HP
D3, D4	2	NRVB0540T1G	NRVB0540T1G	Schottky Diode 40V, 500mA	Mouser	Farnell	SOD123HP
D5	1	3V6	PDZ3.6B,115	Zener Diode 3.6V, 400mW	Mouser	TME	SOD323
IC1	1		LM74700D-Q1	Reverse Battery Protection Ideal Diode Controller			SOIC127P600X175-8N
IC2	1		LTC3780IG#PBF	DC/DC Buck-Boost	Mouser	TME	SOP65P780X200-24N
Input1	1		XT60-PCB-M	XT60 Connector			XT60-PCB-M
L1	1	4.7uH 13A	7443551470	WE-HCI SMT High Current Inductor 4.7uH 20% 100kHz Ferrite 13A SMD T/R Frequency - Self Resonant 30MHz	Digikey	Mouser	WE-HCI
Output1	1		XT60-PCB-F	XT60 Connector			XT60-PCB-F
Q1, Q3, Q4, Q5	4	FDMC86102L	FDMC86102L	Single N-Channel 100V, 18A, 23mOhm	Mouser	Digi-Key	PowerPak1212_LFPAK33
Q2	1	BSC077N12NS3 G	BSC077N12NS3 G	Single N-Channel 120V, 98A, 7.7mOhm	Mouser	Digi-Key	Power56_LFPAK
R1, R3, R4	3	10R	CR0603-FX-10R0ELF	Resistor 1%, 0.1W, 75V	Mouser	Farnell	R0603
R2	1	0R015	GMR100HTBFER015	Current Sense Resistor 1%, 3W, AEC-Q200	Mouser	Digi-Key	Shunt_2512
R5, R8	2	100k	RC0603FR-07100KL	Resistor 1%, 0.1W, 75V	Mouser	Farnell	R0603
R6	1	10K	CRGP0603F10K	Resistor 1%, 0.1W, 75V	Mouser	Digi-Key	R0603
R7	1	180K	CRGCQ0603F180K	Resistor 1%, 0.1W, 75V	Mouser	Digi-Key	R0603
R9, R10	2	12K	CRGCQ0603F12K	Resistor 1%, 0.1W, 75V	Mouser	Digi-Key	R0603