

kea: A Python package for consistent power spectral analysis of data on arbitrary dimensions

Mark A. Bishop^{1*}, Sean Oughton^{2*}, Tulasi N. Parashar^{1*}, and Yvette C. Perrott^{1*}

¹ School of Chemical and Physical Sciences, Victoria University of Wellington, Wellington 6012, New Zealand ² Department of Mathematics, University of Waikato, Hamilton 3240, New Zealand * These authors contributed equally.

DOI: [10.xxxxxx/draft](https://doi.org/10.xxxxxx/draft)

Software

- [Review](#)
- [Repository](#)
- [Archive](#)

Editor: [Open Journals](#)

Reviewers:

- [@openjournals](#)

Submitted: 01 January 1970

Published: unpublished

License

Authors of papers retain copyright and release the work under a Creative Commons Attribution 4.0 International License ([CC BY 4.0](#))

Summary

Power spectral density techniques are widely used across disciplines but often differ in normalization and data handling, with most fields relying on a limited set of established methods. Historically, researchers have been required to implement their own routines or personally request code from others. This increases barriers to entry for performing analysis and requires a deep understanding of specific Fourier conventions to avoid errors. Without a standardized framework, order-unity normalization difference often creep in, which can lead to physical inferences that are mathematically inconsistent or physically erroneous. To address this, we present a computational package that provides consistently normalized estimators that are adaptable to multiple data types – including ICM surface brightness fluctuations, in-situ solar wind time-series, and simulation cubes.

Statement of need & state of the field

Autocorrelation functions (ACF), power spectral densities (PSD), and structure functions (SF) serve as the primary mathematical framework for quantifying the statistical properties of stochastic phenomena across varying spatial and temporal scales. In the context of fluid dynamics and astrophysics, these tools allow researchers to decompose complex, multiscale signals into their constituent parts. Of particular interest, especially within the study of (magneto)-hydrodynamic turbulence, are the characteristic scales (such as the integral scale L where energy is injected, and the dissipation scale η), the power-law indices that define the energy cascade (e.g., the Kolmogorov $-5/3$), and their respective amplitudes which dictate the total turbulent energy budget.

These phenomena are rarely captured in the full continuum of values in the available space in which measurements occur. In other words, in a lot of practical cases, observations are restricted to only 1D slices, 2D projections, or 2D slices. For example, in the case of the solar wind, in-situ measurements are performed by sensors moving in relation to the plasma rest frame. These sensors generate a time-series of data: such as magnetic field (vector field), or density (scalar field) measurements. As another pertinent example, surface brightness observations of the intracluster medium (ICM) observe 2D (emission weighted) projections of scalar fields, or projections of line-of-sight components of a vector field. Often these observations are calibrated or compared against more accessible regimes, or high-fidelity simulations.

Beyond the choice of statistical tool, the reliability of the output is heavily dependent on the nuances of spectral estimation. There exists a vast library of signal processing techniques designed to mitigate the distortions, aliasing, and biases inherent in finite sampling ([Maciejewski](#)

et al., 2009; Sefusatti et al., 2016; Stoica & Moses, 2005). However, the implementation of these techniques introduces its own set of variables: how the data are windowed to prevent spectral leakage, how the estimates are binned in k -space, and how the resulting power is normalized (e.g., ensuring Parseval's theorem is satisfied). For example, (Barbour & Parker, 2022) find a total of six different R packages that provide spectrum estimations with varying normalization options.

If these methodological choices are not standardized, they can induce spurious physical behavior. For example, improper binning can artificially flatten a spectral slope. This could become a significant issue when comparing across different studies or when cross-correlating observational data with numerical models. Without a rigorous, consistent approach to these estimations, the resulting physical interpretations (such as the inferred viscosity of the ICM) may reflect the limitations of the signal processing rather than the underlying plasma physics.

While the mathematical definitions of autocorrelation functions, power spectral densities and structure functions are well-established, their application to “real-world” astrophysical datasets is fraught with nuance. For example, normalizations of the (Arévalo et al., 2012) (i.e., difference-of-Gaussian) method differ (Arévalo et al., 2012; Churazov et al., 2012; Zhou et al., 2022).

Current available software for ICM turbulence analysis are: turbustat (Koch et al., 2019), and PITSZI (Adam et al., 2024). Both of these solutions require 2D data, thus are not readily available for comparisons with e.g., solar wind turbulence analysis, or simulation cubes. Additionally, they both use a nested sequence of object-oriented class based design with build-in handling with assumptions for their respective fields: the interstellar medium for turbustat, and the intracluster medium for PITSZI. Hence, modifying for individual needs is challenging. SF calculation is available using fastSF (Sadhukhan et al., 2021), however, only for uniform 2D and 3D datasets. In other words, gapped datasets are not applicable. SF calculation is also available in Python with fluidsf (Wagner et al., 2025).

We thereby introduce Kea (because Mark doesn't kea. Or, alternatively: **A**nalysis **E**ngine **M**ar**K**, backwards), a Python package that implements several different dimensionally-agnostic PSD estimation techniques for use in turbulence analysis. Kea is available on GitHub via <https://github.com/mab68/Kea>.

Implementation Details

The data we obtain in real life is not the continuous data, but rather, a discrete function that is obtained by sampling an underlying continuous function, y_c , at an interval Δx . This gives the discrete function $y[n]$ and its Fourier transform $\hat{y}[m]$, defined as the following:

$$y[n] = y_c(n\Delta x) = y_c(x),$$

$$\hat{y}[m] = \hat{y}_c(m\Delta k) = \hat{y}_c(k),$$

where $x = n\Delta x$, and $k = m\Delta k$ with $m, n \in \mathcal{Z}$ (integers).

We assume that $y_c(x)$ is periodic on the domain $x \in [0, L]$ such that $y_c(x) = y_c(x+L)$ and we have sampled N evenly separated points within this domain, our sampling interval is $\Delta x = L/N$. Here, L represents the physical domain and N the number of grid points. The discrete function will also be periodic $y[n] = y[n+N]$ for $n \in [0, N-1]$, $m \in [-N/2, N/2]$. As a result, the Fourier-space function is also periodic $\hat{y}_c(k) = \hat{y}_c(k+N\Delta k)$ where $\Delta k = \frac{2\pi}{N\Delta x} = \frac{2\pi}{L}$ and $k \in [-\pi N/L, \pi N/L]$. Alternatively, a non-periodic signal is assumed to be $y_c(x) = 0$ for $x > L$. Note that mathematically, the DFT treats the signal as periodic regardless so the function should be padded with zero's to ensure there is minimal spectral leakage due to a discontinuity at the boundary.

The last step in this process is to acknowledge the following relation for the discretization of the complex exponential term: $xk = (n\Delta x)(m\Delta k) = nm\Delta x 2\pi/(N\Delta x) = 2\pi nm/N$.

88 Applying the relations stated gives us the discrete form of the continuous signal and its Fourier
89 transform, where we have also replaced dx , dk with Δx , Δk respectively (Allen et al., 2012):

$$y[n] = \Delta k \sum_{m=-N/2}^{N/2} \hat{y}[m] e^{2\pi i n m / N},$$

90

$$\hat{y}[m] = \frac{\Delta x}{2\pi} \sum_{n=0}^{N-1} y[n] e^{-2\pi i n m / N}.$$

91 We can derive the generalized D -dimensional form of the DFT using the same arguments
92 provided above, which we state as the following:

$$y[\mathbf{n}] = (\Delta k)^D \sum_{\mathbf{m}} \hat{y}[\mathbf{m}] e^{2\pi i \mathbf{n} \cdot \mathbf{m} / N},$$

93

$$\hat{y}[\mathbf{m}] = \left(\frac{\Delta x}{2\pi} \right)^D \sum_{\mathbf{n}} y[\mathbf{n}] e^{-2\pi i \mathbf{n} \cdot \mathbf{m} / N},$$

94 where the summations are over all $\mathbf{n}$ e.g., $\sum_{\mathbf{n}} = \sum_{n_1=0}^{N_1-1} \sum_{n_2=0}^{N_2-1} \dots \sum_{n_D=0}^{N_D-1}$.

95 The D -dimensional DFT is implemented using the NumPy.fft routines which is then multiplied
96 by the correct scaling factor. The DFT is called using the NumPy.fft.fftn method, and the
97 wavenumbers are obtained using the NumPy.fft.fftfreq, providing the number of sampled
98 data points N (this gives m/N for $m \in [-N/2, N/2]$) which is subsequently multiplied by
99 $2\pi/\Delta x$ to get the *angular* wavenumbers.

100 The DFT is well-defined when $y[\mathbf{n}] \in \mathcal{R}$, however, particularly it is not always the case that
101 $y[\mathbf{n}]$ has such values for all $\mathbf{n} \in \{1, \dots, N-1\}$ with constant $\Delta x = L/N$. This can be
102 due to a myriad of reasons depending on the observation type, but generally, it will result in
103 “gaps” in the data. To retain uniform sampling, a gap in $y[\mathbf{n}]$ is represented by NaN (not a
104 number; NumPy.nan). However, most implementations of the above discrete Fourier transforms
105 do not behave when $y[\mathbf{n}]$ has NaN values. Hence, alternative spectral estimation methods are
106 frequently used.

107 Lag Functions

108 First, we introduce the class of functions termed the “lag-function” which use the same backend
109 i.e., performing some operation (where the ACF performs multiplication, and the SF performs
110 subtraction) on data that has been shifted by a lag distance.

111 Autocorrelation Function

112 The autocorrelation function is estimated via:

$$R[\mathbf{m}] = \frac{1}{\tilde{N}[\mathbf{m}]} \sum_{\mathbf{n}} y[\mathbf{n}] y[\mathbf{n} + \mathbf{m}], \quad (1)$$

113 where $\tilde{N}$ is a normalization by the number of pixels, and $\mathbf{m}$ is a lag-distance in real-space pixels
114 (rather than the wavenumbers, above), and the summation is over the *available* data (i.e., we
115 ignore NaN values). The shift has to cut both $y[\mathbf{n}]$ and $y[\mathbf{m}]$ such that only the overlapping
116 sequence (of equal length $N - m$) is present (Sadhukhan et al., 2021).

117 There are typically two standard ways of normalizing Equation 1, either: $\tilde{N}[m] = N - m - 1$,
118 or $\tilde{N}^{\text{biased}}[m] = N$. Where, for D -dimensions, $\tilde{N}[\mathbf{m}] = (N_1 - m_1 - 1) \dots (N_D - m_D - 1)$
119 and $\tilde{N}^{\text{biased}}[m] = N^D$. If $\tilde{N}[m] = N - m - 1$ is used, then Equation 1 is sometimes
120 called the standard unbiased ACF estimate. In this case, for large lags the factor $\frac{1}{\tilde{N}[m]}$

becomes large; because the average is calculated over relatively few products, the estimate is not statistically well-constrained and is prone to high variance. However, practically large m samples inhomogeneities beyond the correlation scale, so only up to a maximum lag of $m_{\max} = \frac{N}{2}$ (or even $m_{\max} = \frac{N}{4}$) should be taken. In which case, the unbiased estimator (with $\tilde{N}[m] = N - m - 1$) has $\approx 50\% - 75\%$ of N at $m = m_{\max}$ and can be statistically reliable. If the biased estimator is used, then Equation 1 more closely resembles the continuous ACF in the case of non-periodic $y[n]$:

$$R[\mathbf{m}] = \left(\frac{\Delta x}{L}\right)^D \sum_{\mathbf{n}} y[\mathbf{n}]y[\mathbf{n} + \mathbf{m}] = \frac{1}{N^D} \sum_{\mathbf{m}} y[\mathbf{n}]y[\mathbf{n} + \mathbf{m}],$$

for $\Delta x = L/N$.

Structure Function

The SF follows the ACF, as,

$$S^{(p)}[\mathbf{m}] = \frac{1}{\tilde{N}[\mathbf{m}]} \sum_{\mathbf{n}} |y[\mathbf{n}] - y[\mathbf{n} + \mathbf{m}]|^p,$$

for the choice of $\tilde{N}[\mathbf{m}] = (N_1 - m_1 - 1) \dots (N_D - m_D - 1)$, and we ignore NaN values. The unbiased estimator is typically used with (at most) $m_{\max} = \frac{N}{2}$.

Spectral Estimates

Now, we introduce the discrete form of the spectral estimation techniques.

Periodogram

The periodogram spectral estimate is simply, (Schuster, 1898)

$$E^{\text{FFT}}[\mathbf{m}] = |\hat{y}[\mathbf{m}]|^2 \Delta k^D.$$

This is an estimation of the modal spectrum (hence the vector $\mathbf{m}$ argument) which needs to be subsequently angle-averaged or angle-integrated. When $y[\mathbf{n}]$ has NaN values, often these values are instead interpolated (e.g., with the average, or linearly).

Correlogram/Blackman-Tukey

The Blackman-Tukey (BT; sometimes called a correlogram) method (Blackman et al., 1960) uses the (discrete) Fourier transformation of the ACF given by,

$$E^{\text{BT}} = \Re \{ \widehat{Q}[\mathbf{m}] \},$$

where $\widehat{Q}[\mathbf{n}]$ is the (discrete) Fourier transform of the ACF multiplied by a window function, $W[\mathbf{n}]$:

$$Q[\mathbf{n}] = R[\mathbf{n}]W[\mathbf{n}].$$

Note that with the unbiased normalization ($\tilde{N}[m] = N - m - 1$), $\widehat{Q}[\mathbf{m}]$ is not guaranteed to be positive semi-definite and there may result in negative spectral estimates which is undesirable in most applications (Stoica & Moses, 2005).

Equivalent Spectrum

To estimate a power spectrum using the structure function, first, you must:

- Calculate the second-order structure function: $S^{(2)}[\mathbf{m}]$.

151 ▪ Average (bin) the second-order structure function over shells of magnitude $m = |\mathbf{m}|$:
 152 $\bar{S}^{(2)}[m]$.

153 Then, the following algorithm is performed:

154 ▪ Estimate an “uncorrected” equivalent spectrum, $\tilde{\mathcal{E}}^{\text{ESF}}[m]$ using the following relationship:

$$\mathcal{E}^{\text{ESF}}[m] = \frac{1}{2} \frac{1}{b} (m\Delta x)^2 \frac{\Delta \bar{S}^{(2)}[m]}{\Delta(m\Delta x)},$$

155 where $\frac{\Delta \bar{S}^{(2)}[m]}{\Delta(m\Delta x)}$ represents a finite-difference estimate of the derivative. In the above
 156 equation, m still represents the lag-shift. To convert to a wavenumber, a factor b is
 157 required.

158 ▪ Estimate the local power-law slope of the “uncorrected” spectrum.
 159 ▪ Use an analytical expression for the bias for a pure power-law to derive a wavenumber
 160 dependent correction factor.
 161 ▪ Return a “debiased” spectrum: $\mathcal{E}^{\text{ESF}}[m]$.

162 kea performs the above algorithm and returns both the “uncorrected” and “debiased” spectral
 163 estimates along with the associated (equivalent) wavenumbers.

164 See, (Bishop et al., 2026) for further details and validation.

165 Difference of Gaussian

166 The difference-of-Gaussian method is described for the continuous case with no gaps; there
 167 are additional convolutions that can be performed to account for gaps in the data (Arévalo et
 168 al., 2012; Ossenkopf et al., 2008).

169 First, we define the real-space scale σ , and the corresponding pixel-space scale o as,

$$\sigma = o\Delta x = bk^{-1} = b(m\Delta k)^{-1}.$$

170 For $k = \{\frac{2\pi}{L}, \dots, \frac{\pi N}{L}\}$, then $\sigma = \{\frac{bL}{\pi N}, \dots, \frac{bL}{2\pi}\}$ and $o = \{\frac{b}{\pi}, \dots, \frac{bN}{2\pi}\}$. Similar to the ESF
 171 method, $b = \pi$ would be a natural conclusion to arrive at based on a signal in a domain L ,
 172 however (Bishop et al., 2026) suggest otherwise. A common interpretation is $b = \sqrt{2}$ (Arévalo
 173 et al., 2012).

174 For the pixel-scale o , the normalized scale-filtered field is,

$$y_o[\mathbf{n}] = M[\mathbf{n}] \Xi[\mathbf{n}] \frac{(y * G_o)[\mathbf{n}]}{(\Xi * G_o)[\mathbf{n}]},$$

175 where `ndimage.gaussian_filter` is used to perform the discrete convolution (by default,
 176 `scipy` is used but if a GPU is configured the `cupyx` library can be used instead). The Gaussian
 177 function is truncated at $10 \times o$ to increase performance (smaller truncations were found to
 178 provide insufficient accuracy in certain circumstances). The function $\Xi[\mathbf{n}]$ represents a (general)
 179 floating-point exposure map (for e.g., X-ray surface brightness observations where $\Xi[\mathbf{n}] = 1$
 180 represents a pixel that has relative complete observation) that also defines the boolean mask,

$$M[\mathbf{n}] = \begin{cases} 1 & \text{where } \Xi[\mathbf{n}] > 0, \\ 0 & \text{otherwise,} \end{cases}$$

181 which ensures we are not counting regions that should be masked. In other words, $\Xi[\mathbf{n}]$
 182 characterizes the locations of the gapped data.

183 For σ values that are nearly equal (with $\xi \approx 10^{-3}$)

$$\sigma_1 = o_1\Delta x = \frac{\sigma}{\sqrt{1+\xi}}, \sigma_2 = o_2\Delta x = \sigma\sqrt{1+\xi},$$

184 the scale-filtered variance is,

$$V[o] = \sum_{\mathbf{n}} (y_{o_1}[\mathbf{n}] - y_{o_2}[\mathbf{n}])^2,$$

185 which is then normalized to get the angle-averaged spectrum:

$$\overline{E}^{\text{DoG}}[o] = \frac{N^D}{\sum_{\mathbf{n}} \Xi[\mathbf{n}]} \frac{V[o]}{\sum_{\mathbf{n}} (G_{o_1}[\mathbf{n}] - G_{o_2}[\mathbf{n}])^2} N^{-2D},$$

186 where o is related to the Fourier-space $m = \frac{b}{o} \frac{1}{\Delta x \Delta k}$.

187 Binning

188 Since the ACF, SF, and FFT, and BT spectral estimates provide D -dimensional functions, it is
189 useful to bin them to reduce the dimensionality. Kea provides a general binning routine that
190 applies to the spectral estimates as well as the lag-functions.

191 With bin-width $\Delta b = x_+ - x_-$ and $b \in \mathcal{R}$,

$$F[b] = \widetilde{\sum}_{x_- \leq |\mathbf{n} \Delta x| < x_+} f[\mathbf{n}],$$

192 where the following options are provided as parameters for the routine:

- 193 ■ Provide a binning function $\widetilde{\sum}$ which is typically e.g., an average, or a summation, or a
194 standard error to describe the variation within the bin.
- 195 ■ Whether to ignore the range of values that are outside the circular or spherical shell
196 (since the data is represented on a square/cubic grid).
- 197 ■ Defining specific minimum and maximum b : $b_{\min}, b_{\max}$.
- 198 ■ The location of the number that represents the bin e.g., the center of the bin ($b =$
199 $(x_+ + x_-)/2$), or the left most value ($b = x_-$).
- 200 ■ Whether to apply a normalization of the bin width: Δb^{-1} .
- 201 ■ Bin with log-spaced widths. In which case, the bins are uniformly spaced in log-space.
- 202 ■ Specify a fixed specific number of bins, N_{bins} .

203 Following the continuous definitions the ACF and SF are typically represented via averaging
204 the circular/spherical shells¹. Whereas, the angle-integrated and angle-averaged spectra are
205 found when $\widetilde{\sum}$ is the summation and average, respectively:

$$\mathcal{E}[b] = \frac{1}{\Delta b} \sum_{k_- \leq |\mathbf{k}| < k_+} E[\mathbf{m}] (\Delta k)^D,$$

$$\overline{E}[b] = \frac{1}{K_D[b]} \sum_{k_- \leq |\mathbf{k}| < k_+} E[\mathbf{m}] (\Delta k)^D.$$

206 where $K_D[b]$ is the number of pixels within the bin-range (thus defining the function that
207 averages) and we apply an additional normalization by the bin-width Δb^{-1} (which ensures
208 unit consistency and that $\sum \mathcal{E}[b] \Delta b$ is the total energy). Their relation is found via: $\mathcal{E}[b] =$
209 $K_D[b] \overline{E}[b] / \Delta b$ (assuming the remaining binning properties are kept the same). The bin-shell
210 volume coefficients for centered ($b_1 = b - \Delta b/2$, $b_2 = b + \Delta b/2$), or left-edge bins ($b_1 = b$,
211 $b_2 = b + \Delta b$) are:

$$K_D[b] = \frac{V(b_1) - V(b_2)}{(\Delta k)^D}$$

213 where

$$V(r) = \frac{r^D \pi^{D/2}}{\Gamma(D/2 + 1)}$$

214 is the volume of a D -dimensional hypersphere.

¹In the case of 1D data, there are exactly 2 values for each $|\mathbf{k}|$: the positive and negative value.

Synthesis of Stochastic Fields

Power-law correlations are a key feature of turbulence (particularly with high Reynolds numbers flows). The scale-by-scale energy transfer associated with the cascade of energy from large scales to smaller scales leads to a power-law power spectrum which is indicative of fractal-like structure where small-scale features are statistically similar to large-scale ones.

Observing the complete set of information provided by self-similar physical phenomena can be practically challenging. In particular, we highlight that the majority of astronomy and astrophysical observations are driven by the detection and manipulation of photons. The properties of these photons are determined by the conditions of the source (temperature, density, velocity, etc.) of the emitting material and its subsequent interaction with any intervening material. Determining the conditions of the source from the photons alone can be a serious challenge. Noise and resolution constraints may also limit the accuracy of the inference and increase complexity. To understand biases and systematics or comparison of theory to observation, where data is lacking, it can be necessary to compute expected observational properties from controlled surrogate models (Haworth et al., 2018; Simionescu et al., 2019).

For example, synthetic fields have been used extensively to validate methods for interstellar turbulence e.g., (Brunt & Heyer, 2002; Esquivel et al., 2003; Miville-Deschênes et al., 2003; Ossenkopf et al., 2006). Synthetic fields have similarly been used for the ICM when measuring turbulence e.g., (Vogt & EnBlin, 2005; XRISM Collaboration et al., 2025; ZuHone et al., 2016).

kea provides methods to produce (monofractal and multifractal) synthetic fields with correlations parameterized by power spectral density. Following (Barnsley et al., 1988; Lakhal et al., 2023), these fields are synthesized in Fourier-space and Fourier-transformed to provide real-space fluctuation fields. Thus, the above PSD estimators can be tested for validity with known/expected forms, and their performance tested under constraints of noise and missing data.

Future Work

It is intended for future development of kea to implement a general interpretation of spectral estimation using arbitrary filters along with automatic implementation of debiasing using the non-parametric local power-law approximation that is currently only available for the ESF method.

Another area of potential improvement will be the implementation of synthetic fields with anisotropy. This would be useful to test the statistics of projected fluctuations in more complex scenarios.

Acknowledgements

This project was supported by the Marsden Fund Council from New Zealand Government funding, managed by Royal Society Te Apārangi (No. E4200).

References

- Adam, R., Eynard-Machet, T., Bartalucci, I., Cherouvrier, D., Clerc, N., Di Mascolo, L., Dupourqué, S., Ferrari, C., Macías-Pérez, J.-F., Pointecouteau, E., & Pratt, G. W. (2024). PITSZI: Probing Intra-cluster medium Turbulence with Sunyaev-Zel'dovich Imaging – Application to the triple merging cluster MACS J0717.5+3745. In *arXiv e-prints*. <https://doi.org/10.48550/arXiv.2409.14804>

- 257 Allen, B., Anderson, W. G., Brady, P. R., Brown, D. A., & Creighton, J. D. E. (2012).
258 FINDCHIRP: An algorithm for detection of gravitational waves from inspiraling compact
259 binaries. *Physical Review D*, 85, 122006. <https://doi.org/10.1103/PhysRevD.85.122006>
- 260 Arévalo, P., Churazov, E., Zhuravleva, I., Hernández-Monteagudo, C., & Revnivtsev, M.
261 (2012). A Mexican hat with holes: Calculating low-resolution power spectra from data
262 with gaps. *Monthly Notices of the Royal Astronomical Society*, 426, 1793–1807. <https://doi.org/10.1111/j.1365-2966.2012.21789.x>
- 263
- 264 Barbour, A. J., & Parker, R. L. (2022). *Normalization of Power Spectral Density Estimates*.
265 <https://cran.rstudio.com/web/packages/psd/index.html>
- 266 Barnsley, M. F., Devaney, R. L., Mandelbrot, B. B., Peitgen, H.-O., Saupe, D., & Voss, R.
267 F. (1988). *The Science of Fractal Images* (H.-O. Peitgen & D. Saupe, Eds.). Springer.
268 <https://doi.org/10.1007/978-1-4612-3784-6>
- 269 Bishop, M. A., Oughton, S., Parashar, T. N., & Perrott, Y. C. (2026). Direct power spectral
270 density estimation from structure functions without Fourier transforms. *Physics of Fluids*,
271 38(2), 025107. <https://doi.org/10.1063/5.0310561>
- 272 Blackman, R. B., Tukey, J. W., & Teichmann, T. (1960). The Measurement of Power Spectra.
273 *Physics Today*, 13, 52. <https://doi.org/10.1063/1.3056826>
- 274 Brunt, C. M., & Heyer, M. H. (2002). Interstellar Turbulence. I. Retrieval of Velocity Field
275 Statistics. *The Astrophysical Journal*, 566, 276–288. <https://doi.org/10.1086/338031>
- 276 Churazov, E., Vikhlinin, A., Zhuravleva, I., Schekochihin, A., Parrish, I., Sunyaev, R., Forman,
277 W., Böhringer, H., & Randall, S. (2012). X-ray surface brightness and gas density
278 fluctuations in the Coma cluster. *Monthly Notices of the Royal Astronomical Society*, 421,
279 1123–1135. <https://doi.org/10.1111/j.1365-2966.2011.20372.x>
- 280 Esquivel, A., Lazarian, A., Pogosyan, D., & Cho, J. (2003). Velocity statistics from spectral
281 line data: Effects of density-velocity correlations, magnetic field and shear. *Monthly*
282 *Notices of the Royal Astronomical Society*, 342, 325–336. <https://doi.org/10.1046/j.1365-8711.2003.06551.x>
- 283
- 284 Haworth, T. J., Glover, S. C. O., Koepferl, C. M., Bisbas, T. G., & Dale, J. E. (2018).
285 Synthetic observations of star formation and the interstellar medium. *New Astronomy*
286 *Reviews*, 82, 1–58. <https://doi.org/10.1016/j.newar.2018.06.001>
- 287 Koch, E. W., Rosolowsky, E. W., Boyden, R. D., Burkhart, B., Ginsburg, A., Loeppky, J. L., &
288 Offner, S. S. R. (2019). TURBUSTAT: Turbulence Statistics in Python. *The Astronomical*
289 *Journal*, 158, 1. <https://doi.org/10.3847/1538-3881/ab1cc0>
- 290 Lakhal, S., Ponson, L., Benzaquen, M., & Bouchaud, J.-P. (2023). *Wrapping and unwrapping*
291 *multifractal fields* (No. arXiv:2310.01927). arXiv. <https://doi.org/10.48550/arXiv.2310.01927>
- 292
- 293 Maciejewski, M. W., Qui, H. Z., Rujan, I., Mobli, M., & Hoch, J. C. (2009). Nonuniform
294 sampling and spectral aliasing. *J Magn Reson*, 199(1), 88–93. <https://doi.org/10.1016/j.jmr.2009.04.006>
- 295
- 296 Miville-Deschênes, M.-A., Levrier, F., & Falgarone, E. (2003). On the Use of Fractional
297 Brownian Motion Simulations to Determine the Three-dimensional Statistical Properties of
298 Interstellar Gas. *The Astrophysical Journal*, 593, 831–847. <https://doi.org/10.1086/376603>
- 299 Ossenkopf, V., Esquivel, A., Lazarian, A., & Stutzki, J. (2006). Interstellar cloud structure:
300 The statistics of centroid velocities. *Astronomy and Astrophysics, Volume 452, Issue 1,*
301 *June II 2006, Pp.223-236, 452(1), 223.* <https://doi.org/10.1051/0004-6361:20052754>
- 302 Ossenkopf, V., Krips, M., & Stutzki, J. (2008). Structure analysis of interstellar clouds. II.
303 Applying the Δ -variance method to interstellar turbulence. *Astronomy and Astrophysics*,

- 304 485(3), 719–727. <https://doi.org/10.1051/0004-6361:20079107>
- 305 Sadhukhan, S., Bhattacharya, S., & Verma, M. K. (2021). fastSF: A parallel code for
306 computing the structure functions of turbulence. *Journal of Open Source Software*, 6(57),
307 2185. <https://doi.org/10.21105/joss.02185>
- 308 Schuster, A. (1898). On the investigation of hidden periodicities with application to a supposed
309 26 day period of meteorological phenomena. *Terrestrial Magnetism (Journal of Geophysical*
310 *Research)*, 3, 13. <https://doi.org/10.1029/TM003i001p00013>
- 311 Sefusatti, E., Croce, M., Scoccimarro, R., & Couchman, H. M. P. (2016). Accurate estimators
312 of correlation functions in Fourier space. *Monthly Notices of the Royal Astronomical*
313 *Society*, 460(4), 3624–3636. <https://doi.org/10.1093/mnras/stw1229>
- 314 Simionescu, A., ZuHone, J., Zhuravleva, I., Churazov, E., Gaspari, M., Nagai, D., Werner,
315 N., Roediger, E., Canning, R., Eckert, D., Gu, L., & Paerels, F. (2019). Constraining
316 Gas Motions in the Intra-Cluster Medium. *Space Science Reviews*, 215, 24. <https://doi.org/10.1007/s11214-019-0590-1>
- 317
- 318 Stoica, P., & Moses, R. (2005). *Spectral Analysis of Signals*. Pearson Prentice Hall Upper
319 Saddle River, NJ.
- 320 Vogt, C., & Enßlin, T. A. (2005). A Bayesian view on Faraday rotation maps Seeing the
321 magnetic power spectra in galaxy clusters. *Astronomy and Astrophysics, Volume 434, Issue*
322 *1, April IV 2005, Pp.67-76*, 434(1), 67. <https://doi.org/10.1051/0004-6361:20041839>
- 323 Wagner, C. M., Lee, A., & Pearson, B. (2025). FluidSF: A Python package for calculating
324 turbulent flow statistics. *Journal of Open Source Software*, 10(114), 7873. <https://doi.org/10.21105/joss.07873>
- 325
- 326 XRISM Collaboration, Audard, M., Awaki, H., Ballhausen, R., Bamba, A., Behar, E., Boissay-
327 Malaquin, R., Brenneman, L., Brown, G. V., Corrales, L., Costantini, E., Cumbee, R.,
328 Diaz Trigo, M., Done, C., Dotani, T., Ebisawa, K., Eckart, M. E., Eckert, D., Eguchi,
329 S., ... Zuhone, J. (2025). XRISM Forecast for the Coma Cluster: Stormy, with a Steep
330 Power Spectrum. *The Astrophysical Journal*, 985, L20. <https://doi.org/10.3847/2041-8213/add2f6>
- 331
- 332 Zhou, Y., Mitsuda, K., & Yamasaki, N. Y. (2022). Spatial Power Spectral Analysis of the Suzaku
333 X-Ray Background. *The Astrophysical Journal*, 929, 128. <https://doi.org/10.3847/1538-4357/ac5966>
- 334
- 335 ZuHone, J. A., Markevitch, M., & Zhuravleva, I. (2016). Mapping the Gas Turbulence
336 in the Coma Cluster: Predictions for Astro-H. *The Astrophysical Journal*, 817, 110.
337 <https://doi.org/10.3847/0004-637X/817/2/110>