



Specifications: Advance Shipment Notice (DESADV D.07A)

DESADV Spec

DESADV File Example (WITH Packaging)	Details (Important fields)
UNA:+,? '	
UNB+UNOC:3+Sender_ID+Receiver-ID+180613:1423+8327'	Unique Sender/Receiver combination for each plant
UNH+1+DESADV:D:07A:UN'	ACCUPATION OF THE PROPERTY OF
BGM+351+0211808373'	ASN or Bill of Lading Number
DTM+137:20180613:102'	ASN / Ship Date (CCYYMMDD)
DTM+132:20180614:102'	Estimated arrival date (CCYYMMDD)
MEA+AAX+AAD+KGM:974'	Gross weight
MEA+AAX+AAL+KGM:959'	Net weight
RFF+AAS:0211808373'	Transport-document-ref/Tracking-number
	Buyer = Conti plant Code from DELFOR (Default)
NAD+BY+XXXX::92'	Can be account at vendor value per request
NAD+ST+XXXX::92'	Ship To = Continental Plant Code from DELFOR
NAD+SU+0000XXXXXX::92'	Continental SAP Supplier ID
	Means of transport
TDT+12+12345+30++FDXI'	If available, provide SCAC Code and Transport Mode
	Many locations in North America request this code
	(Example = FDXI and "30" values mean delivery by FedEx via Road)
CPS+1++1'	Packaging sequence (++1 = inner package, example = box)
	Package: quantity with packaging item number
PAC+20++98-4500-6417-0-00::92'	Article number refers to inner package (inner package example = box)
	Article number for box or pallet can be different from plant to plant (example: 20 boxes with item
	number)
QTY+52:180:PCE'	Actual quantity per inner package
PCI+17+XXXXXX++S::92'	Package identification type
	Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Reference to outer package (example = metal crate or pallet)
RFF+ACI:12811063'	
GIN+ML+943692001'	Label number on outer package
GIN+ML+943692001'	Label serial number(s) - example of 20 labels
GIN+ML+543092002	Label serial number(s) - example of 20 labels
GIN+ML+943692019'	inserted to shorten example length GIN+ML required for serial number values 03 -> 18
GIN+ML+943692019'	Label serial number(s) - example of 20 labels
GIN+ML+343092020	Label serial number(s) - example of 20 labels Continental material number
LIN+1++11-8105-1646-2-00:IN'	
	Maximum occurrence of segment/group = 1
	Usage of single line items required
	Multiple line items cannot be processed Supplier's article number (SA)
PIA+1+201490216:SA'	Can also include: Revision number (DR), Enginnering change level (E),
	, ,, ,
OMV 12 - 2600 - DCE	General specification number (GS), Color number (CL)
QTY+12:3600:PCE'	
**	Total dispatched quantity (example: 20 boxes x 180 Pieces)
ALI+IT'	Country of origin
**	Country of origin Order reference / PO Number
ALI+IT'	Country of origin Order reference / PO Number Packaging sequence (++3=outer)
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc)
ALI+IT' RFF+ON:55000XXXXX'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet)
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pav attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that pallet
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that pallet inserted to shorten example length GIN+AW required for serial number values 03 -> 18
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet Reference to boxes on that pallet
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00::92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pav attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00:92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019' GIN+AW+943692020' CPS+3++2'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet required for serial number values 03 -> 18 Reference to boxes on that pallet Reference to boxes on that pallet Packaging sequence (++2= packaging aid materialexample: lid or box divider/separator) Outer/pallet required if using packaging aid material
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00:92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019' GIN+AW+943692020' CPS+3++2' PAC+1++98-4500-1208-0-00::92'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet Packaging sequence (++2= packaging aid materialexample: lid or box divider/separator) Outer/pallet required if using packaging aid material packaging aid material number / lid, box divider/separator number
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00:92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019' GIN+AW+943692020' CPS+3++2' PAC+1++98-4500-1208-0-00::92' CPS+4++2'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet Packaging sequence (++2= packaging aid materialexample: lid or box divider/separator) Outer/pallet required if using packaging aid material packaging aid material number / lid, box divider/separator number consignment pack-sequence (2= lid or box divider/separator)
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00:92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019' GIN+AW+943692020' CPS+3++2' PAC+1++98-4500-1208-0-00::92' CPS+4++2' PAC+1++98-4500-1218-0-00::92'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet Packaging sequence (++2= packaging aid materialexample: lid or box divider/separator) Outer/pallet required if using packaging aid material packaging aid material number / lid, box divider/separator number
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00:92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019' GIN+AW+943692020' CPS+3++2' PAC+1++98-4500-1208-0-00::92' CPS+4++2' PAC+1++98-4500-1218-0-00::92' UNT+73+1'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet Packaging sequence (++2= packaging aid materialexample: lid or box divider/separator) Outer/pallet required if using packaging aid material packaging aid material number / lid, box divider/separator number consignment pack-sequence (2= lid or box divider/separator)
ALI+IT' RFF+ON:55000XXXXX' CPS+2++3' PAC+1++98-0690-0000-0-00:92' PCI+17+12811063++M::92' GIN+ML+12811063' GIN+AW+943692001' GIN+AW+943692002' GIN+AW+943692019' GIN+AW+943692020' CPS+3++2' PAC+1++98-4500-1208-0-00::92' CPS+4++2' PAC+1++98-4500-1218-0-00::92'	Country of origin Order reference / PO Number Packaging sequence (++3=outer) This is an outerpackage (examples = Pallet, Metal crate, etc) Outer-packaging-number / Pallet number Package identification type: S (Single/box) or M (Master/pallet) Pay attention to handling unit category: S (Single/box) or M (Master/pallet), etc Label number of pallet Reference to boxes on that pallet Reference to boxes on that palletinserted to shorten example length GIN+AW required for serial number values 03 -> 18 Reference to boxes on that pallet Packaging sequence (++2= packaging aid materialexample: lid or box divider/separator) Outer/pallet required if using packaging aid material packaging aid material number / lid, box divider/separator number consignment pack-sequence (2= lid or box divider/separator)

Note: The Supplier has to ensure the usage of single line items when posting the ASN, as multiple line items cannot be processed in most of the Continental plants. Single line item means that one ASN/delivery note number is created for each single part number and not for multiple part numbers.