

1. Connect a USB webcam to your computer, install any required drivers, and verify that the webcam works by opening the default camera app and capturing a photo.

Step 1: Connect the USB Webcam

1. Insert the webcam's USB cable into an available USB port on your computer.
2. Wait for Windows to detect the device.

Step 2: Install Drivers

1. If Windows automatically installs the drivers, wait until the message "**Your device is ready to use**" appears.
2. If drivers are not installed automatically, install them from the webcam manufacturer's website or the included CD.

Step 3: Verify Detection

1. Press **Windows + X** and select **Device Manager**.
2. Expand **Cameras** or **Imaging Devices**.
3. Confirm that the webcam appears in the list without any warning symbols.

Step 4: Open the Camera App

1. Click **Start** and search for **Camera**.
2. Open the **Camera** application.
3. Check that live video from the webcam is displayed.

Step 5: Capture a Photo

1. Click the **Take Photo** button (camera icon).
2. Save the captured image.

Step 6: Verify the Photo

1. Open the saved image.
2. Confirm that the photo was captured correctly.

2. Set up a local printer (USB or network), install the correct driver, and print a test page to confirm successful installation.

Step 1: Connect the Printer

For a USB Printer:

1. Connect the printer to the computer using a USB cable.
2. Turn on the printer.

For a Network Printer:

1. Connect the printer to the same Wi-Fi network as the computer.
2. Ensure the printer is powered on.

Step 2: Install the Printer Driver

1. Open **Settings → Devices → Printers & Scanners**.
2. Click **Add a Printer or Scanner**.
3. Select your printer when it appears.
4. Follow the on-screen instructions to install the correct driver.
5. If Windows cannot find the driver, download it from the printer manufacturer's website.

Step 3: Verify Installation

1. Open **Control Panel → Devices and Printers**.
2. Check that the printer appears in the list.
3. Ensure there are no warning icons on the printer.

Step 4: Print a Test Page

1. Right-click the installed printer.
2. Select **Printer Properties**.
3. Click **Print Test Page**.
4. Wait for the printer to print the page.

Step 5: Confirm Successful Installation

Check that:

- The printer responds.
- The test page prints correctly, No error messages appear.

3. Simulate a connectivity issue by unplugging the printer's USB cable, then use Windows Device Manager to identify and resolve the 'printer not detected' problem.

Hint: Check for error icons and use the 'Scan for hardware changes' option after reconnecting.

Step 1: Disconnect the Printer

1. Turn on the computer and printer.
2. Unplug the printer's USB cable from the computer.
3. Try to print a document.
4. Windows should display a message such as "**Printer Not Detected**" or "**Printer Offline**".

Step 2: Open Device Manager

1. Press **Windows + X**.
2. Select **Device Manager**.
3. Expand **Printers, Print Queues, or Universal Serial Bus Controllers**.

Step 3: Identify the Problem

1. Look for the printer in the device list.
2. Check for:
 - A **yellow warning icon** ().
 - An **Unknown Device** entry.
 - The printer missing from the list.

Observation: The printer may disappear from the list because the USB cable is disconnected.

Step 4: Reconnect the Printer

1. Plug the USB cable back into the computer.
2. Wait a few seconds for Windows to detect the printer.

Step 5: Scan for Hardware Changes

1. In Device Manager, click **Action** on the menu bar.
 2. Select **Scan for Hardware Changes**.
 3. Windows will search for newly connected devices.
 4. Verify that the printer appears in the device list.
-

Step 6: Check Driver Status

1. Right-click the printer.
 2. Select **Properties**.
 3. Check the **Device Status** section.
 4. Confirm that the message reads:
"This device is working properly."
-

Step 7: Test the Printer

1. Open **Control Panel → Devices and Printers**.
2. Right-click the printer.
3. Select **Printer Properties**.
4. Click **Print Test Page**.
5. Verify that the page prints successfully.

4.A user reports that their webcam video is not displaying in Zoom, but it works in the default camera app. Troubleshoot and resolve the issue so the webcam works in both applications.

Hint: Check if another app is using the webcam or if Zoom permissions are enabled.

Step 1: Verify Webcam Functionality

1. Open the **Camera** app in Windows.
2. Confirm that live video is displayed.
3. This proves the webcam and driver are working correctly.

Result: Webcam works in Camera app 

Step 2: Close Other Applications Using the Webcam

1. Close the Camera app.
2. Close applications such as:
 - Microsoft Teams
 - Skype
 - Google Meet
 - OBS Studio
3. Restart Zoom.

Reason: Only one application may be able to use the webcam at a time.

Step 3: Check Zoom Camera Settings

1. Open **Zoom**.
2. Click **Settings → Video**.
3. Under **Camera**, select the correct webcam from the drop-down menu.
4. Verify that the video preview appears.

Result: Correct webcam selected 

Step 4: Check Windows Camera Permissions

1. Open **Settings** → **Privacy** → **Camera**.
2. Ensure:
 - **Camera access for this device** is ON.
 - **Allow apps to access your camera** is ON.
 - **Allow desktop apps to access your camera** is ON.
3. Verify that Zoom is allowed to use the camera.

Result: Camera permissions enabled 

Step 5: Restart the Webcam

1. Unplug the webcam (if external).
 2. Wait 10 seconds.
 3. Reconnect it.
 4. Reopen Zoom and check the video.
-

Step 6: Check Device Manager

1. Press **Windows + X** and open **Device Manager**.
2. Expand **Cameras**.
3. Verify the webcam appears without warning symbols.
4. If necessary, right-click the webcam and select **Update Driver**.

Result: Webcam driver working properly 

Step 7: Restart Zoom and the Computer

1. Exit Zoom completely.
 2. Restart the computer.
 3. Open Zoom again and test the camera.
-

Step 8: Test in a Zoom Meeting

1. Start or join a Zoom meeting.
2. Click **Start Video**.
3. Confirm that your webcam video appears.