

Feeder ID	From	To	Load Type	Load Current (A)	Largest Motor Current (A)	Other Motor Current (A)	Minimum Feeder Ampacity (A)	Selected Feeder Rating (A)		Equipment	Calculated Load	Selected Rating
FDR-01	SWBD-1	MCC-1	Motors	225.3	110.2	115.1	252.85	300		SWBD-1	590.7	800
FDR-02	SWBD-1	MCC-2	Motors	245.6		117.6	277.6	300		MCC-1	225.3	300
FDR-03	SWBD-1	AUX-1	Auxiliary	120.3			150.375	175		MCC-2	245.6	300
FDR-MAIN	T1	SWBD-1	Main Distribution	590.7			653.3	800		AUX-1	120.3	175
Branch ID	MCC	Motor	Control	Motor Current (A)	Minimum Conductor Ampacity (A)	Selected Branch Rating (A)						
FDR-101	MCC-1	M-101	VFD	110.2	137.75	150						
FDR-102	MCC-1	M-102	DOL	68.4	85.5	100						
FDR-103	MCC-1	M-103	VFD	46.7	58.375	60						
FDR-201	MCC-2	M-201	VFD	82.6	103.25	125						
FDR-202	MCC-2	M-202	DOL	128	160	175						
FDR-203	MCC-2	M-203	DOL	35	43.75	50						