USER ACCEPTANCE TEST (UAT)

UAT Form MTI Radio Management

User acceptance test scenarios for every menu of the app: filled in while testing, then approved by the testers, the IT team and the approver.

App version: 1.21.4 · **Date:** 21 October 2026 · 118 scenarios

For: the user representatives who test, the IT/ICT team, and the manager or process owner who approves.

The same scenarios are in the Excel file UAT-Scenarios-MTI-Radio-Management-EN.xlsx, to fill in on a computer.

Contents

1. Test information 3
2. How to fill in 4
3. Sign-in and sign-out (8) 5
4. Layout, language and Version history (6) 6
5. Notifications (3) 7
6. Dashboard (5) 7
7. Register Radio (16) 8
8. Radio details, handover and print form (7) 11
9. Needs Attention (6) 12
10. Service & Repair (7) 13
11. Stock Opname (6) 14
12. Radio History (2) 15
13. Radio Master Data (4) 16
14. E-Sign Master (3) 16
15. Import Excel (3) 17
16. COF Scan (4) 18
17. ICT Masterlist and Edit Approvals (9) 18
18. Snipe-IT (7) 20
19. Registered Users (6) 21
20. Role & Permission (3) 22
21. Audit Log (4) 23
22. API Tokens and the API (5) 23
23. Access per role (4) 24
24. Findings 26
25. Results summary 27
26. Sign-off 28

1. Test information

Application	MTI Radio Management
Version tested	1.21.4 (check it against the version number in the footer of the app)
Environment	☐ Test copy (UAT) ☐ Production
Address of the app (URL)	
Browser and its version	
Phone for Stock Opname	
Start / end date	
Place of testing	

Testers

No	Name	Position / Department	Roles tested	Initials
1				
2				
3				
4				
5				

Test accounts per role

Role	Account (e-mail / username)	Used by
SA · Super Admin		
AR · Admin Radio		
VR · Viewer Radio		
DC · Document Controller		

2. How to fill in

This form checks that MTI Radio Management works the way its users expect. Each scenario names the role of the account to use, its steps, and the expected result.

1. Make sure the version number in the footer of the app is the version on the cover of this form.
2. Run the scenarios in the order of the sections. Some scenarios use the result of an earlier one; its ID is named in the steps.
3. Sign in with an account of the role in the Role column (All: any account that may open the menu).
4. Compare what happens with the Expected result column, then tick one box in the Result column.
5. For each Fail, write what happened in the Notes column and in the Findings, with the scenario ID.
6. Once every section is done, fill in the Results summary, then sign the Sign-off page.

Meaning of the Result column

☐ **Pass**	What happens is the expected result.
☐ **Fail**	What happens is different. Write what happened in Notes and record it in the Findings.
☐ **N/A**	Does not apply or cannot be tested in this environment. Write the reason in Notes.

Role codes

SA	Super Admin
AR	Admin Radio
VR	Viewer Radio
DC	Document Controller
All	any account that may open the menu

Severity of findings

Critical	The app cannot be used, data is damaged or lost, or a security problem.
High	A main function fails and there is no other way.
Medium	A function fails, but there is another way to get the work done.
Low	Looks, texts or comfort; the work can still be done.

> Data: use test radios, accounts and rows. An import that deletes the old data only on a test copy. The scenarios that write to the ICT Masterlist change the workbook in SharePoint: use rows agreed with the owner of the data. Put the data back after testing, and do not write passwords or tokens on this form.

3. Sign-in and sign-out

> Prepare a test account that may be deactivated. The session scenarios need 30 minutes without activity.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-LOG-01	All	**Sign in with Microsoft** 1. Open the address of the app. 2. Click **Microsoft** under **Sign in with SSO**. 3. Choose your work Microsoft account and finish the sign-in.	The app opens on the home page of your role; your name and role show at the top right. The choice of Microsoft account always appears.	☐ Pass ☐ Fail ☐ N/A	
UAT-LOG-02	All	**Sign in with a Merdeka Account (LDAP)** 1. In the **Sign in with Merdeka Account** form, fill in **Email or username** with the Windows username (without @...). 2. Fill in **Password** with the Windows password, then click **Login**.	You are signed in on the home page of your role. The account must use the LDAP method in Registered Users.	☐ Pass ☐ Fail ☐ N/A	
UAT-LOG-03	All	**A wrong password is refused** 1. Fill in the right **Email or username** and a wrong **Password**. 2. Click **Login**.	The message "Wrong username or password!"; no sign-in. The Audit Log records "Sign-in failed" with its reason.	☐ Pass ☐ Fail ☐ N/A	
UAT-LOG-04	All	**An unregistered Microsoft account is refused** 1. Click **Microsoft** and sign in with a Microsoft account that is not registered in the app.	A message that the user is not registered in Microsoft SSO; no sign-in.	☐ Pass ☐ Fail ☐ N/A	
UAT-LOG-05	SA	**An inactive account cannot sign in** 1. The Super Admin deactivates the test account in **Registered Users**. 2. Try to sign in with that test account, then activate the account again and retry.	The message "Account inactive"; no sign-in. Once activated again, the account can sign in.	☐ Pass ☐ Fail ☐ N/A	
UAT-LOG-06	All	**Session warning after inactivity** 1. Sign in, then leave the app without activity for 28 minutes. 2. When the warning appears, click **Stay signed in**.	The dialog "Your session is about to end" with a 2-minute countdown; **Stay signed in** extends the session and the work can go on.	☐ Pass ☐ Fail ☐ N/A	
UAT-LOG-07	All	**The session ends** 1. Let the countdown of the session warning run out without pressing any button.	The page goes to the login with the message "Session expired" and its reason (inactive for 30 minutes). The Audit Log records the expired session.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-LOG-08	All	**Sign out** 1. Click your name at the top right, then **Sign out**. 2. Open a page of the app again.	Back on the login page, and the pages of the app ask for a sign-in again. The Microsoft account in the browser stays signed in.	☐ Pass ☐ Fail ☐ N/A	

4. Layout, language and Version history

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-GEN-01	All	**Switch the language ID | EN** 1. Click **EN** in the top bar and open a few menus. 2. Sign out, then sign in again. 3. Click **ID** to go back.	Menus, titles, buttons, tables, dialogs and messages show in English; the choice stays after signing in again (saved on the account). **ID** brings Indonesian back.	☐ Pass ☐ Fail ☐ N/A	
UAT-GEN-02	All	**Language and guide on the login page** 1. On the login page, click **EN** then **ID** at the bottom right. 2. Click **Click here** next to **Access Login Guide:**.	The texts of the login page switch language; a summary of how to sign in shows.	☐ Pass ☐ Fail ☐ N/A	
UAT-GEN-03	AR	**Data stays as stored in English** 1. Choose **EN**, then open the details of a radio and **Radio History**.	Labels and buttons in English; the history entries, notes and descriptions stay as stored (Indonesian). Locations and conditions show with their English names (for example With user, Good).	☐ Pass ☐ Fail ☐ N/A	
UAT-GEN-04	All	**Sidebar and breadcrumb** 1. Click the button at the left end of the top bar to shrink the sidebar, then reload the page. 2. Open the details of a radio, then click **Register Radio** in the breadcrumb.	The sidebar becomes a row of icons and stays so after the reload; the menu name shows when the pointer is over an icon. The breadcrumb leads back to Register Radio.	☐ Pass ☐ Fail ☐ N/A	
UAT-GEN-05	All	**Version history** 1. Click the version number in the footer (for example v1.21.4). 2. Switch the language, then open the dialog again.	The **Version history** dialog shows a timeline, newest first; the running version is marked **This version**. The legend and the labels of the kinds (Added, Changed, Fixed, ...) are always in English; the notes follow the chosen language.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-GEN-06	VR	**A page without access** 1. Sign in as a Viewer Radio. 2. Type the address of a page that is not in its menu in the address bar, for example `/audit-log`.	The page "You do not have access to this page" with the button **To the home page**; the content of the page does not show.	☐ Pass ☐ Fail ☐ N/A	

5. Notifications

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-NOT-01	DC	**Notification bell** 1. Make sure there is a new notification (for example the cell change request of UAT-ICT-03). 2. Click the bell, then click the notification.	The red number on the bell is the unread count; clicking the notification marks it as read and opens its page (Edit Approvals).	☐ Pass ☐ Fail ☐ N/A	
UAT-NOT-02	All	**Mark all as read and the Notifications page** 1. Click the bell, then **Mark all as read**. 2. Click **See all notifications**.	The number on the bell goes away. The **Notifications** page opens with the tabs All, Unread, Radio, Documents and System with their counts, grouped Today, Yesterday and Earlier.	☐ Pass ☐ Fail ☐ N/A	
UAT-NOT-03	All	**Mark one as read** 1. On the **Notifications** page, open the **Unread** tab. 2. Click **Mark as read** on one row.	That row is marked as read without opening the notification; the count on the tab and on the bell goes down by one.	☐ Pass ☐ Fail ☐ N/A	

6. Dashboard

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-DSB-01	AR	**Dashboard number cards** 1. Open **Dashboard**. 2. Compare the **Active radios** card and the cards per location with the counts in Register Radio. 3. Click the **IT stock** card.	The heading "Welcome to Radio Management System". The numbers match Register Radio; the card opens Register Radio already filtered on the location IT stock.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-DSB-02	AR	**Condition of active radios** 1. In the **Condition of active radios** panel, click the slice or row **Needs service**.	Register Radio opens filtered on the condition Needs service; the count matches the panel.	☐ Pass ☐ Fail ☐ N/A	
UAT-DSB-03	AR	**Next free Radio IDs** 1. Look at the **Next free Radio IDs** panel. 2. Work out the MDC Code (hexadecimal) of a few IDs shown.	No ID whose MDC Code contains the letter F, and no ID already used by an active radio.	☐ Pass ☐ Fail ☐ N/A	
UAT-DSB-04	AR	**Needs action** 1. In the **Needs action** panel, click **Show** on one issue. 2. Go back to the Dashboard, then click **Open inbox**.	**Show** opens Register Radio filtered on that issue with the same count; **Open inbox** opens **Needs Attention**.	☐ Pass ☐ Fail ☐ N/A	
UAT-DSB-05	VR	**Charts and recent activity** 1. Look at the panels **Active radios per user company**, **Active radios per type** and **Recent activity**. 2. Click a radio in Recent activity, then **All history**.	The total in the middle of the ring equals the number of active radios; each bar per type carries its number. The link opens the radio's details, and **All history** opens **Radio History**.	☐ Pass ☐ Fail ☐ N/A	

7. Register Radio

> Use test radios for the scenarios that change, archive or delete data, and put the data back after testing when testing on production.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-REG-01	VR	**Search, sort and page** 1. Open **Register Radio** and type part of an SN, Radio ID or user name in the search box. 2. Click the **Radio ID** column heading, then change **Rows per page** and go to another page.	The list changes while typing; the order and the rows per page follow the choice; the summary line "Showing … of …" is right.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-02	VR	**Active and archived radios** 1. Choose **Archived**, then **All**, then **Active**.	**Archived** shows only archived radios, with the columns last user, archive date and reason; **All** shows both.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-REG-03	VR	**Filters and Refresh** 1. Click **Filter**, choose for example Radio type and Condition, then **Apply filters**. 2. Type something in the search box, then click **Refresh**. 3. Click × on one chip, then **Clear filters**.	Active filters show as chips after **Applied:**; **Refresh** fetches the latest list without clearing the search and filters; × removes one filter, **Clear filters** removes them all.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-04	VR	**Export Excel** 1. Set one filter, then click **Export Excel**. 2. Open the downloaded file.	An .xlsx file with every radio matching the filter (not only the page shown).	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-05	AR	**Add a radio** 1. Click **Add radio**. 2. Fill in a new SN, Radio type, Location and Condition (required), and a free Radio ID. 3. Click **Save radio**.	The new radio is in the list; MDC Code, category and power are filled in automatically; a result message shows at the bottom of the screen; the radio's history records "Created".	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-06	AR	**A Radio ID whose MDC contains F is refused** 1. In the radio form, type the Radio ID **751** (MDC 2EF). 2. Try to save with that ID.	The form says right away that the ID cannot be used because its MDC Code contains F and offers a replacement that can be used (for example **Use 768**); saving with that ID is refused.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-07	AR	**A Radio ID already in use** 1. In the radio form, type a Radio ID used by another active radio. 2. Click **Choose ID**.	The form says the ID is in use, with its holder; **Choose ID** shows the next free ID, and the **IDs around it** panel marks free, used or has an F.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-08	AR	**A duplicate SN is refused** 1. Add a radio with an SN that is already in the register, then click **Save radio**.	Saving is refused with a message that the SN is already in use; no new radio.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-09	AR	**A change of a radio is recorded in its history** 1. Click the pencil icon (Edit) on a radio. 2. Change the User / unit name, Location or Condition, then **Save changes**. 3. Open the radio's details.	The change is saved; the radio's history shows the old value struck through and the new value beside it; the Audit Log records the change with the values before and after.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-10	AR	**Two people save the same radio** 1. Two testers open the Edit form of the same radio. 2. The first tester saves a change. 3. The second tester saves another change.	The second save is refused with a message that this radio was changed just now (with the name of who changed it); the first change is not overwritten.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-REG-11	AR	**Archive a radio** 1. Click **Archive** on a test radio. 2. Choose a reason (for example **Moved to another site**), fill in the date and the note, then **Archive radio**.	The radio moves to the **Archived** view with its reason and date; its Radio ID is released and can be used by another radio; the history records the archiving.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-12	AR	**Restore a radio** 1. In the **Archived** view, click **Restore** on the radio of UAT-REG-11.	The radio is active again; its old Radio ID comes back unless another radio has taken it, in which case the ID stays empty.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-13	AR	**Select many** 1. Tick a few radios, go to another page, then tick some more. 2. Click **Select all N radios of the filter**, then **Clear the selection**.	The selection is kept when changing pages; the bar above the table gives the number selected; **Clear the selection** removes them all.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-14	AR	**Verify today for many radios** 1. In the **All** view, tick a few active radios and one archived radio. 2. Click **Verify today**, choose the date, then confirm.	The active radios get a "Verification" history entry and their verification date moves forward; the archived radio is skipped, with the reason given.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-15	AR	**Export selected and archive many radios** 1. Tick two test radios, click **Export selected** and open the file. 2. With the same radios ticked, click **Archive**, fill in the reason, date and note, then confirm.	The Excel file holds only the ticked radios. Both radios are archived with one reason; archiving many works for at most 100 radios ticked one by one.	☐ Pass ☐ Fail ☐ N/A	
UAT-REG-16	AR	**Delete many radios entered by mistake** 1. Tick test radios entered by mistake, then click **Delete**. 2. Type the number of ticked radios as the confirmation.	The deletion only runs once the number is typed right; the radios are deleted and recorded in the Audit Log. Only for wrong entries.	☐ Pass ☐ Fail ☐ N/A	

8. Radio details, handover and print form

> The handover needs the receiver to sign on the screen (pen, finger or mouse).

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-DET-01	VR	**Radio details page** 1. Click a row in **Register Radio**.	The details show Radio ID, MDC Code, SN, location and condition, the **Check results** card (if any), three data cards, the history (newest first) and the **Original Excel data** for imported radios. A Viewer does not see the Edit, Handover, Archive and delete buttons.	☐ Pass ☐ Fail ☐ N/A	
UAT-DET-02	AR	**Add a history entry by hand** 1. In the radio details, click **Add history**. 2. Choose the kind Programming, fill in today's date and the description, then save.	The new entry shows at the top of the radio's history and in **Radio History**; the radio's last programming date is updated too.	☐ Pass ☐ Fail ☐ N/A	
UAT-DET-03	AR	**Delete a radio from its details** 1. In the details of a test radio, click **Delete**. 2. Type its Radio ID as the confirmation.	The radio is deleted only after the Radio ID is typed right, and it is recorded in the Audit Log.	☐ Pass ☐ Fail ☐ N/A	
UAT-DET-04	AR	**Handover with a signature** 1. In the radio details, click **Handover**. 2. Find the **Receiver** in the employee directory (or type the name), fill in **BA No.**, tick the accessories, choose the condition and the location after the handover. 3. Ask the receiver to sign in the **Receiver's signature** box and tick the statement, then click **Confirm the handover**.	The confirm button only works once there is a signature, and the BA No. is required. The radio is recorded as the receiver's, a "Handover" history entry is written with the BA No., and the checkout form opens with the receiver's signature under RESPONSIBLE USER.	☐ Pass ☐ Fail ☐ N/A	
UAT-DET-05	AR	**The handover signature is not stored** 1. After UAT-DET-04, close the form, then open **Print the form** of the same radio. 2. Look at that handover record in the Audit Log.	The RESPONSIBLE USER box is empty again; the receiver's signature is neither in the app nor in the Audit Log, only on the printout.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-DET-06	VR	**Print the checkout form** 1. Click **Print the form** in the radio details (or the printer icon in Register Radio). 2. Check the fields filled in, sign the RESPONSIBLE USER box on the screen, then **Use signature**. 3. Click **Print**, then close the pop-up with **Close**.	The IT Equipment Checkout Form (MTI-HRM-ICT-FRM-001 Rev.000) is filled in from the register: ID No., Brand & Type, Serial Number, name and department; the HT or RIG choice that is not its kind is struck out; it fits one A4 page. Clicking outside the pop-up or Esc does not close it.	☐ Pass ☐ Fail ☐ N/A	
UAT-DET-07	SA	**PROCESSED BY signature from E-Sign Master** 1. Sign in with an account that has a signature in **E-Sign Master**, then open **Print the form** of a radio. 2. Repeat with an account without a signature.	First account: its signature and name show under PROCESSED BY, and the use is recorded in the E-Sign use history. Second account: the PROCESSED BY box is empty, to be signed on paper.	☐ Pass ☐ Fail ☐ N/A	

9. Needs Attention

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ATT-01	AR	**The Needs Attention page** 1. Open **Needs Attention**. 2. Choose a kind of check on the left, then an item in the middle. 3. Click **Run the checks now**.	Left: the kinds of check with their open items; middle: the items; right: the details, the fixes and the assignment. The red number in the sidebar equals the open items; the checks run again right away.	☐ Pass ☐ Fail ☐ N/A	
UAT-ATT-02	AR	**Fix a Radio ID that contains F** 1. Choose an item under **Radio ID contains F**. 2. Choose **Use the next ID that can be used**, then **Apply**.	The radio gets a new ID whose MDC has no F; its history and the Audit Log record it; the item leaves the list and the number in the sidebar goes down.	☐ Pass ☐ Fail ☐ N/A	
UAT-ATT-03	AR	**Record verification today** 1. Choose an item under **Verified over 12 months ago** (or **Verification date empty**). 2. Choose **Record verification today**, then **Apply**.	The radio's verification date becomes today, a "Verification" history entry is recorded, and the item is done.	☐ Pass ☐ Fail ☐ N/A	
UAT-ATT-04	AR	**Duplicate SN** 1. Choose an item under **Duplicate SN**. 2. Compare the radios, then choose **Archive radio ... as a duplicate** and **Apply**.	The radios show side by side with the differing columns marked; the duplicate is archived (its history stays) and the item is done.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ATT-05	AR	**Dismiss with a reason** 1. Choose an item, then click **Dismiss** without a reason. 2. Fill in the reason, then **Dismiss** again. 3. Change that radio's data in Register Radio, then **Run the checks now**.	Without a reason it is refused; with a reason the item closes. After the radio's data changes, the item comes back if the problem is still there.	☐ Pass ☐ Fail ☐ N/A	
UAT-ATT-06	AR	**Assign an item** 1. Choose an item, then pick a name under **Assigned to**. 2. Sign in as that person, open **Needs Attention** and choose **Assigned to me**.	The item shows under **Assigned to me** for that person and no longer under **Unassigned**; the Audit Log records the assignment.	☐ Pass ☐ Fail ☐ N/A	

10. Service & Repair

> Use a test radio: a ticket changes the location and condition of its radio.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-SRV-01	AR	**Create a service ticket** 1. Open **Service & Repair**, click **New ticket**. 2. Choose the radio, fill in **Issue** and **Reported by**, then save.	A ticket numbered SRV-xxxx shows in the **Reported** step, and the message "Ticket SRV-xxxx created." appears.	☐ Pass ☐ Fail ☐ N/A	
UAT-SRV-02	AR	**One open ticket per radio** 1. Try to create a second ticket for the radio of UAT-SRV-01. 2. Try to create a ticket for an archived radio.	Neither works: the radio cannot be chosen or saving is refused with the reason.	☐ Pass ☐ Fail ☐ N/A	
UAT-SRV-03	AR	**Send for service** 1. Open the ticket of UAT-SRV-01, click **Send for service**. 2. Fill in **Service center** (required), the send date, BA No. and the expected return, then save.	The ticket moves to **Sent for service**; the radio's location becomes In service, and a "Service" history entry is recorded with the ticket number and the BA No.	☐ Pass ☐ Fail ☐ N/A	
UAT-SRV-04	AR	**From in repair until returned** 1. Click **Mark as in repair**, then **Mark as ready for pickup** with its cost. 2. Click **Mark as returned**: fill in the return date, **Radio location afterwards** and **Condition when returned** (required).	The ticket goes through In repair, Ready for pickup, then Returned; the radio's location and condition are updated and a "Service" history entry is recorded; its cost counts in this quarter's cost.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-SRV-05	VR	**Board, List and ticket details** 1. Switch between the **Board** and **List** views, search by Radio ID or SN, then filter by service center. 2. Click a ticket.	The four numbers at the top (open tickets, average service time, late, cost this quarter) show; the list follows the search and filter; the ticket details show the steps, facts, activity and the **Open the radio** link. A Viewer does not see the step buttons and **New ticket**.	☐ Pass ☐ Fail ☐ N/A	
UAT-SRV-06	AR	**Notes and Export** 1. In the ticket details, write a note with **Add a note**. 2. Click **Export** and open the file.	The note shows in the ticket's activity. The Excel file holds every ticket, including those already returned.	☐ Pass ☐ Fail ☐ N/A	
UAT-SRV-07	AR	**Two people move the same ticket** 1. Two testers open the same ticket. 2. The first moves it to the next step, then the second moves the same step.	The second move is refused: "Someone else has moved this ticket on. Reload the page."	☐ Pass ☐ Fail ☐ N/A	

11. Stock Opname

> Needs a phone (Chrome on Android to scan with the camera) and test radios with an SN barcode.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-OPN-01	AR	**Start a stock opname session** 1. Open **Stock Opname** on a phone. 2. Choose the Department (and Company if needed), then **Start a session**.	The page without sidebar gives the number of radios expected and the last stock take, then a new session starts. If a session of that department is still open, the button is **Continue the session**.	☐ Pass ☐ Fail ☐ N/A	
UAT-OPN-02	AR	**Scan the SN barcode** 1. In Chrome on Android, scan the SN barcode of a radio with the camera. 2. In another browser, type the Radio ID or SN, then click **Find**.	The radio found shows with its holder and condition in the register.	☐ Pass ☐ Fail ☐ N/A	
UAT-OPN-03	AR	**A radio not in the register** 1. Type an SN that is not in the register, then **Find**.	The message "No radio in the register has that Radio ID or SN."	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-OPN-04	AR	**Check a radio** 1. For a radio found, answer **Who has it now?** (for example **Someone else** with the name), choose the condition and fill in a note. 2. Click **Verify radio**.	The scan is saved at once, and the radio counts in the session.	☐ Pass ☐ Fail ☐ N/A	
UAT-OPN-05	AR	**Report a problem from the opname** 1. For a radio with a problem, write the issue in the note, then click **Report a problem**.	A new ticket is created in **Service & Repair** for that radio (needs the Create permission on Service & Repair).	☐ Pass ☐ Fail ☐ N/A	
UAT-OPN-06	AR	**Summary and send to the register** 1. Click **See the summary**. 2. Click **Send to the register**.	The summary gives verified, not found, other holder and other department. After sending, every radio found gets a "Verification" history entry, changed conditions are updated, and the session is closed.	☐ Pass ☐ Fail ☐ N/A	

12. Radio History

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-HIS-01	VR	**Filter Radio History** 1. Open **Radio History**. 2. Type in the search box, choose several **Kind** values, then fill in **From date** and **To date** with the calendar.	The list follows the filters at once; each kind shows its count; events outside the date range do not show.	☐ Pass ☐ Fail ☐ N/A	
UAT-HIS-02	VR	**Content of Radio History** 1. Search for the radio used in the earlier scenarios (handover, service, verification, archiving).	Each event of those scenarios shows with its date, kind, user, document no. and description, with a link to the radio.	☐ Pass ☐ Fail ☐ N/A	

13. Radio Master Data

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-MDR-01	AR	**Add a Radio Type** 1. Open **Radio Master Data** → **Radio Types**, click **Add radio type**. 2. Fill in Type name, Category and Power, tick Active, then save. 3. Open the **Add radio** form.	The new type is in the list and can be chosen in the radio form; a radio of that type gets the category and power of its type.	☐ Pass ☐ Fail ☐ N/A	
UAT-MDR-02	AR	**Asset owner and Owner** 1. In the radio form, choose as Asset owner a company with the code MTI, then save. 2. Change it to another company, then save.	The radio's Owner becomes MTI for the company coded MTI, and Non MTI for another company.	☐ Pass ☐ Fail ☐ N/A	
UAT-MDR-03	AR	**Deactivate and delete master data** 1. Deactivate a Department used by radios. 2. Try to delete that Department, then delete a new Department not used yet.	An inactive Department can no longer be chosen for other radios, and radios already using it do not change; deleting one in use is refused, an unused one is deleted.	☐ Pass ☐ Fail ☐ N/A	
UAT-MDR-04	AR	**Channel Template and reprogramming** 1. Change **Effective from** of a Channel Template used by a test radio to today. 2. Open **Needs Attention**, then **Run the checks now**.	Radios with that template last programmed before that date are marked **Needs reprogramming**.	☐ Pass ☐ Fail ☐ N/A	

14. E-Sign Master

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ESG-01	SA	**Register a signature** 1. Open **Radio Master Data** → **E-Sign Master**, click **Register a signature**. 2. Choose the ICT officer's account, sign in the box (or upload a picture of the signature), then **Save**.	The signature shows in the Grid view with its preview; one account can have only one signature.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ESG-02	SA	**Manage signatures** 1. Switch between **Grid** and **List**, then reload the page. 2. Open the use history of a signature, then deactivate that signature and activate it again.	The view choice is remembered; the use history lists every printed form that used it; an inactive signature does not show under PROCESSED BY.	☐ Pass ☐ Fail ☐ N/A	
UAT-ESG-03	AR	**E-Sign Master is for the Super Admin only** 1. Sign in as an Admin Radio and open **Radio Master Data**.	The **E-Sign Master** menu does not show; opening its address directly shows the no-access page.	☐ Pass ☐ Fail ☐ N/A	

15. Import Excel

> Only on a test copy, never on production: an import that deletes the old data deletes the whole register and its history.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-IMP-01	AR	**Import into an empty register (test copy)** 1. On the test copy with an empty register, open **Import Excel**, choose the old register file (.xlsx), then **Start the import**. 2. Click the **Open in Register Radio** link for the radios marked Needs checking.	The result shows in number tiles (read, imported, skipped, needs checking); the radios appear in Register Radio; the Needs checking radios open filtered.	☐ Pass ☐ Fail ☐ N/A	
UAT-IMP-02	AR	**Import into a register holding radios** 1. Choose a file and click **Start the import** without ticking the red box. 2. Tick the red box **Delete every radio and all history before the import**, then **Start the import**.	Without the tick, the import is refused because the register already holds radios. With it, the app asks for a confirmation once more; only go on in a test copy.	☐ Pass ☐ Fail ☐ N/A	
UAT-IMP-03	AR	**An import that deletes the old data is refused** 1. Make sure a service ticket (UAT-SRV-01) or a stock opname session is open. 2. Run the import with the red box ticked.	The import is refused with a message giving how many service tickets or stock opname sessions are still open; no data is deleted.	☐ Pass ☐ Fail ☐ N/A	

16. COF Scan

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-COF-01	DC	**COF Scan numbers and filters** 1. Open **COF Scan** with an account that may also open the ICT Masterlist. 2. Click **Review** on the warning about files not linked, then the filters **All**, **Linked** and **Not linked**.	Three numbers **Last synced**, **Linked to a row** and **Not linked** for the whole folder; **Review** and the filters show the files by their status.	☐ Pass ☐ Fail ☐ N/A	
UAT-COF-02	DC	**Search and the Masterlist column** 1. Search by COF No. or name, then click a column heading to sort. 2. Click the link in the Masterlist column of a file.	Names like ICTCOF123 - Name.pdf are split into COF No. and Name; the Masterlist column gives the row ("Row N", "Different name · row N" or "No row") and opens that row in the ICT Masterlist.	☐ Pass ☐ Fail ☐ N/A	
UAT-COF-03	DC	**View a scan file** 1. Click the eye icon (View) on a file, then the next and previous buttons. 2. Click the file name.	The PDF or picture (up to 10 MB) shows in a pop-up and can move between files; the file name opens that file in SharePoint with the tester's Microsoft account.	☐ Pass ☐ Fail ☐ N/A	
UAT-COF-04	DC	**Reload and Reset** 1. Upload a test file to the COF folder in SharePoint, then click **Reload**; remove the test file again afterwards. 2. Click **Reset**.	The new file shows right away (without Reload, within 10 minutes at most); **Reset** clears the search, filter and order.	☐ Pass ☐ Fail ☐ N/A	

17. ICT Masterlist and Edit Approvals

> The scenarios that change content write to the workbook in SharePoint: use a test row agreed with the owner of the data, and put its values back after testing.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ICT-01	DC	**Read the ICT Masterlist** 1. Open **ICT Masterlist** and move between the sheet tabs. 2. Type two words in the search box.	Each sheet is a tab with its row count; dates show as dd-mm-yyyy and formulas as their result; the search looks in all sheets and each tab gives the number of matching rows.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ICT-02	DC	**Cross-check in the COF tab** 1. Open the COF tab, click the **Missing** card, then click it again.	The File scan column and five cards (Total rows, Found, Missing, Different name, Subfolder) show; clicking a card filters its rows, clicking again shows all.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-03	AR	**Ask for a cell change** 1. Sign in as an Admin Radio, open **ICT Masterlist**, click the pencil in the test cell. 2. Fill in the new value, then click **Ask for the change**. 3. Try to click a cell holding a formula.	The cell is marked waiting, and a cell can have only one waiting request; formula cells carry a padlock and cannot be asked for. The approvers get a notification.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-04	DC	**Approve a request** 1. Sign in as a Document Controller, open **Edit Approvals**, tab **Pending**. 2. Compare the old and new values, then click **Approve**.	The status becomes **Applied**; the new value is written in the SharePoint workbook (a new version of the file); the requester gets a notification of the result.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-05	DC	**Reject a request** 1. For another request, click **Reject** and fill in the reason.	Status **Rejected**; nothing is written to SharePoint; the requester gets a notification with the reason.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-06	AR	**The requester does not decide their own request** 1. Sign in as the Admin Radio who asked in UAT-ICT-03, then open **Edit Approvals**.	The request shows as Pending, without the **Approve** and **Reject** buttons: a request is always decided by someone else.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-07	DC	**Conflict when the cell has changed** 1. An Admin Radio asks for a change of a test cell. 2. Change the same cell directly in Excel and save it there. 3. A Document Controller approves the request.	The status becomes **Conflict**; the value in Excel is not overwritten; the requester is told to ask again from the latest value.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-08	DC	**Edit a row directly** 1. Sign in as a Document Controller, click the pencil on the number of the test row. 2. Change one or two fields, then **Save**.	The **Edit row** dialog holds every column; formula cells, cells with a waiting request and the File scan column are read-only. The change is written at once; **Edit Approvals** says "Written directly by ..."; the Audit Log records it.	☐ Pass ☐ Fail ☐ N/A	
UAT-ICT-09	DC	**Edit a row when the workbook changed or is locked** 1. Open the test row in **Edit row**, then change the same row in Excel and save it there. 2. Save in the app. 3. Repeat while the workbook is open in Excel desktop.	Nothing is written; the message says the row has changed in SharePoint since the page was loaded, or the workbook is locked because somebody has it open in Excel.	☐ Pass ☐ Fail ☐ N/A	

18. Snipe-IT

> Snipe-IT must be set up on the server (SNIPEIT_URL and SNIPEIT_TOKEN). By default only the Super Admin gets this menu.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-SNP-01	SA	**Snipe-IT overview** 1. Open **Snipe-IT** → **Overview**. 2. Click **Fetch again from Snipe-IT**, then **See all** on one panel.	The top line gives the Snipe-IT version and when the data was fetched; assets per status and per category and the count of each list show. Fetching again updates the time; **See all** opens its page.	☐ Pass ☐ Fail ☐ N/A	
UAT-SNP-02	SA	**Assets list** 1. Open **Assets**, then filter by category and status. 2. Search for an asset tag or SN, sort a column, then go to another page.	Each row starts with the asset's picture (or its category icon) with the asset tag and its name; the filters show their counts; the results match Snipe-IT.	☐ Pass ☐ Fail ☐ N/A	
UAT-SNP-03	SA	**Asset details** 1. Click the eye button (**See the details**) at the end of an asset's row. 2. Click **Open full size** on its picture, then **Open in Snipe-IT**.	The details show the asset data, holder and location, purchase and warranty, history (old value struck through, new beside it), custom fields, maintenance, licenses and audit times; the picture opens at full size; the same asset opens in Snipe-IT.	☐ Pass ☐ Fail ☐ N/A	
UAT-SNP-04	SA	**Secret custom fields are hidden** 1. Open the details of an asset with a secret custom field (for example a password or BitLocker key).	Its value reads **Hidden**, in the history too; license keys do not show.	☐ Pass ☐ Fail ☐ N/A	
UAT-SNP-05	SA	**Catalog, People & Organization, Licenses & Stock, History** 1. Open each page and move between its list tabs. 2. In **History** → **Activity log**, filter by action.	Each list shows with search, sort and paging; the Changes column of the Activity log is readable (for example "Status: Ready to Deploy → Deployed"); names and notes show as in Snipe-IT.	☐ Pass ☐ Fail ☐ N/A	
UAT-SNP-06	SA	**Snipe-IT is read only** 1. Check every Snipe-IT page.	No button adds, changes or deletes Snipe-IT data; changes are made in Snipe-IT only.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-SNP-07	AR	**Access to the Snipe-IT menu** 1. Sign in as an Admin Radio: the **IT ASSETS** section does not show. 2. The Super Admin grants that role Read on **Snipe-IT → Assets** in **Role & Permission**, then the Admin Radio signs in again; afterwards, revoke the permission again.	Without permission the menu does not show; with Read granted, **Assets** shows and opens (read only).	☐ Pass ☐ Fail ☐ N/A	

19. Registered Users

> Prepare test accounts to add, deactivate and delete; do not use the accounts of people at work.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-USR-01	SA	**Add a user with the Microsoft method** 1. Open **User Management → Registered Users**, click **Add user**. 2. Choose the **Sign-in method** Microsoft, type a name in **Find employee**, then pick the person. 3. Choose the Role and Status, click **Submit**, then answer **Is the data correct?**.	Name and Email are filled in from the HR database; the new user shows in the list; that person can sign in with the Microsoft button.	☐ Pass ☐ Fail ☐ N/A	
UAT-USR-02	SA	**Add a user with the LDAP method** 1. In **Add user**, choose the **Sign-in method** LDAP, then find the person with **Find employee**. 2. Submit; repeat with a **Directory username** that is not in Active Directory.	Name, Email and Directory username are filled in from Active Directory; a username that does not exist or is disabled is refused on submit.	☐ Pass ☐ Fail ☐ N/A	
UAT-USR-03	SA	**User list and filters** 1. Filter the list by name or e-mail, role and status.	The list shows No, Name, Email, Role, Status, Sign-in (Microsoft, LDAP, Both, Password, Pending) and Last sign-in matching the filters.	☐ Pass ☐ Fail ☐ N/A	
UAT-USR-04	SA	**Deactivate and activate an account** 1. Keep the test account signed in in another browser. 2. Click **Deactivate** on that account, then the test account clicks a menu. 3. Click **Activate**.	The test account's session ends on its next click and its sign-in is refused "Account inactive"; once activated, the account can sign in again.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-USR-05	SA	**Set a password** 1. On a test account that is not LDAP, click **Set password** and fill in a new password. 2. Sign in with that account using the new password.	The sign-in works with the new password; LDAP accounts have no **Set password** button.	☐ Pass ☐ Fail ☐ N/A	
UAT-USR-06	SA	**Actions on many accounts** 1. Tick two test accounts, click **Deactivate**, then **Activate**. 2. Tick a test account, click **Delete**, then type the count. 3. Try to tick your own account.	The action applies to every ticked account (at most 100); deleting is confirmed by typing the count; your own account cannot be ticked.	☐ Pass ☐ Fail ☐ N/A	

20. Role & Permission

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-ROL-01	SA	**Add a role** 1. Open **Role & Permission**, click **Add Role**. 2. Fill in the name and **Home Page**, tick Read on a few menus under **Menu & Permission**, then save. 3. Give that role to the test account, then sign in with it.	The test account lands on the role's home page and sees only the menus it was given.	☐ Pass ☐ Fail ☐ N/A	
UAT-ROL-02	SA	**Permissions apply at once** 1. Revoke Update on **Register Radio** from the test account's role. 2. The test account opens Register Radio and the details of a radio.	The Edit, Handover, Archive and Restore buttons do not show; changes through the address or the API are refused by the server.	☐ Pass ☐ Fail ☐ N/A	
UAT-ROL-03	SA	**View, change and delete a role** 1. Click **View** on the Super Admin role. 2. Change, then delete the test role.	**View** shows the permissions without changing them; the test role can be changed and deleted; the Super Admin role has no delete button.	☐ Pass ☐ Fail ☐ N/A	

21. Audit Log

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-AUD-01	SA	**Sign-in records** 1. Open **Audit Log**, then filter **Action** on the Sign-in group.	The successful and failed sign-ins (with the reason), sign-outs and expired sessions of the LOG scenarios are recorded with time, user and IP.	☐ Pass ☐ Fail ☐ N/A	
UAT-AUD-02	SA	**Data changes and Event details** 1. Filter **Entity** Radio and **Date range** Today. 2. Click the row of the radio change from UAT-REG-09.	**Event details** shows the time to the second, user, action, entity, IP, Browser and the changes line by line (values before and after).	☐ Pass ☐ Fail ☐ N/A	
UAT-AUD-03	SA	**Filters, calendar and views** 1. Choose **Date range** → **Custom range...**, click the first and the last day, then **Apply**. 2. Copy the page address and open it in a new tab. 3. Switch between the **Table** and **Log activity** views.	The list follows the date range; the copied address opens the same view with the same filters; Log activity shows a timeline of "who did what" sentences.	☐ Pass ☐ Fail ☐ N/A	
UAT-AUD-04	SA	**Audit records cannot be changed** 1. Check the Audit Log page and its event details.	No button changes or deletes an audit record; passwords, tokens and signature pictures never show in it.	☐ Pass ☐ Fail ☐ N/A	

22. API Tokens and the API

> Needs a tool to call the API, for example curl or Postman. Revoke the test tokens afterwards.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-API-01	SA	**Create a token** 1. Open **API Tokens**, click **New token**. 2. Choose **Read only** and a validity of 30 days, then create the token.	The token is shown only once, with a curl example; once the dialog is closed the token cannot be seen again; the token shows in the list with its end date.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-API-02	SA	**Call the API with a token** 1. Call `GET /api/v1/me` with the header `Authorization: Bearer <token>`. 2. With the same Read only token, try `POST /api/v1/radios`.	GET answers with the account of the token's owner; POST is refused (403) because the token may only read.	☐ Pass ☐ Fail ☐ N/A	
UAT-API-03	SA	**Revoke a token** 1. Click **Revoke** on the token of UAT-API-01. 2. Call `GET /api/v1/me` again with that token.	The token is recorded as revoked, and the call is answered 401.	☐ Pass ☐ Fail ☐ N/A	
UAT-API-04	SA	**API client** 1. Click **New client**, give it a name and a role, then create a token for it. 2. Deactivate that client, then call the API with its token.	The client is not listed in User Management; once deactivated, its token is refused (401).	☐ Pass ☐ Fail ☐ N/A	
UAT-API-05	SA	**API documentation and health check** 1. Click **API documentation**. 2. Open `GET /api/v1/health` without a token, then `/up`.	The documentation `/docs/api` opens (only for who may hold a token). Health answers the status `ok` with the checks web, database, storage and session; `/up` answers the status `up`.	☐ Pass ☐ Fail ☐ N/A	

23. Access per role

> Compare with the table of default access in the User Guide, section 1.

Tester		Date		Initials	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-PRM-01	VR	**Viewer Radio access** 1. Sign in as a Viewer Radio and open every menu that shows.	Only the Dashboard and the RADIO menus show (without E-Sign Master); no Add radio, Edit, Archive, Delete, New ticket, Start a session, Apply or Dismiss buttons; viewing, Export and Print the form still work.	☐ Pass ☐ Fail ☐ N/A	
UAT-PRM-02	AR	**Admin Radio access** 1. Sign in as an Admin Radio and open every menu that shows.	Full RADIO menus (without E-Sign Master), COF Scan view only, ICT Masterlist can ask for cell changes, Edit Approvals view only; the IT ASSETS, USER and SETTINGS sections do not show.	☐ Pass ☐ Fail ☐ N/A	

ID	Role	Scenario and steps	Expected result	Result	Notes
UAT-PRM-03	**DC**	**Document Controller access** 1. Sign in as a Document Controller and open every menu that shows.	Dashboard (view), COF Scan (view), ICT Masterlist with direct row edits, and Edit Approvals with **Approve** and **Reject**; the other radio menus, IT ASSETS, USER and SETTINGS do not show.	☐ Pass ☐ Fail ☐ N/A	
UAT-PRM-04	**SA**	**Super Admin access** 1. Sign in as a Super Admin and open every menu.	Every menu shows, including E-Sign Master, Snipe-IT, User Management, Audit Log and API Tokens.	☐ Pass ☐ Fail ☐ N/A	

24. Findings

Record every Fail here. Once it is fixed, test the scenario again and tick the result.

No	Scenario ID	Description of the finding	Severity	Found by / date	Fix (version)	Retest
1						☐ Pass ☐ Fail
2						☐ Pass ☐ Fail
3						☐ Pass ☐ Fail
4						☐ Pass ☐ Fail
5						☐ Pass ☐ Fail
6						☐ Pass ☐ Fail
7						☐ Pass ☐ Fail
8						☐ Pass ☐ Fail
9						☐ Pass ☐ Fail
10						☐ Pass ☐ Fail
11						☐ Pass ☐ Fail
12						☐ Pass ☐ Fail
13						☐ Pass ☐ Fail
14						☐ Pass ☐ Fail

25. Results summary

No	Section	Scenarios	Pass	Fail	N/A	Notes
1	Sign-in and sign-out	8				
2	Layout, language and Version history	6				
3	Notifications	3				
4	Dashboard	5				
5	Register Radio	16				
6	Radio details, handover and print form	7				
7	Needs Attention	6				
8	Service & Repair	7				
9	Stock Opname	6				
10	Radio History	2				
11	Radio Master Data	4				
12	E-Sign Master	3				
13	Import Excel	3				
14	COF Scan	4				
15	ICT Masterlist and Edit Approvals	9				
16	Snipe-IT	7				
17	Registered Users	6				
18	Role & Permission	3				
19	Audit Log	4				
20	API Tokens and the API	5				
21	Access per role	4				
	Total	**118**				

Conclusion

- ☐ Accepted
- ☐ Accepted with notes
- ☐ Rejected

Notes on the conclusion

26. Sign-off

By signing this page, the people below state that MTI Radio Management version 1.21.4 has been tested with the scenarios of this form, with the results recorded in the Results summary and the Findings, and the conclusion ticked there.

Tested by
User representative

Signature

Name _____

Position _____

Date _____

Reviewed by
IT/ICT team

Signature

Name _____

Position _____

Date _____

Approved by
Manager / process owner

Signature

Name _____

Position _____

Date _____