ShopEase SmartBand X1 - User Manual & Operating Guide

Model: SBX1-2026-BLK | High-Precision Fitness & Health Tracker

1. Box Contents & Hardware Overview

Congratulations on purchasing the ShopEase SmartBand X1. Your package includes the SmartBand X1 main tracking module, one hypoallergenic medical-grade silicone strap, a proprietary magnetic 2-pin USB charging cable (Length: 1.0m), and this quickstart user guide.

Hardware Specifications:

- **Display:** 1.47-inch AMOLED color touchscreen, 194x368 resolution, 282 PPI with anti-fingerprint coating.
- **Biometric Sensors:** 6-axis accelerometer, optical PPG heart rate sensor, SpO2 blood oxygen sensor, and capacitive skin contact sensor.
- **Connectivity:** Bluetooth Low Energy (BLE 5.2) with 10-meter unobstructed operating range.
- **Water Resistance:** 5 ATM / IP68 certified up to 50 meters water depth (suitable for pool swimming and showering; not for scuba diving or hot saunas).

2. Charging & Battery Maintenance

Before first use, charge the SmartBand X1 continuously for at least 90 minutes. Connect the magnetic charging cradle to the metallic charging pins on the rear of the band module. Connect the standard USB-A plug to any certified 5V/1A or 5V/2A wall power adapter or computer USB port.

Important Charging Precautions: Do not use fast-charging adapters exceeding 5V/2A (10W), as excessive voltage will degrade the 180mAh lithium-polymer battery cells. Ensure charging pins are clean and dry before docking. A full charge delivers up to 12 days of typical usage, or 6 days with Continuous 24/7 Heart Rate and Always-On Display enabled.

3. Smartphone Pairing & App Setup

The SmartBand X1 requires a smartphone running iOS 13.0 or Android 8.0 and above. Follow these steps to pair:

1. Download the official **'ShopEase Fitness'** app from the Apple App Store or Google Play Store.
2. Turn on Bluetooth on your smartphone and launch the app.
3. Sign in with your ShopEase account credentials.
4. Wake the SmartBand X1 by tapping the display; a QR code will appear.
5. In the app, tap 'Add New Device', select 'SmartBand X1', and scan the QR code displayed on the band screen.
6. Confirm the Bluetooth pairing challenge on both your phone and band within 30 seconds.

ShopEase SmartBand X1 - Operating Guide (Continued)

Page 2: Operations, Maintenance, Reset, and Warranty

4. Daily Gestures and Navigation

- **Swipe Up:** Access notifications, unread messages, and incoming call alerts.
- **Swipe Down:** Open the Quick Settings control center (Do Not Disturb, Flashlight, Find My Phone, Screen Brightness).
- **Swipe Left/Right:** Cycle through biometric widgets (Daily Activity Rings, Real-time Heart Rate, SpO2 Tracker, Weather, Music Controls).
- **Press & Hold Watchface (2 seconds):** Enter the watchface gallery to swap visual themes.

5. Troubleshooting and Factory Reset Procedures

If you encounter erratic behavior, inaccurate sensor metrics, or Bluetooth disconnection issues:

Soft Reboot: Swipe Down to Quick Settings > tap the Gear icon (Settings) > tap 'Restart'. All user data and step counts for the current day will be preserved.

Hard Factory Reset: To unpair and wipe all data: Settings > System > 'Factory Reset'. Confirm when prompted. The device will vibrate for 2 seconds, erase all onboard cache, and restart showing the original out-of-the-box QR pairing screen.

Unresponsive Screen Recovery: If the screen is black and does not respond to touch, connect the device to the magnetic charger. While charging, press and hold the hidden recessed pinhole button located beside the charging terminal using a paperclip for 8 seconds. The device will force reboot.

6. Cleaning, Skin Health & Safe Care

Rinse the band regularly with clean water after swimming, intense sweating, or exposure to sunscreen and lotions. Do not use abrasive chemicals, dish soap, or solvent cleaners. Dry the band thoroughly with a lint-free cloth. To avoid contact dermatitis, wear the band comfortably snug (not overly tight) allowing one finger of slack.

7. 1-Year Limited Hardware Warranty

The ShopEase SmartBand X1 includes a **One (1) Year Limited Warranty** covering defects in materials and workmanship under normal consumer use. The warranty covers sensor failure, display malfunction, and battery capacity loss exceeding 30% within 12 months. The warranty strictly excludes accidental screen cracking, liquid damage beyond 5 ATM ratings (such as hot showers/saunas), and unauthorized third-party disassembly. For warranty service, email warranty@shopease.com with proof of purchase.