Universal Robots Support > Downloads Web > UsingMagicFiles (04 Mar 2013, StefanToenderingStubgaard)

Using "magic" files to copy the log file or making backups

This guide will show you how to automatically copy the log file from the robot to a USB disk, using a so called magic file. Using this same technique it is also possible to make a backup of the programs on the robot to a USB disk. Magic files are only supported on robots with controllerbox 2.0, so if you have an old controllerbox you need to copy the files manually. See this guide about copying the files manually. Using a magic files i really simple:

1. Download the file.
2. Save it in the root folder on a USB stick.
3. Insert the USB stick into the robot.
4. A red "! USB !" warning sign will appear on the screen, warning not to remoe the USB stick.
5. The file will do it's magic.
6. A green "<- USB" sign will appear on the screen, telling that it is ok to remove the USB stick. *)
7. Remove the USB stick.

*) If more than one magic file is on a USB stick, they will be run in sequence, the warnings will then appear for each file. Do not remove the USB stick before after the last file have been run.

Below you will find a couple of magic files along with a short description of what they do:

Copy log file.

Download the magic file here: urmagic_log_file.sh

This file copies the log_history.txt file to the USB stick, and places it in a folder named after the robots serial number.

Backup all programs.

Download the magic file here: urmagic_backup_programs.sh

This file copies all program files to the USB stick, and places them in a folder named after the robots serial number.

Copy robot configuration files.

Download the magic file here: urmagic_configuration_files.sh

This file will copy all configuration files from the robot to the USB stick

Using "magic" file to make a screenshot of the GUI

1. Download the file.
2. Unpack it to the root folder on a USB stick.
3. Insert the USB stick in the USB slot in teach pendant.
4. A red "! USB !" warning sign will appear indicating a screenshot is taken
5. Await a green "<- USB" sign appearing, indicating the screenshot is completed, it is now safe to remove the USB-stick.

Screenshots are saved in a folder named \screenshots on the USB. If the folder does not already exist, it will be created. The saved files will be subsequently numbered, from 0 to 9999. File format is *.png.

If you want multiple screenshots, it can be done by inserting a keyboard and pressing the PrtScr? (PrintScreen?) button

1. Insert a USB keyboard in the USB slot inside of ControlBox?.
2. Press PrtScr? (Print Screen) for saving the screenshot on the USB stick.

It is possible to take screenshots as long as the USB stick is inserted.

Make screenshot of GUI.

Download the magic file here: urmagic_screenshot.zip

Using "magic" file to upload programs from USB to controller

1. Download the file.
2. Unpack it to the root folder on a USB stick.
3. Insert the USB stick in the USB slot in teach pendant.
4. A red "! USB !" warning sign will appear indicating a screenshot is taken
5. Await a green "<- USB" sign appearing, indicating the upload is completed, it is now safe to remove the USB-stick.

All programs and installation files present on the USB will be copied to the /programs folder, subfolders included. The following file types will be copied:

.urp

.txt

.script

.installation

.vars (files containing persistent variables, planned for software v1.8)

Upload programs from USB to controller.

Download the magic file here: urmagic_upload_programs.sh

Topic revision: r8 - 04 Mar 2013 - 12:03:28 - StefanToenderingStubgaard

Copyright © UNIVERSAL ROBOTS.