LISTA PARTI SCHEDA 26-349-0

Pos.	Qtà	Rif	Descrizione	Value	Package	PN	Costruttore	Note
1	41	C1,C2,C4,C5,C6,C8,C9,C10,C11,C13,C14,C15,C27,C29,C30,C31,C33,C40,C51,C53,C55,C56,C57,C58,C60,C61,C62,C63,C64,C66,C67,C68,C87,C88,C89,C90,C92,C100,C101,C102,C103	MLCC - SMD/SMT 50V 0.1uF X7R 0603 10%	100nF	SMD0603	C0603C104K5RACTU	KEMET	
2	8	C7,C21,C32,C35,C43,C52,C54,C91	MLCC - SMD/SMT 50V 0.01uF X7R 0603 5%	10nF	SMD0603	C0603C103J5RACTU	KEMET	
3	10	C12,C16,C17,C18,C22,C23,C24,C37,C39,C50	MLCC - SMD/SMT 25V 1uF X7R 0805 10%	1uF	SMD0805	08053C105K4Z2A	KYOCERA	
4	1	C19	MLCC - SMD/SMT 100V 1nF COG 0805 5%	1nF	SMD0805	08051A102J4T2A	KYOCERA	
5	4	C20,C42,C44,C45	MLCC - SMD/SMT 50V 1n5F COG 0805 5%	1n5F	SMD0805	C0805C152J5GACTU	KEMET	
6	12	C25,C26,C70,C72,C75,C76,C78,C79,C81,C82,C84,C104	Cond.Elt.Tantalio solido 35V SIZE C	4u7	6032-28	T491C475K035AT	KEMET	
7	1	C28	MLCC - SMD/SMT 2KV 820pF X7R1210 10%	820pF	SMD1210	1210GC821KAT2A	KYOCERA	
8	1	C34	MLCC - SMD/SMT 2K5V 5n6F X7R1210 10%	5n6F	SMD1825	825WC562KAT2A	KYOCERA	
9	2	C36,C41	MLCC - SMD/SMT 100V 470pF COG 0805 5%	470pF	SMD0805	08051A471JAT2A	KYOCERA	
10	1	C38	MLCC - SMD/SMT 50V 47nF X7R 0603 10%	47nF	SMD0805	C0805C473K5RAC	KEMET	
11	1	C46	MLCC - SMD/SMT 100V 330pF COG 0805 5%	330pF	SMD0805	C0805C331J1GAC	KEMET	
12	2	C47,C48	MLCC - SMD/SMT 50V 56pF COG 0805 5%	56pF	SMD0805	C0805C560J5GACTU	KEMET	
13	2	C49,C69	Cond.Elt.Tantalio solido 35V SIZE D	22uF	7343-43	T491X226K035AT7280	KEMET	
14	1	C59	MLCC - SMD/SMT 10V 10uF X7R 0805 10%	10uF	SMD0805	C0805C106K8RACTU	KEMET	
15	1	C65	MLCC - SMD/SMT 35V 4u7F X7R 1206 10%	4u7	SMD1206	C1206C475K6RACTU	KEMET	
17	6	C77,C80,C83,C86,C93,C94	Safety Capacitors WCAP-CSSA X&Y Safety 470pF 5kV 10% 1812	470pF	SMD1812	8853522110011	WURTH	
18	4	DL7,DL8,DL9,DL10	Diodo led smd 0805	VERDE	SMD0805	KP-2012SGD	KINGBRIGHT	
19	1	DL22	Diodo led smd 0805	BLU	SMD0805	KP-2012PBC	KINGBRIGHT	
20	11	DL24,DL26,DL27,DL28,DL29,DL30,DL31,DL32,DL33,DL34,DL35	Diodo led 90 gradi smd	GIALLO	APA2106SYCK/J3-PRV	APA2106SYCK/J3-PRV	KINGBRIGHT	
21	1	DL25	Diodo led 90 gradi smd	ROSSO	APA2106SECKJ3PRV	APA2106SECK/J3-PRV	KINGBRIGHT	
22	1	D1	ESD Protection compatible with CAN BUS	ESD2CAN24DBZRQ1	SOT23-3	ESD2CAN24DBZRQ1	TEXAS	
23	8	D2,D4,D13,D14,D17,D18,D21,D22	Small Signal Switching Diodes SINGLE JUNC. 75V 4.0NS COMP	1N4148WT	SOD-523F-2	1N4148WT	ONSEMI	
24	8	D5,D6,D7,D8,D9,D10,D11,D12	Rectifiers Diode, Superfast, SMA, 50V, 1A, 150C	ES1A	DO-214AC-2	ES1A	DIOTEC	
25	4	D15,D16,D19,D20	Rectifiers 1.0A 1000V	RS1M-13-F	SMA-2	RS1M-13-F	DIODES	
26	1	D23	Zener Diodes Zener Diode 3.0V 1000mW Surface Mount	PDZVTR3.0B	SOD-128-2	PDZVTR3.0B	ROHM	
27	2	D24,D25	Rectifiers Diode, Superfast, SMA, 100V, 1A, 150C	ES1B	SMA	ES1B	DIOTEC	
28	1	D26	DIODO EDS BIDIREZIONALE	ESD5V0D3B-TP	SOD-323-2	ESD5V0D3B-TP	MCC	
29	1	FL1	Circuiti filtro EMI 40 DB 50V 15A LEADED	BNX012-01		BNX012-01	MURATA	
30	1	F1	FUSIBILE +PORTAFUSIBILE 0154002.DRT	2A		0154002.DRT	LITTELFUSE	
32	2	JP1,JP2	HEADER DRITTO 2 PIN PASSO 2.54	SIP	THT	TSW-102-09-T-S-RA	SAMTEC	
33	1	J1	NANOFIT HDR RA DLR 4CKT TIN BLK	105314-1104		105314-1104	MOLEX	
34	1	J2	Connettore RJ45 8 Posizioni 90 gradi con leds	RJHSE538W01B	RJ45	RJHSE538W01B	AMPHENOL	

Pos.	Qtà	Rif	Descrizione	Value	Package	PN	Costruttore	Note
35	2	J4,J5	Mini-Fit Jr. Header, Dual Row, 10 vie	39-30-1102		39-30-1102	MOLEX	
36	1	J8	WR-BHD 2.54mm Male 6P Strt Gold Box Hdr	61200621621	THT	61200621621	WURTH	
37	1	J9	CONN.HEADER 2X5 RIGHT ANG	105314-2310	THT	105314-2310	MOLEX	
38	2	J10,J13	CONN.HEADER 2X1 DRITTO P2	448179	THT	448179	MOLEX	
39	1	J11	CONN.HEADER 2X3 DRITTO P2	105314-2306	THT	105314-2306	MOLEX	
40	1	J12	TTerminali e capicorda 2.54MM CGRIDIII HDR 8P V DR SHRD AU-E	105314-2208	THT	105314-2208	MOLEX	
41	1	K1	RELE' STATO SOLIDO SMD	CPC1017NTR	SOP-4	CPC1017NTR	IXYS	
42	1	L1	Filtro Modo Comune x CAN BUS	DLW32SH101XF2L	DLW32SH101XF2L	DLW32SH101XF2L	MURATA	
43	2	L2,L3	Ferrite Bead	BLM18BD102	SMD0603	BLM18BD102SN1D	MURATA	
44	1	L4	Common Mode Choke 470uH	470uH		744272471	WUERTH	
45	1	PT1	Resettable Fuses - PPTC PTS0603 0.05A, 15V	PTS060315V005		PTS060315V005	EATON	
46	2	P1,P3	Trimmer Resistors - Through Hole 3/8" 5Kohms Sealed Vertical Adjust	5K		3296W-1-502LF	BOURNS	
47	1	P2	Trimmer Resistors - Through Hole 3/8" 10Kohms Sealed Vertical Adjust	10K		3296W-1-103LF	BOURNS	
48	1	P4	Trimmer Resistors - Through Hole 3/8" 20Kohms Sealed Vertical Adjust	20K		3296W-1-203LF	BOURNS	
49	32	Q1,Q2,Q3,Q4,Q6,Q9,Q10,Q11,Q14,Q15,Q16,Q17,Q18,Q19,Q20,Q21,Q22,Q23,Q24,Q25,Q26,Q27,Q28,Q29,Q30,Q31,Q32,Q33,Q34,Q35,Q36,Q37	MOSFETs 60V 115mA N-Channel	2N7002LT1G	SOT23	2N7002LT1G	ON	
50	1	Q5	Bipolar Transistors - BJT BJT, SOT-323, 45V, 100mA, PNP	BC857BW	SOT323	BC857BW	DIOTEC	
51	2	Q7,Q8	MOSFETs 60V N-Channel Enhancement Mode MOSFET	PJE8472B_R1_00001	SOT-523-3	PJE8472B_R1_00001	PANJIT	
52	1	R1	Resistore thick film 1/10W 1% 0603	33R	SMD0603	MULTICOMP		
53	3	R2,R172,R173	Resistore thick film 1/10W 1% 0603	120R	SMD0603	MULTICOMP		
54	14	R5,R7,R20,R40,R52,R56,R60,R61,R77,R93,R103,R126,R132,R189	Resistore thick film 1/10W 1% 0603	1K	SMD0603	MULTICOMP		
55	3	R6,R15,R46	Resistore thick film 1/10W 1% 0603	2K2	SMD0603	MULTICOMP		
56	10	R8,R66,R69,R87,R119,R128,R135,R141,R151,R166	Resistore thick film 1/10W 1% 0603	280R	SMD0603	MULTICOMP		
57	22	R9,R16,R19,R22,R23,R24,R59,R67,R70,R79,R89,R91,R94,R108,R109,R116,R125,R134,R139,R149,R160,R171	Resistore thick film 1/10W 1% 0603	10K	SMD0603	MULTICOMP		
58	1	R10	Resistore thick film 1/4W 1% 1206	1K5	SMD1206	MULTICOMP		
59	18	R11,R12,R13,R18,R21,R68,R71,R72,R73,R78,R90,R92,R111,R112,R118,R147,R157,R163	Resistore thick film 1/10W 1% 0603	100K	SMD0603	MULTICOMP		
60	3	R14,R105,R114	Resistore thick film 1/4W 1% 1206	1K3	SMD1206	MULTICOMP		
61	9	R17,R55,R88,R100,R101,R102,R150,R159,R169	Resistore thick film 1/10W 1% 0603	3K3	SMD0603	MULTICOMP		
62	1	R25	Resistore thick film 1/8W 1% 0805	2K2	SMD0805	MULTICOMP		
63	2	R26,R64	Resistore thick film 1/8W 1% 0805	3K3	SMD0805	MULTICOMP		
64	2	R27,R39	Resistore thick film 1/8W 1% 0805	1K	SMD0805	MULTICOMP		

Pos.	Qtà	Rif	Descrizione	Value	Package	PN	Costruttore	Note
65	3	R28,R29,R30	Resistore thick film 1/4W 1% 1206	1R	SMD1206	MULTICOMP		
66	1	R31	Resistore thick film 1/4W 1% 1206	10K	SMD1206	MULTICOMP		
67	1	R32	Resistore thick film 1/4W 1% 1206	18K	SMD1206	MULTICOMP		
68	2	R33,R204	Resistore thick film 2W 1% 2512	33K	SMD 2512	MULTICOMP		
69	7	R34,R35,R36,R41,R42,R44,R45	Resistore thick film 1/4W 1% 1206	130K	SMD1206	MULTICOMP		
70	1	R37	Resistore thick film 1/4W 1% 1206	220K	SMD1206	MULTICOMP		
71	1	R38	Resistore thick film 1/8W 1% 0805	20K	SMD0805	MULTICOMP		
72	2	R43,R47	Resistore thick film 1/4W 1% 1206	4K7	SMD0805	MULTICOMP		
73	1	R48	Resistore thick film 1/8W 1% 0805	5K6	SMD0805	MULTICOMP		
74	1	R49	Resistore thick film 1/8W 1% 0805	470R	SMD0805	MULTICOMP		
75	1	R50	Resistore thick film 1/8W 1% 0805	4K32	SMD0805	MULTICOMP		
76	1	R51	Resistore thick film 1/10W 1% 0603	1K2	SMD0603	MULTICOMP		
77	1	R53	Resistore thick film 1/10W 1% 0603	8K45	SMD0603	MULTICOMP		
78	27	R54,R123,R124,R131,R133,R138,R145,R146,R148,R155,R158,R164,R165,R170,R178,R179,R181,R183,R185,R187,R191,R193,R196,R197,R199,R201,R203	Resistore thick film 1/10W 1% 0603	33K	SMD0603	MULTICOMP		
79	1	R57	Resistore thick film 1/8W 1% 0805	390R	SMD0805	MULTICOMP		
80	1	R58	Resistore thick film 1/10W 1% 0603	18K	SMD0603	MULTICOMP		
81	1	R62	Resistore thick film 1/8W 1% 0805	10R	SMD0805	MULTICOMP		
82	1	R63	Resistore thick film 1/8W 1% 0805	120K	SMD0805	MULTICOMP		
83	1	R65	Resistore thick film 1/8W 1% 0805	220R	SMD0805	MULTICOMP		
84	1	R74	Resistore thick film 1/10W 0.1% 10PPM 0603	2K67	SMD0603	RP0603BRD072K67L		
85	2	R75,R84	Resistore thick film 1/8W 1% 0805	10K	SMD0805	MULTICOMP		
86	1	R76	Resistore thick film 1/8W 1% 0805	2K	SMD0805	MULTICOMP		
87	1	R80	Resistore thick film 1/2W 1% 2512	100R	SMD2512	MULTICOMP		
88	1	R81	Resistore thick film 1/10W 0.1% 10PPM 0603	33K	SMD0603	RT0603BRC0733KL		
89	1	R82	Resistore thick film 1/10W 0.1% 10PPM 0603	100K	SMD0603	RT0603BRB07100KL		
90	1	R83	Resistore thick film 1/10W 0.1% 10PPM 0603	11K	SMD0603	RT0603BRD0711KL		
91	1	R85	Resistore thick film 1/10W 0.1% 10PPM 0603	14K	SMD0603	RT0603BRB0714KL		
92	1	R86	Resistore thick film 1/8W 1% 0805	47R	SMD0805	MULTICOMP		
93	1	R95	Resistore thick film 1/10W 1% 0603	330R	SMD0603	MULTICOMP		
94	1	R104	Resistore thick film 1/4W 1% 1206	1K8	SMD1206	MULTICOMP		
95	1	R106	Resistore thick film 1/10W 1% 0603	12K	SMD0603	MULTICOMP		
96	2	R107,R115	Resistore thick film 1/10W 1% 0603	15K	SMD0603	MULTICOMP		
97	1	R110	Resistore thick film 1/10W 1% 0603	2K	SMD0603	MULTICOMP		
98	3	R113,R117,R188	Resistore thick film 1/10W 1% 0603	4K7	SMD0603	MULTICOMP		
99	16	R120,R121,R122,R129,R130,R136,R137,R142,R143,R144,R152,R153,R154,R162,R167,R168	Resistore thick film 1/4W 1% 1206	2K	SMD1206	MULTICOMP		
100	1	R127	Resistore thick film 1/10W 1% 0603	2K	SMD1206	MULTICOMP		
101	3	R140,R156,R161	Resistore thick film 1/10W 1% 0603	47K	SMD0603	MULTICOMP		
102	1	R174	Resistore thick film 1/8W 1% 0805	330K	SMD0805	MULTICOMP		
103	1	R175	Resistore thick film 1/8W 1% 0805	22K	SMD0805	MULTICOMP		
104	13	R176,R177,R180,R182,R184,R186,R190,R192,R194,R195,R198,R200,R202	Resistore thick film 1/10W 1% 0603	680R	SMD0603	MULTICOMP		

Pos.	Qtà	Rif	Descrizione	Value	Package	PN	Costruttore	Note
105	12	TP2,TP5,TP6,TP10,TP11,TP13, TP15,TP16,TP23,TP24,TP26,TP 27	Test Plugs & Test Jacks TEST POINT YELLOW	YEL		5004	KEYSTONE	
106	4	TP3,TP4,TP7,TP25	Test Plugs & Test Jacks TEST POINT BLK .063	BLK		5006	KEYSTONE	
107	2	TP12,TP28	Test Plugs & Test Jacks TEST POINT (GREEN)	GRN		5116	KEYSTONE	
108	2	TP14,TP29	Test Plugs & Test Jacks TEST POINT WHITE .040	WHT		5002	KEYSTONE	
109	1	U1	Digital Isolators Reinforced, fast, low-power 2-channel di	MAX22246CAWA/V+	SOIC-8	MAX22246CAWA/V+	ANALOG DEVICE	
110	1	U2	CAN Interface IC High-speed CAN transceiver	TJA1050T/CM,118	SOIC-8	TJA1050T	NXP	
111	2	U3,U19	Amplificatori di isolamento High Stability Isolated Error Amplifier	ADuM3195BRQZ	QSOP-16	ADuM3195BRQZ	ANALOG DEVICE	
112	2	U4,U6	Logic Gates SSOP5 IC LOGIC 2INPUT AND GATE	BD7LS08ZG-CTL	SSOP-5	BD7LS08ZG-CTL	ROHM	
113	19	U5,U7,U21,U22,U26,U35,U36,U 41,U44,U45,U46,U47,U48,U49,U 50,U51,U52,U53,U54	Transistor Output Optocouplers	TLP383D4BLLTLE	SO-6-4	TLP383D4BLLTLE	TOSHIBA	
114	4	U8,U37,U38,U42	Supervisory Circuits Ultra-Lo 150nA	TPS3839G33DBZR	SOT23-3	TPS3839G33	TEXAS	
115	2	U10,U23	Op Amps Dual Operational Amp lifier TSSOP8	LM358PT	TSSOP-8	LM358PT	TEXAS	
116	1	U11	Digital Isolators 3-CHANNEL DIGITAL ISOLATORS	ADUM1310ARWZ-RL	WIDE-SOIC	ADUM1310ARWZ-RL	ANALOG DEVICE	
117	1	U12	Digital to Analog Converters - DAC Single 12-bit DAC	MCP4821T-E/MS	MSOP8	MCP4821T-E/MS	MICROCHIP	
118	1	U13	Timers & Support Products Single Precision Timer	NE555DR1G4	SOIC-8	NE555DR1G4	TEXAS	
119	1	U14	Flip-Flops Dual CMOS	CD4013BPWR	TSSOP-14	CD4013BPWR	TEXAS	
120	3	U16,U17,U18	Gate Drivers Dual 5A Hi-Spd Low- Side Pwr MOSFET	UCC27525DSDT	WSON-8	UCC27525DSDT	TEXAS	
121	1	U20	Switching Controllers Prog Off-Line PWM Controller	UC3841DW	SOIC18-W	UC3841DW	TEXAS	
123	1	U24	Optoisolatore 5300VRMS singolo	SI8710AD-B-ISR	S-DIP-6	SI8710AD-B-ISR	SKYWORKS	
124	1	U25	Analog Comparators VOLTAGE COMPARATOR	LM311MX/NOPB	SOIC-8	LM311MX/NOPB	TEXAS	
125	1	U27	Voltage References 100-ppm/C precision micropower shunt vol	LM4040AIM3X-2.0/G4	SOT-23	LM4040AIM3X-2.0/G4	TEXAS	
126	1	U28	32bit ARM 4F 1MB Flash, 256K Ram, 2xCAN-FD	SAME51J20A-AF	TQFP	SAME51J20A-AF	MICROCHIP	
127	2	U29,U31	DC/DC Converters 0.5A switching regulator in a SIP3 package	RBT05W24S05	RBT05W	RBT05W24S05	MEANWELL	
128	1	U30	DC/DC Converters 18-36Vin 15Vout 1A 15W 2x1 Med Iso Reg	MDS15B-15	MDS15B-15	MDS15B-15	MEANWELL	
129	1	U32	DC/DC Converters 1W DC/DC Converter isolated, unregulated	TMA-1515S	THT	TMA-1515S	TRACO	
130	1	U33	LDO Voltage Regulators 3.3V 1A Positive	NCP1117ST33T3G	SOT223	NCP1117ST33T3G	ON	
131	1	U34	DC/DC Converters 9-36Vin 5V 0-600mA 3W DIP Med	MDS03F-05	MDS03F-05	MDS03F-05	MEANWELL	
132	1	U55	Digital Isolators General-purpose qua d-channel 2/2 digit	ISO6742FDWR	SOIC-16	ISO6742FDWR	TEXAS	
133	2	U57,U58	RS-422/RS-485 Interface IC 10MBps Full Duplex 5V	ADM4857ARZ-REEL7	SOIC-8	ADM4857ARZ-REEL7	ANALOG DEVICE	
134	4	Z1,Z2,Z3,Z4	Zener Diodes	PLVA650A,215	SOT23-3	PLVA650A,215	NEXPERIA	