Mass properties of Joint02_Assembly
Configuration: Default
Coordinate system: Joint02_Coordinates

Mass = 687.67 grams

Volume = 341496.18 cubic millimeters

Surface area = 135243.10 square millimeters

Center of mass: (millimeters)
X = -90.56
Y = 0.00
Z = -50.83

Principal axes of inertia and principal moments of inertia: (grams * square millimeters)
Taken at the center of mass.

Ix = (0.99, 0.00, -0.14)	Px = 355190.74
Iy = (-0.14, 0.00, -0.99)	Py = 1854079.85
Iz = (0.00, 1.00, 0.00)	Pz = 1913642.15

Moments of inertia: (grams * square millimeters)
Taken at the center of mass and aligned with the output coordinate system. (Using positive tensor notation.)

Lxx = 384127.81	Lxy = -23.76	Lxz = -206242.83
Lyx = -23.76	Lyy = 1913642.15	Lyz = 23.52
Lzx = -206242.83	Lzy = 23.52	Lzz = 1825142.79

Moments of inertia: (grams * square millimeters)
Taken at the output coordinate system. (Using positive tensor notation.)

Ixx = 2160985.20	Ixy = -64.60	Ixz = 2959368.75
Iyx = -64.60	Iyy = 9330286.24	Iyz = 0.60
Izx = 2959368.75	Izy = 0.60	Izz = 7464929.50

One or more components have overridden mass properties:
Toothless Pulley<4><Default>
Toothless Pulley<3><Default>
NEMA17 Stepper MotorAssembly
M4_ISO (4762)_35<91290A173>
M4_ISO (4762)_35<91290A173>
M4_ISO (4762)_35<91290A173>
M3_ISO (4762)_25<90358A120>
M3_ISO (4762)_25<90358A120>
M3_ISO (4762)_25<90358A120>
M3_ISO (4762)_25<90358A120>
Contact ball bearing(627) 7x22x7<4481N35>
Contact ball bearing(627) 7x22x7<4481N35>