(NEW)

PANEL PP

VOLTAGE: 208 / 120 **AMP: 400**
PHASE: 3 **MAIN: MCB**

DESCRIPTION	KW	BKR	CK	PH	CK	BKR	KW	DESCRIPTION
RTU-1	15.6	90/3	1	A	2	30/3	0.0	SPD
-----	15.6	---	3	B	4	---	0.0	-----
-----	15.6	---	5	C	6	---	0.0	-----
RTU-1	15.6	90/3	7	A	8	30/2	2.3	CU-1/FCU-1
-----	15.6	---	9	B	10	---	2.3	-----
-----	15.6	---	11	C	12	20/2	1.3	WH-WATER HEATER
SPACE		---	13	A	14	---	1.3	-----
SPACE		---	15	B	16	---		SPACE
SPACE		---	17	C	18	---		SPARE
SPACE		---	19	A	20	---		SPARE
SPACE		---	21	B	22	---		SPARE
SPACE		---	23	C	24	---		SPARE
PANEL RP-A	12.2	225/3	25	A	26	---		
-----	13.6	---	27	B	28	---		SPACE SUBFEED SECTION
-----	16.9	---	29	C	30	---		

NOTE: PROVIDE EQUIPMENT GROUND BUS

Phase A Load (kVA)	46.8	Connected kVA	143.0	100%	A-B Balance
Phase B Load (kVA)	47.0	Dem. kVA	129.2	95%	B-C Balance
Phase C Load (kVA)	49.2	Dem. Amps	358.8	95%	C-A Balance

(NEW)

PANEL RP-A

VOLTAGE: 208 / 120 **AMP: MLO**
PHASE: 3 **MAIN: 225**

	DESCRIPTION	KW	BKR	CK	PH	CK	BKR	KW	DESCRIPTION	
	MISC. FIRE ALARM CONTROL PANEL	0.2	20/1	1	A	2	20/1	0.4	LTG-BACK OF HOUSE	
	LTG - PARPET LIGHTING	0.5	20/1	3	B	4	20/1	0.4	LTG-BUILDING CANOPY	
	LTG - ENTRY/WEATHER VESTIBULE	0.1	20/1	5	C	6	20/1	1.2	SIGN-BUILDING SIGN - BACK	
	REC - EMPLOYEE LOUNGE	0.4	20/1	7	A	8	20/1	0.1	LTG-TRANSACTION BAR	
	LTG - RELAXED SEATING	0.2	20/1	9	B	10	20/1	0.5	LTG VESTIBULE	
	SIGN-BUILDING SIGN - FRONT	1.2	20/1	11	C	12	20/1	0.9	REC-PRINTER TRANSACTION	
	REC - COPIER LOBBY	0.8	20/1	13	A	14	20/1	0.0	MISC-LIGHTING CONTROL PANEL	
	LTG - ELEC/IT/MEETING/BOOTHS	0.2	20/1	15	B	16	20/1	0.7	REC-RESTROOM/JAN	
	REC - BOOTH 104	0.5	20/1	17	C	18	20/1	0.9	REC-MEETING ROOM	
#	REC - REFIGERATOR	1.2	20/1	19	A	20	20/1	0.5	MISC-DDCV HOTBOX	*
	REC - WORK ROOM	0.4	20/1	21	B	22	20/1	0.4	REC-PRINTER -TRANSACTION	
	MISC - MECHOSHADES	0.5	20/1	23	C	24	20/1	0.2	REC-TECH WALL/GATHERING	
	MISC - RECIRCULATING PUMP	0.2	20/1	25	A	26	20/1	0.3	MISC-DOOR MOTOR/PUSH...	
	MISC - CONDENSATE PUMP	0.1	20/1	27	B	28	20/1	1.5	REC-TCR TRANSACTION BAR	
	MID- IRRIGATION BACKFLOW	0.5	20/1	29	C	30	20/1	1.1	REC-QUAD ELEC/IT	
	REC - TRANSACTION BAR	0.7	20/1	31	A	32	20/1	0.4	REC-ROOF	
	REC - TRANSACTION BAR	0.7	20/1	33	B	34	20/2	0.0	LTG-LIGHT POLES	
	MISC-DOOR MOTOR/PUSH...	0.3	20/1	35	C	36	---	0.0	------	
	REC-TRANSACTION	0.4	20/1	37	A	38	20/1	1.8	MISC-DRIVE-UP ATM	
	REC-VESTIBULE/ELEC/IT	0.4	20/1	39	B	40	20/1	0.5	MISC-VTM	
	REC-TECH WALL	0.4	20/1	41	C	42	20/1	0.5	REC-PHONE RM	
	REC-EMPLOYEE LOUNGE	0.5	20/1	43	A	44	20/1	1.2	SIGN-BUILDING SIGN - BACK	
	REC-QUAD ELEC/IT	1.4	20/1	45	B	46	20/1	1.1	REC-QUAD ELEC/IT	
	MISC-CRITICAL LIGHTING...	0.2	20/1	47	C	48	20/1	1.5	REC-DISH WASHER	#
	MISC-MECHOSHADES-MEETING..	0.5	20/1	49	A	50	20/1	0.7	REC-NIGHT DEPOSITORY	
	REC-RELAXED SEATING	0.5	20/1	51	B	52	20/1	1.4	REC-QUAD ELEC/IT	
	REC-MICROWAVE LOUNGE	1.5	20/1	53	C	54	20/1	0.4	REC-LIBRARY COUNTER	
	MISC-VAT BLOWER	0.5	20/1	55	A	56	20/1	0.2	MISC-DTOPEN/CLOSE SIGN	
	MISC-LIGHTING CONTACTOR	0.2	20/1	57	B	58	20/1	0.5	MISC-TRANSAC MECHOSHADES	
	REC-LIBRARY COUNTER	0.4	20/1	59	C	60	20/1	0.6	LTG-DRIVE UP ATM TOPPER	
	REC-PHONE RM	0.2	20/1	61	A	62	20/1	0.6	LTG-DRIVE UP ATM TOPPER	
	REC-TRANSACTION DISPLAY	0.4	20/1	63	B	64	20/1	0.5	MISC-BOOTH MECHOSHADES	
	LTG-LIGHT POLES	0.0	20/2	65	C	66	20/1	0.9	REC-WORK ROOM	
	-----	0.0	---	67	A	68	20/1	0.2	REC-DRINKING FOUNTAIN	#
	MISC-VAT DIVERTER	0.5	20/1	69	B	70	20/1	0.2	MISC-IRRIGATION CONTROL	
	REC-ADA COUNTER	0.9	20/1	71	C	72	20/1	1.0	OPEN/CLOSE SIGN	
	LTG-ATM CANOPY	0.1	20/1	73	A	74	20/1	0.1	LIGHTING CONTACTOR	
	REC-WORK 111	0.4	20/1	75	B	76	20/1		SPARE	
	SIGN-MONUMENT SIGN	1.2	20/1	77	C	78	20/1		SPARE	
	REC-MONUMENT SIGN RECEPT	0.2	20/1	79	A	80	20/1		SPARE	
	SPARE		20/1	81	B	82	20/1		SPARE	
	SPARE		20/1	83	C	84	20/1		SPARE	

NOTE: PROVIDE EQUIPMENT GROUND BUS
- PROVIDE CONNECTION TO NEW GFCI CIRCUIT BREAKER.
* - PROVIDE CONNECTION TO NEW GFPE CIRCUIT BREAKER.

Phase A Load (kVA)	12.2	Connected kVA	42.6	90%	A-B Balance
Phase B Load (kVA)	13.6	Dem. kVA	31.4	81%	B-C Balance
Phase C Load (kVA)	16.9	Dem. Amps	87.1	72%	C-A Balance

PANELBOARD NOTES:

1. PROVIDE PANELBOARD AS SPECIFIED ON ELECTRICAL PANEL SCHEDULES AND RISER DIAGRAM.
2. CONTRACTOR SHALL ENSURE ALL NEC WORKING SPACE AND DEDICATED EQUIPMENT SPACE CLEARANCES ARE PROVIDED PER NEC 110. IF FIELD CONDITIONS DO NOT ALLOW FOR ADEQUATE CLEARANCE AT THE LOCATION SHOWN ON THE PLANS, THE CONTACTOR SHALL PROPOSE AN ALTERNATE LOCATION FOR REVIEW AND APPROVAL BY ENGINEER PRIOR TO ROUGH-IN OF PANEL.
3. FIELD COORDINATE INSTALLATION WITH OTHER TRADES TO ENSURE NO FOREIGN SYSTEMS ARE LOCATED WITHIN THE DEDICATED EQUIPMENT SPACE OF THE ELECTRICAL EQUIPMENT.
4. ALL BUSING SHALL BE COPPER.
5. BOLT-ON BREAKERS ONLY.
6. PROVIDE DOOR-IN-DOOR TRIM.
7. PROVIDE TYPEWRITTEN CIRCUIT DIRECTORY CARD.
8. ALL PANELBOARDS SHALL BE SUPPLIED FROM THE SAME MANUFACTURER.
9. IN EXISTING INSTALLATIONS, NEW CIRCUIT BREAKERS SHALL MATCH EXISTING IN TYPE AND AIC RATING, UNO.
10. LOAD TYPES IN DESCRIPTION AS FOLLOWS:

BOLD TEXT	NEW LOAD, WIRE, CONDUIT, CIRCUIT BREAKER(AS APPLICABLE)
GREY TEXT	EXISTING LOAD, WIRE, CONDUIT, CIRCUIT BREAKER(AS APPLICABLE) TO REMAIN
(OLD X-#)	RELOCATED CIRCUIT FROM OLD PANEL 'X', CIRCUIT '#'
CLG	COOLING
EWH	ELECTRIC WATER HEATER
HTG	HEATING
KIT	KITCHEN
LTG	LIGHTING
MISC	MISCELLANEOUS
MTR	MOTOR
REC	RECEPTACLE
REF	REFRIGERATION

11. CIRCUIT BREAKER TYPE ABBREVIATIONS ARE AS FOLLOWS:

AFCI	ARC-FAULT CIRCUIT INTERRUPTER
F/RED	RED MARKING & "FIRE ALARM CIRCUIT"
GFCI	GROUND-FAULT CIRCUIT INTERRUPTER
GFPE	30 mA EQUIPMENT GROUND FAULT PROTECTION
HT2	HANDLE TIE FOR SHARED NEUTRAL CIRCUIT (2 POLE)
HT3	HANDLE TIE FOR SHARED NEUTRAL CIRCUIT (3 POLE)
L/ON	LOCKABLE "LOCK ON" HANDLE HARDWARE
L/OFF	"LOCK OFF"
TAN	TANDEM
SHNT	SHUNT TRIP
SWD	SWITCH DUTY RATED
SWN	SWITCHED NEUTRAL

12. CIRCUIT BREAKER FURNISHED AS FOLLOWS:

ETR	EXISTING TO REMAIN
FW	FACTORY WIRED
NEW	NEW TO MATCH EXISTING
REM	REMOVE EXISTING AND PROVIDE NEW

13. LOAD FUNCTION AS FOLLOWS:

CONT	CIRCUIT CONTROLLED BY CONTRACTOR
HOOD	CIRCUIT CONTROLLED BY HOOD FIRE SUPPRESSION SYSTEM
T/C	CIRCUIT THRU TIME CLOCK
PHO	CIRCUIT THRU PHOTOCELL
LCP	CIRCUIT THRU LIGHTING CONTROL PANEL
L/C	CIRCUIT THRU LIGHTING CONTACTOR

PRAXIS3

100 Peachtree St NW
Suite 1450
Atlanta, GA 30303
404-875-4500 tel
www.praxis3.com

GEORGIA REGISTERED No. 041508 PROFESSIONAL ENGINEER RAHN ONEAL WILLIAMS

Copyright (c) 2024 Praxis3, LLC

All reports, plans, specifications, computer files, field data, notes and other documents and instruments prepared by Praxis3 shall retain all common law, statutory and other reserved rights, including copyright thereto.

This drawing may not be reproduced in whole or in part without written permission of Praxis3. It is to be returned upon request. Scales as stated are valid on the original drawings.

Rev	Date	Comments
	07/02/2026	PERMIT SET

Client:
FIFTH THIRD BANK

Project Number: 26032
Project Name:
FIFTH THIRD BANK WATSON
1,900 SF

2711 WATSON BOULEVARD
WARNER ROBBINS, GA 31093

Key Plan:

Sheet Title:
ELECTRICAL PANEL SCHEDULES

Sheet Number:
E-610

6/30/2026 2:32:09 PM