HARDWARE SCHEDULE

Set 1.0
Doors: 100 (Weather Vestibule)
Description: Standard - Exterior Aluminum Storefront Pair - Access Control - Panic Egress - Auto-Door

2 Continuous Hinge x EPT prep	CFM__HD1 PT		PE
1 Elec CVR Exit Device (Nightlatch)	53 55 56-HK AD8410 106 x less pull (24V)	US32D	SA
1 Elec CVR Exit Device (Exit Only)	53 55 56-HK AD8410 EO (24V)	US32D	SA
1 Mortise Cylinder	41 series as req'd	US32D	SA
1 Permanent Medeco Cylinder	By Owner (installed by Contractor – coordinate / verify keying with owner)	24	MC
2 Offset Pull	RM201	US32D316	RO
1 Conc Overhead Stop	6-X36	630	RF
1 Door Closer W/ Stop	281 CPS	EN	SA
1 Blade Stop Spacer	581 as req'd	EN	SA
1 Closer Mtg Plate	281D as req'd	EN	SA
1 Automatic Opener	6061 (D) - Push Side	689	NO
1 Threshold	253x3AFG FHSL14SS		PE
1 Credential Reader	By Div 28 (12V)		OT
1 ADA Switch – Flush Mount Box	10BOXJAMBFM		BEA
1 ADA Switch - Jamb Mount	503		NO
2 Power Supply Battery (24V)	B-24-5		SU
2 Position Switch	DPS-M		SU
2 Shared Power Supply (24V)	AQD2-8F8R2 24V-2 AMP		SU
2 Electric Power Transfer	EPT10		VD
1 Seals, Sweeps & Astragals	By Aluminum Door Mfr.		OT

Notes:
Entry by valid credential at reader to retract latches (both leafs) or manual key (active leaf) when locked.
Free egress (both leafs) at all times. Push / Pull operation as required by electronic dogging of exit devices, either timed unlock via access control system or by Hex Key dogging
Door position switches to monitor opening status. Exit devices have integral RX feature to signal egress.
Auto-Door operator and ADA switches must be integrated with electronic exit devices.
Exterior ADA switch is controlled by exit device latch monitor in active door leaf. Switch active only when latch is in retracted position.
Vestibule ADA switch always active and will unlock door for egress.
See plan sheet for locations of automated door leafs and switch locations.
Coordinate with electrical and security contractors.

Set 3.0
Doors: 110 (Employee Lounge)
Description: Standard - Exterior Aluminum Storefront Single - Access Control Function

1 Continuous Hinge	CFM__HD1		PE
1 Rim Exit Device (NL x less dogging)	43 AD8504 Less Pull	US32D	SA
1 Rim Cylinder	34 series as req'd	US32D	SA
1 Permanent Medeco Cylinder	By Owner (installed by Contractor – coordinate keying with owner)	24	MC
1 Electric Strike w/ Latch Monitor	9500-LBM (12V)	630	HS
1 Offset Pull	RM201 Mtg-Type 12XHD	US32D316	RO
1 Door Closer w/ Stop	281 CPS	EN	SA
1 Blade Stop Spacer	581 as req'd	EN	SA
1 Closer Mtg Plate 281D as req'd EN SA			
1 Threshold	253x3AFG FHSL14S		PE
1 Access Control Reader	By Div 28 (12V)		OT
1 Power Supply	By Div 28 (12V)		OT
1 Seals, Sweeps & Astragals	By Aluminum Door Mfr.		OT

Notes:
Entry by valid input at exterior reader to release electric strike and shunt alarm or manual key.
Free egress by manual push bar operation to retract latch
LBM feature in electric strike to monitor opening status, shunted by valid input at exterior reader.
Coordinate with electrical and security contractors.

Set 4.0
Doors: 101 (Entry)
Description: Double Interior Aluminum Storefront Pair – Push / Pull Function - Auto-Door

2 Continuous Hinge	CFM__HD1		PE
2 Push / Pull Set	RM251 Mtg-Type 12XHD	US32D	RO
1 Conc Overhead Stop	6-X36	630	RF
1 Door Closer W/ Stop	281 CPS	EN	SA
1 Blade Stop Spacer	581 as req'd	EN	SA
1 Closer Mtg Plate	281D as req'd	EN	SA
1 Automatic Opener	6061 (D) - Push Side	689	NO
1 ADA Switch - Jamb Mount	503		NO
1 ADA Switch Mounting Box	10BOXJAMBFM		BEA
1 ADA Switch – Vestibule Button	10PBDGP1		BEA
1 ADA Switch Mounting Box	10BOX475SQFM		BEA
1 Seals, Sweeps & Astragals	By Aluminum Door Mfr.		OT

Notes:
Auto door operation by Interior & Vestibule ADA switches at all times.
See plan sheet for locations of automated door leafs and switch locations.
Coordinate with electrical and security contractors.

Set 5.0 (1900 Narrow)
Doors: 101 (Entry)
Description: Interior Aluminum Storefront Single - Push / Pull Function - Auto-Door

1 Continuous Hinge	CFM__HD1		PE
1 Push Pull Set	RM251 Mtg-Type 12XHD	US32D	RO
1 Conc Overhead Stop	6-X36	630	RF
1 Automatic Opener	6061 (D) - Push Side	689	NO
1 ADA Switch	503 (jamb)		NO
1 ADA Switch Mounting Box	10BOXJAMBFM		BEA
1 ADA Switch – Vestibule Button	10PBDGP1		BEA
1 ADA Switch Mounting Box	10BOX475SQFM		BEA
1 Seals, Sweeps & Astragals	By Aluminum Door Mfr.		OT

Notes:
Auto door operation by Interior & Vestibule ADA switches at all times.
See plan sheet for locations of automated door leaf and switch locations.
Coordinate with electrical and security contractors.

Set 6.0
Doors: 111 (Work Room)
Description: Access Control Function x Door Closer x Viewers

3 Hinge, Full Mortise	TA2714 NRP (outswing) / TA2714 (inswing)	US26D	MK
1 Storeroom Lock	10XG04 LL (w/ std cyl)	US26D	SA
1 Permanent Medeco KIL Cylinder	By Owner (installed by Contractor – coordinate keying with owner)	24	MC
1 Electric Strike w/ Latch Monitor	5200C-LBM (12V)	630	HS
1 Door Stop	441CU floor stop (Use Rixson 10-x36 overhead stop as req'd if floor stop is not feasible	US26D	RO
1 Door Closer	281 O / P10 as req'd	EN	SA
1 Kick Plate	K1050 10" HGT x CSK x BEV	US32D	RO
3 Silencer	608/609 as req'd		RO
1 Access Control Reader	By Div 28 (12V)		OT
1 Wiring Harness (frame)	QC-C3000P		MK
1 RX Motion Sensor	By Div 28 (12V)		SU
1 Power Supply	By Div 28 (12V)		OT
2 Door Scope / Viewer	DS1000	626	OT

Notes:
Entry by valid input at reader or manual key. Free egress at all times.
LBM in electric strike to monitor opening status, shunted by RX motion sensor if required.
Coordinate with electrical and security contractors.
Mount door scopes according to typical mounting height diagram

Set 7.0
Doors: 106 (Electrical/IT Room)
Description: Access Control Function x Closer w/ Stop

3 Hinge, Full Mortise	TA2714 NRP (outswing) / TA2714 (inswing)	US26D	MK
1 Storeroom Lock	10XG04 LL (w/ std cyl)	US26D	SA
1 Permanent Medeco KIL Cylinder	By Owner (installed by Contractor – coordinate keying with owner)	24	MC
1 Electric Strike w/ Latch Monitor	5200C-LBM (12V)	630	HS
1 Door Closer W/ Stop	281 CPS	EN	SA
3 Silencer	608/609 as req'd		RO
1 Credential Reader	By Div 28 (12V)		OT
1 Wiring Harness (frame)	QC-C3000P		MK
1 RX Motion Sensor	By Div 28 (12V)		SU

Notes:
Entry by valid input at reader or manual key. Free egress at all times.
LBM feature in electric strike to monitor opening status, shunted by RX motion sensor if required.
Coordinate with electrical and security contractors.

Set 8.0
Doors: (Storage Rooms) (1900N IT ROOM)
Description: Access Control Function x Door Closer

3 Hinge, Full Mortise	TA2714 NRP (outswing) / TA2714 (inswing)	US26D	MK
1 Storeroom Lock	10XG04 LL (w/ std cyl)	US26D	SA
1 Permanent Medeco KIL Cylinder	By Owner (installed by Contractor – coordinate keying with owner)	24	MC
1 Electric Strike w/ Latch Monitor	5200C-LBM (12V)	630	HS
1 Door Stop	441CU floor stop (Use Rixson 10-x36 overhead stop as req'd if floor stop is not feasible	US26D	RO
1 Door Closer	281 O / P10 as req'd	EN	SA
3 Silencer	608/609 as req'd		RO
1 Access Control Reader	By Div 28 (12V)		OT
1 Wiring Harness (frame)	QC-C3000P		MK
1 RX Motion Sensor	By Div 28 (12V)		SU
1 Power Supply	By Div 28 (12V)		OT

Notes:
Entry by valid input at reader or manual key. Free egress at all times.
LBM in electric strike to monitor opening status, shunted by RX motion sensor if required.
Coordinate with electrical and security contractors.

Set 9.0
Doors: 115 (Janitor)
Description: Access Control Function x Kickplate (Janitor Closet)

3 Hinge, Full Mortise	TA2714 NRP (outswing) / TA2714 (inswing)	US26D	MK
1 Storeroom Lock	10XG04 LL (w/ std cyl)	US26D	SA
1 Permanent Medeco KIL Cylinder	By Owner (installed by Contractor – coordinate keying with owner	24	MC
1 Electric Strike w/ Latch Monitor	5200C-LBM (12V)	630	HS
1 Kick Plate	K1050 10" HGT x CSK x BEV	US32D	RO
1 Door Stop	441CU floor stop (Use Rixson 10-x36 overhead stop as req'd if floor stop is not feasible	US26D	RO
3 Silencer	608/609 as req'd		RO
1 Wiring Harness (frame)	QC-C3000P		MK
1 Access Control Reader	By Div. 28 (12V)		OT
1 Power Supply (12V)	By Div 28		OT

Notes:
Entry by valid input at reader or manual key. Free egress at all times.
LBM in electric strike to monitor opening status if required.
Coordinate with electrical and security contractors.

Set 10.0
Doors: 114 (Phone Room)
Description: Privacy Function - Occupancy Indicator (Phone Room)

3 Hinge, Full Mortise	TA2714 4.5" x 4.5"	US26D	MK
1 Privacy Lock w/ Indicator	LB V20 8265 LNL	US26D	SA
1 Door Stop	441CU floor stop (Use Rixson 10-x36 overhead stop as req'd if floor stop is not feasible	US26D	RO
3 Silencers	608/609 as req'd		PE
2 Coat Hook	RM817	US26D	RO

Set 11.0
Doors:112 (Womens), 113 (Mens)
Description: Privacy Function w/ Occupancy Indicator x Door Closer (Restroom)

3 Hinge, Full Mortise	TA2314 4.5" x 4.5"	US26D	MK
1 Privacy Lock w/ Indicator	LB V20 8265 LNL	US26D	SA
1 Door Stop	441CU floor stop (Use Rixson 10-x36 overhead stop as req'd if floor stop is not feasible	US26D	RO
1 Door Closer	281 O / P10 as req'd	EN	SA
1 Kick Plate	K1050 10" HGT x CSK x BEV	US32D	RO
3 Silencer	608/609 as req'd		RO
2 Coat Hook	RM817	US26D	RO

Set 14.0
Doors: 105 (Meeting Room)
Description: DIRTT Doors

1 Concealed Overhead Slider Hardware	By DIRTT	US26D	DT
1 Back-to-Back Pull	30"/24" CTC	630	DT

PRAXIS3
100 Peachtree St NW
Suite 1450
Atlanta, GA 30303
404-875-4500 tel
www.praxis3.com

STATE OF GEORGIA
STUART M. ROMM
07/02/26
CERTIFICATE NO. 3457
REGISTERED ARCHITECT

Copyright (c) 2026 Praxis3, LLC

All reports, plans, specifications, computer files, field data, notes and other documents and instruments prepared by Praxis3 shall retain all common law, statutory and other reserved rights, including copyright thereto.

This drawing may not be reproduced in whole or in part without written permission of Praxis3. It is to be returned upon request. Scales as stated are valid on the original drawings.

Rev	Date	Comments
	07/02/2026	PERMIT SET

Client:
FIFTH THIRD BANK

Project Number: 26302
Project Name:
WATSON BLVD.

2711 WATSON BOULEVARD
WARNER ROBINS, GA 31093

Key Plan:

Sheet Title:
HARDWARE SCHEDULES

Sheet Number:
A-601

7/8/2026 2:38:49 PM