PCB Coating Procedure 2016_020

May 17th

2016

Method to coat PCB at the field or Repair Shop

[Applicable for All PCB's subject to excessive foreign particle deposition]

Method to coat PCB at the field or Repair Shop

1. Contents

This manual is described about the method to coat PCB that is covered with the lubricant (oil mist) at the field or the repair shop.

2. Procedure

Cleaning

- Clean the coating area of PCB with the spray type electric equipment cleaner *1.
- In case that there are connectors, contacts, check pins, and sockets near the area of cleaning, mask them with the tape *2 to prevent the dirty cleaning liquid from staining them.

(*1) Recommended electric equipment cleaner:

1. Hi-Shower Model DS-216 made by Sunhayato
2. Electric equipment cleaner PANDO 29D made by Three Bond.

(*2) 781DF made by Permacel, or equivalence.

Method of cleaning

- Remove the dust on the PCB.
- Spray the cleaner to the coating area of PCB to remove the lubricant (oil mist).
- In case that the coating area is too dirty, wipe the dirt with the cloth after spraying the cleaner.

Coating

- Pour the coating liquid (Hayacoat AY1000(G) or AY1002(G) made by Sunhayato) into the small vessel, and paint the coating area with the coating liquid by a brush.
- The work area should be well ventilated when coating, so as not to breathe in the vapor of the coating liquid, and wear a mask or a protector if necessary.

Method of coating

- In case that there are connectors, contacts, check pins, and sockets near the coating area, mask them with the tape, so as not to stain them with the coating liquid.
- Coating of the parts side of PCB.
    - The coating liquid should be painted evenly with a light touch.
    - The speed to paint the coating liquid should be less than 1cm/sec.
- Dry the coating liquid painted on PCB about an hour *3. (Temperature in the workshop.)
- Check the coating area is not sticky after drying.
- Coating of the soldering side of PCB. (See step 2)
- Dry the coating liquid painted on PCB about an hour. (See step 3)
- Strip the masking tape in case of taping at step 1.
- Do coating 2 times on the directed area to acquire the effect enough.

(*3) It takes 10 minutes to become not sticky, and an hour to dry completely.

3. Others

- The life of the coating liquid is 2 months after opening.
- Keep the coating liquid in cool storage with the can closed tightly after using.
- Pour a small quantity of coating liquid to use up in a day into the small vessel, and do not return the remained coating liquid to the can and waste it.