

glasstech, inc.

Service Bulletin

Customer Service Department

TELEPHONE: 419-661-9000 FAX: 419-661-9639

Glasstech SCR Heating Controllers

Reference 007

The Glasstech solid state SCR heating controllers (part numbers E-RRL4CSSAAA481 and E-RRL4CSSAAA482) used on your Glasstech system were originally fitted with two correctly rated 63 amp fast acting fuses in parallel. Due to instances of a high failure rate of these fuses, the SCR Controller manufacturer had previously advised Glasstech that these fuses could be replaced in pairs with 80 FE Fast Acting fuses without degrading the safety of the circuit. This information was passed on to you, the end-use customer, in Glasstech Service Bulletin Reference 004.

In spite of this replacement, an increasing number of SCR failures were experienced in addition to continuing fuse failures. Glasstech and the SCR Controller manufacturer have worked together to identify the root cause of this problem. The type of fuse initially selected for this application creates a thermal cycling and degradation of the fuse, and possibly, the SCR. Heat transferred from the hot end(s) of the existing style "FE" fuse can be extremely high in an overload condition. This is the reason that the fuses are failing after a limited number of thermal cycles. Since this is a thermal problem, Glasstech highly recommends that you assure that maximum cooling of the SCR panels is available. The filters and cooling fans in the panel doors should be kept clean, and maintained in top working order.

*A different style fuse has been identified, tested, and is now being produced in quantities. The new fuse is a Bussmann ceramic square body fuse rated at 65amps for both short circuit and overload conditions. The replacement fuse is a **Bussmann 170N3437**, UL approved for usage in the controller.*

Glasstech will provide at no charge to its customers, sufficient quantities of these new fuses to cover your original complement of SCR Controllers and information for their proper installation. We require that all of the existing fuses be changed immediately upon the receipt of the new style which we will be providing. Please return the original fuses to Glasstech after securing a Return Goods Authorization #(RGA).

If you have any questions on this or any other matters, please do not hesitate to contact Glasstech Customer Service at the numbers listed in this bulletin header.