

HURC - Hatchling Universal Robot Controller

Fall 2025 Hatchling Controller

Class Documentation.....	3
1 NetController Class Reference.....	3
2 Constructor & Destructor Documentation.....	3
2.1 NetController().....	3
3 Member Function Documentation.....	4
3.1 getJoy1X().....	4
3.2 getJoy1Y().....	4
3.3 getJoy1Z().....	4
3.4 getJoy2X().....	4
3.5 getJoy2Y().....	4
3.6 getJoy2Z().....	4
3.7 getA().....	4
3.8 getB().....	4
3.9 getX().....	4
3.10 getY().....	4
3.11 getLb().....	4
3.12 getRb().....	5
3.13 getLt().....	5
3.14 getRt().....	5
3.15 getDpad().....	5

Class Documentation

1 NetController Class Reference

Public Member Functions

- [NetController](#) (bool displayDebugMessage=false)
Creates a "network controller" - basically a receiver for your HURC. Make sure to call [controllerSetup\(\)](#) in your setup() function before using trying to get any inputs.
- void [controllerSetup](#) ()
sets up stuff related to the controller, put this in ur setup function
- float [getJoy1X](#) ()
returns the left joystick's x value
- float [getJoy1Y](#) ()
returns the left joystick's y value
- bool [getJoy1Z](#) ()
returns whether or not the left joystick is clicked down
- float [getJoy2X](#) ()
returns the right joystick's x value
- float [getJoy2Y](#) ()
returns the right joystick's y value
- bool [getJoy2Z](#) ()
returns whether or not the right joystick is clicked down
- bool [getA](#) ()
returns whether or not the A button is pressed down (Xbox layout)
- bool [getB](#) ()
returns whether or not the B button is pressed down (Xbox layout)
- bool [getX](#) ()
returns whether or not the X button is pressed down (Xbox layout)
- bool [getY](#) ()
returns whether or not the Y button is pressed down (Xbox layout)
- bool [getLb](#) ()
returns whether or not the left bumper is pressed down
- bool [getRb](#) ()
returns whether or not the right bumper is pressed down
- bool [getLt](#) ()
returns whether or not the left trigger is pressed down
- bool [getRt](#) ()
returns whether or not the right trigger is pressed down
- bool [getDpad](#) ()
returns whether or not the dpad button is pressed down

2 Constructor & Destructor Documentation

2.1 NetController()

```
NetController::NetController (  
    bool displayDebugMessage = false)
```

Creates a "network controller" - basically a receiver for your HURC. Make sure to call [controllerSetup\(\)](#) in your setup() function before using trying to get any inputs.

3 Member Function Documentation

3.1 getJoy1X()

```
float NetController::getJoy1X ()
```

returns a float of the left joystick's x value in the range [-1, 1]

3.2 getJoy1Y()

```
float NetController::getJoy1Y ()
```

returns a float of the left joystick's y value in the range [-1, 1]

3.3 getJoy1Z()

```
bool NetController::getJoy1Z ()
```

returns true when left joystick is held down, false otherwise

3.4 getJoy2X()

```
float NetController::getJoy2X ()
```

returns a float of the right joystick's x value in the range [-1, 1]

3.5 getJoy2Y()

```
float NetController::getJoy2Y ()
```

returns a float of the right joystick's y value in the range [-1, 1]

3.6 getJoy2Z()

```
bool NetController::getJoy2Z ()
```

returns true when right joystick is held down, false otherwise

3.7 getA()

```
bool NetController::getA ()
```

returns true when the A button is held down, false otherwise (Xbox layout)

3.8 getB()

```
bool NetController::getB ()
```

returns true when the B button is held down, false otherwise (Xbox layout)

3.9 getX()

```
bool NetController::getX ()
```

returns true when the X button is held down, false otherwise (Xbox layout)

3.10 getY()

```
bool NetController::getY ()
```

returns true when the Y button is held down, false otherwise (Xbox layout)

3.11 getLb()

```
bool NetController::getLb ()
```

returns whether or not the left bumper is held down, false otherwise

3.12 getRb()

`bool NetController::getRb ()`

returns whether or not the right bumper is held down, false otherwise

3.13 getLt()

`bool NetController::getLt ()`

returns whether or not the left trigger is held down, false otherwise

3.14 getRt()

`bool NetController::getRt ()`

returns whether or not the right trigger is held down, false otherwise

3.15 getDpad()

`bool NetController::getDpad ()`

returns whether or not the dpad button is held down, false otherwise