gator legio

_travelers guide
_for sawing through the swamp

2	3	6
switches · 3 ways	cv inputs	hp

[pitch] press [pitch] hold › then noon = 12 o'clock tags = the panel drawing

supersaw oscillator · detune, manis-style saw mod, stereo spread and phase-mod inputs

← back to the legio starsystem

= hold

01 what it is

ga_01

supersaw	a stack of detuned saws
saw mod	manis-style shaping, a bit like hard sync
stereo	spread across L and R
in L R	pm · audio in · L feeds R if alone
out L R	stereo out, up to 16 V peak to peak
platform	a legio firmware · other firmwares

02 pitch

ga_02 · enc

[enc] turn	fine tune
[enc] press + turn	coarse tune
enc jack	pitch · –2 to +5 V

10 first flight

ga_10 · the manual's tutorial

1. out through a stereo vca + envelope
2. a pitch sequence into enc
3. gates into the envelope
4. raise 1 and 2
5. random gates into trig

03 detune · saw mod

ga_03 · knobs 1 + 2

1 [detune]	spreads the saws apart
2 [saw mod]	timbre shift, sync-like

04 saw count · stereoness

ga_04 · s1 · s2 · top → bottom

s1 saw count	how many saws
s2 stereoness	how wide the spread
note	the manual doesn't list the counts

__fig.01 : signal path

in → out



as the manual describes it

05 jacks

ga_05 · trig · cv · audio

trig 8va	up an octave while the gate is high
in pm L R	phase-mod inputs · L feeds R if alone
out L R	up to 16 V peak to peak
cv	pitch –2 to +5 V · detune + saw mod 0 – 5 V

__fig.02 : waveforms

shape · mod



08 patch ideas

ga_08 · the manual

lead — any
out to a stereo vca, an envelope (ampla legio works) on gate

octave jumps — any
gate sequence or random gates into 8va

pm movement — any
another oscillator, or a second gator, into pm

__fig.03 : the panel

numbers match the legend



- enc **pitch** · fine tune
- 1 **detune** · spreads the saws apart
- 2 **saw mod** · timbre shift, sync-like
- s1 **saw count** · up · mid · down
- s2 **stereoness** · up · mid · down
- trig **8va** · up an octave while the gate is high
- cv **pitch** · **1** · **2** · pitch –2…+5 V · others …
- in **pm L / R** · L feeds R if alone
- out **out L / R** · stereo out

09 specs

ga_09

size	6 hp · 1.5 in deep
power	140 mA +12 V · 22 mA –12 V
cv in	0 – 5 V · pitch –2 to +5 V
trig	rising edge near +1.6 V
boot LEDs	yellow / yellow

design homage to the house of x / powers of x data pages — designed by tom muller with jonathan hickman · panel drawing after the noise engineering legio overlay template
not affiliated with noise engineering or marvel

conceived by mellotom · legio-gator-navigator ... 00.10_01
created with claude