# yesterversio

## _travelers guide
## _for echoing yesterday

| 3 | 95% | 7 |
|---|---|---|
| taps | max regen | knobs · 2 switches · tap |

[ tap ] press  [ tap ] hold  › then  noon = 12 o'clock  numbers = the numbered panel

three-tap stereo delay · fold + pitch shift · tap tempo · a free firmware for any versio

← back to the versio starsystem

yellow = hold

## 01 what it is

yv_01

| | |
|---|---|
| a delay | three taps, stereo, with wavefolding and pitch shift · clock, tap tempo, triplets and dotted |
| in 1 in 2 | stereo in |
| out 1 out 2 | stereo out |
| every knob | an offset added to its cv jack, 0 – 5 V |
| swap in | free on any versio · how to swap |

## 02 time · regen

yv_02 · knobs 6 + 5 · fig.01

| | |
|---|---|
| 6 [ time ] | internal clock rate when nothing is tapped or patched |
| clocked | left of noon divides · right multiplies · with the abc rhythm |
| 5 [ regen ] | feedback 0 to about 95% · stays calm at most settings |
| always | at least three repeats · it's three taps |

## _fig.01 : time when clocked

knob 6 · with abc




## 10 first flight

yv_10 · the manual's first patch

1. sound into in 1 · out 1 out 2 to your mixer
2. 7 [ fold ] min · everything else at noon
3. set spacing with 6 [ time ], count with 5 [ regen ]
4. place the taps with 2 [ pan ]
5. 4 [ chorus ] left for harmonies, right for chorus
6. shape with 3 [ tone ] and fold · tap [ tap ] to sync

## 03 pan · chorus · tone

yv_03 · knobs 2 · 4 · 3

| | |
|---|---|
| 2 [ pan ] | where the three taps sit in the stereo field |
| 4 [ chorus ] | left of noon fixed pitch shift (harmonies) · right lfo-wobbled (chorus) |
| 3 [ tone ] | left of noon lowpass · right highpass |

## 04 fold · blend

yv_04 · knobs 7 + 1 · fig.02

| | |
|---|---|
| 7 [ fold ] | on the delay output · saturation, then folding, then doom |
| past 3:00 | sub-octaves · great on high sounds |
| 1 [ blend ] | dry left · both at noon · only echoes right |

## _fig.02 : fold

knob 7 · three zones




## _fig.04 : signal path

as far as the manual says




fold sits on the delay output · 5 regen feeds the taps back

## 05 switches

yv_05 · abc · xyz

| | |
|---|---|
| abc left | [ even ] straight time |
| abc mid | [ triplet ] triplet rhythm |
| abc right | [ dotted ] dotted rhythm |
| xyz left | [ fade ] smooth time changes · no repitch |
| xyz mid | [ octave ] rate-limited · octave harmonies |
| xyz right | [ jump ] instant · glitchy artifacts |

## 07 tap · holds

yv_07 · fsu = tap

| | |
|---|---|
| [ tap ] | tap tempo |
| fsu jack | clock in · above 2 V |
| [ tap ] few s | forget tap + clock · internal clock · LEDs flash blue |
| [ tap ] longer | clear the feedback · LEDs flash white |
| patched clock | unpatch it, then hold until blue |
| boot | yellow · magenta · magenta · magenta = yester is loaded |

## 08 two patches

yv_08 · from the manual

**first patch** — any

sound into in 1 (+ in 2) · fold min, the rest at noon · time + regen set spacing and count · pan places them · chorus left for harmony, right for smear · tone + fold for colour

**synced delay** — even / triplet / dotted

a clock into tap · time + abc set the rhythm

## _fig.06 : what the LEDs say

boot + holds

| | | |
|---|---|---|
| boot | yellow magenta magenta magenta | yester is loaded |
| hold tap | blue blue blue blue | tempo forgotten |
| hold longer | off off off off | feedback cleared |

## _fig.03 : the panel

numbers match the legend




1. **blend** · dry ↔ echoes
2. **pan** · tap placement
3. **tone** · lp ← · → hp
4. **chorus** · shift ← · → wobble
5. **regen** · up to ~95%
6. **time** · rate · or ratio
7. **fold** · sat · fold · doom

abc **rhythm** · even · triplet · dotted
xyz **changes** · fade · octave · jump
fsu **tap** · tap · clock · holds
in **in 1 / 2** · stereo in
out **out 1 / 2** · stereo out

## 09 specs

yv_09

| | |
|---|---|
| cv in | 0 – 5 V |
| tap gate | above 2 V |
| audio in | clips near 16 V peak to peak |
| size | 10 hp · 1.5 in deep |
| power | version a 70 mA +12 V · 70 mA –12 V · version b 125 mA · 10 mA · no 5 V |

design homage to the house of x / powers of x data pages — designed by tom muller with jonathan hickman · panel art: noise engineering
not affiliated with noise engineering, mathias kettner or marvel