

NEXCORT iQ · CAMPUS · VENUE · TRANSIT

NFC Tag Installation Guide

Step-by-step programming and mounting for Campus, Venue, and Transit — Field app only, no third-party NFC writers.

Legal entity: Apps on Demand LLC · Marketing: www.nexcortiq.us · Ops console: app.rapidcortex.us · (404) 520-1747 · jeff@nexcortiq.us

An NFC tag is a coin-sized sticker. Tap a phone → browser opens the NexCort iQ safety report for that exact zone. No camera, no app download, and no typing for the person reporting.

NOTE — NFC and QR on the same sign point to the same location. NFC is faster on newer phones; QR covers every camera.

WHO — Create / download / deactivate codes: Campus Admin & Supervisor; Venue Admin, Supervisor & Operator; Transit Admin & Supervisor; RC platform operators (rcadmin / rcitadmin / rcsuperadmin). **PSAP roles are excluded** — dispatcher, supervisor, agencyadmin, and agencyit do not manage campus/venue/transit QR & NFC. Program NFC tags in the Field app: the create roles above, plus Campus Security, Venue Security, and Transit Security for existing codes.

Trade-show booth signs

Do **not** create a location code for a marketing booth. Use Trade show signs → Home (www.nexcortiq.us) or Demo. A location tag on a booth opens a live tip form.

WARNING — Always program tags inside the NexCort iQ Field app. Do not use NFC Tools or paste URLs manually.

What you need

Item	Details	Where
Web login	Campus/Venue/Transit role that can create codes	app.rapidcortex.us
Field app	Writes NFC; verifies QR	App Store / Google Play — NexCort iQ / NexiQ Field
NTAG213 stickers	Pack of 100 · white	Amazon — “NTAG213 NFC stickers”
NFC phone	iPhone 7+ · most Android since ~2014	Installer device
Marker + alcohol wipes	Label backs; clean mount surface	Office / pharmacy

1 — Create the location in the browser

- Sign in at app.rapidcortex.us → open your Campus / Venue / Transit console → **QR Codes**.
- Create a new code: name (e.g. McKinley Hall — 3rd Floor), zone, report type, vertical. Save.
- Leave the URL in NexCort — the Field app writes it. Do not copy into another writer.
- One code per physical sign. Free Community Connect supports a single zone; paid Multi-zone expands coverage.

2 — Program the tag in the Field app

- Open Field app → QR & NFC → the location → **Program NFC Tag**.
- Hold NTAG213 still (~2 seconds) until success. Use Write Another for spare tags at the same location.
- If write fails, slide the tag slowly to find the antenna; keep NFC enabled.

3 — Test before attaching

- Tap with a locked-awake phone (screen on). Reporter needs no app.
- Confirm the correct vertical + location report form opens.
- Optional: Scan QR Code in the Field app to verify the printed PNG.
- In the web console, confirm the NFC tap / scan count incremented.

4 — Attach and mount

- Label the tag back (e.g. MH-3F) before peeling.
- Clean surface with isopropyl; dry 30 seconds.
- Center on the back of the sign (or face/corner if metal — see table). Press 10–15 seconds.
- Mount the sign; final tap-test through the front.

Sign material compatibility

Material	NFC?	Notes
Acrylic / PVC / plastic / wood / glass	Yes	Best results; glass — stick on inner surface.
Aluminum face	Partial	Metal blocks NFC. Mount tag on face corner or use a spacer block.
Solid metal back	No	Use non-metallic plate between tag and metal, or mount nearby.

5 — Troubleshooting

Problem	Solution
Phone does not detect tag	Enable NFC; move across antenna; try another NTAG213.
Wrong page opens	Rewrite from Field app. Check location vs trade-show Home/Demo.
Stopped after mounting	Too close to metal — relocate or use on-metal NFC tag.
Tap count not updating	Count increments when the form loads — check network at the sign.
Correct form, wrong name	Update zone/name in dashboard when the product allows; else create new code and deactivate old.
Write failed	NFC on; hold still; NTAG213; stay in Field app.

6 — Quick reference card

Supplies	Steps
NTAG213 · NFC phone · Field app · admin login · marker · wipes	1) Create location at app.rapidcortex.us → QR Codes 2) Field app → location → Program NFC Tag 3) Hold tag until success · tap-test 4) Optional Scan QR · label · clean · stick · mount · final tap

Need help? jeff@nexcortiq.us · www.nexcortiq.us