


Streaming from the Mevo app

This guide walks through pointing a Mevo camera at the RTMP relay so the stream shows up on the site and is forwarded to YouTube + GameChanger.



What you need

- A Mevo camera + the **Mevo** app (iOS/Android — the basic single-camera app, not *Mevo Multicam*), signed in with a **Mevo Plus / Pro** account — *Custom RTMP* is a paid-tier feature.
- The relay's public IP or hostname (the same server that runs `docker compose up` from this folder). Default RTMP port is **1935**.
- <https://streamthehawks.ca/relay> open on a phone or laptop so you can confirm the stream is live.

One-time: set up a Custom RTMP destination in Mevo

1. Open the **Mevo** app and tap your camera to connect.
2. Tap the **broadcast** button (the "Live" / play-on-air icon, usually bottom-center of the camera preview).
3. Tap **Streaming Destination** (or the destination icon showing the current target — Facebook/YouTube logo, etc.).
4. Tap **Custom RTMP** in the destination list. If you don't see it, tap **+ Add / More** first.
5. Fill in:

Field	Value
Name	e.g. Hawk relay
RTMP URL	rtmp://<DROPLET_IP>:1935/live
Stream Key	anything non-empty, e.g. mevo
Username	leave blank
Password	leave blank

The relay's `application live { ... }` block (see `nginx.conf.template`) accepts any stream key on the `/live` path, so the key value itself doesn't matter — pick something memorable.

6. Tap **Save**, then make sure the new destination is **selected** as the active streaming target.

Recommended encoding settings

Set these from the broadcast sheet → **Settings** (gear icon) before going live. The relay just forwards bytes, so the bitrate Mevo sends is what YouTube and GameChanger will receive.

Setting	Recommended	Notes
Resolution	1080p	Drop to 720p if you're on weak LTE.
Frame rate	30 fps	60 fps doubles bitrate for little benefit.
Bitrate	4–6 Mbps	YouTube's 1080p30 sweet spot.
Keyframe	2 s	Required by YouTube; GameChanger is happy.
Audio	AAC, 128 kbps	Mevo default — leave alone.

If the **Source** bandwidth on `/relay` keeps dipping, the upload link is the bottleneck — drop to 720p / 3 Mbps.

Going live

1. In Mevo, confirm **Custom RTMP** → **Hawk relay** is the selected streaming destination (not Facebook / YouTube direct — the relay is what fans out, so a direct destination would double-broadcast).
2. Tap the big red **Go Live** button.
3. Open `https://streamthehawks.ca/relay` on a phone:
 - **Source** dot should turn green within ~5 seconds and show "Mevo".
 - **YouTube** and **GameChanger** dots should follow once the relay opens its push connections (usually 2–5 s later).
 - The big banner flips to **LIVE** with the incoming bitrate.
4. `https://streamthehawks.ca` auto-detects the YouTube live broadcast and embeds it once YouTube reports the stream as active (typically 10–30 s after the relay starts pushing).

Stopping the stream

Tap **End broadcast** in the Mevo app. Within a few seconds:

- `/relay` flips back to **OFFLINE**.
- YouTube ends the live broadcast (and may auto-publish a VOD depending on your YouTube Studio settings).

Troubleshooting

Symptom on <code>/relay</code>	Likely cause / fix
Source: No input after Go Live	Wrong RTMP URL in Mevo, or port 1935 blocked. Check <code><DROPLET_IP></code> and firewall.
Source green, YouTube red	YouTube stream key in <code>rtmp-relay/.env</code> (<code>DEST1</code>) is wrong/expired. Rotate it.
Source green, GameChanger red	Game not started in GameChanger, or <code>DEST2</code> URL/key stale. Re-grab from GC app.
Bitrate flapping / "Source" pulsing offline	Weak uplink. Lower Mevo bitrate, or move closer to the hotspot/router.
<code>/relay</code> shows "Relay server not configured"	Set the stats URL once: <code>http://<DROPLET_IP>:8080/stat</code> in the Relay server URL panel.
Page shows OFFLINE but Mevo says live	The stats-pusher container probably crashed. <code>docker compose ps</code> on the relay host.

Rotating the YouTube key

YouTube keys can be regenerated from **YouTube Studio** → **Go Live** → **Stream settings**. After rotating, update `DEST1` in `rtmp-relay/.env` and restart the relay:

```
docker compose up -d --force-recreate rtmp-relay
```

GameChanger keys live in the GameChanger app under **Streaming** — same flow, update `DEST2` and recreate.

Appendix — Quick setup card for a new phone

Hand this page to whoever's running camera. Assumes the droplet is already configured (someone else owns the YouTube + GameChanger keys in `.env`).

1. Install + sign in

- App: **Mevo** (iOS / Android — the basic single-camera app, *not* Mevo Multicam)
- Sign in with the team's Mevo account (must be **Mevo Plus / Pro** — Custom RTMP is a paid feature)
- Pair the camera once over Bluetooth, then connect via the camera's Wi-Fi or a shared hotspot

2. Add the Custom RTMP destination

Tap the **broadcast** button → **Streaming Destination** → **Custom RTMP** → fill in:

Field	Value
Name	Hawk relay
RTMP URL	rtmp://<DROPLET_IP>:1935/live
Stream Key	mevo <i>(any non-empty string)</i>
Username	<i>(blank)</i>
Password	<i>(blank)</i>

Save, then make sure **Hawk relay** is the selected destination.

<DROPLET_IP> is the same IP shown on <https://streamthehawks.ca/relay> under **Relay server URL** — change the port from 8080 to 1935.

3. Encoding settings (gear icon on the broadcast sheet)

Setting	Value
Resolution	1080p <i>(720p on weak LTE)</i>
Frame rate	30 fps
Bitrate	4–6 Mbps
Keyframe	2 s
Audio	AAC, 128 kbps <i>(Mevo default — leave it)</i>

4. Don't pick a second destination

The basic Mevo app only streams to one destination at a time, so this is mostly automatic — just make sure the selected destination is **Hawk relay** and not Facebook / YouTube direct. The relay handles the fan-out to YouTube and GameChanger; streaming direct *as well* would double-broadcast and burn upload bandwidth.

5. Go-live checklist

1. Tap **Go Live** in Mevo.
2. Open <https://streamthehawks.ca/relay> on a laptop or second phone.
3. Within ~5 s all three dots should be green:
 - **Source** → Mevo connected
 - **YouTube** → relay pushing to YT
 - **GameChanger** → relay pushing to GC
4. In **YouTube Studio** → **Live Control Room**, click the blue **GO LIVE** button once the preview shows your feed.

5. <https://streamthehawks.ca> auto-embeds the YouTube live broadcast within ~30 s.

If any dot stays red, see the **Troubleshooting** table earlier in this doc.