

Set-Up Instructions | PUBLIC
SAP S/4HANA Cloud Public Edition
2026-06-16

Setting Up *Basic Credit Management* (BD6)

© 2026 SAP SE or an SAP affiliate company. All rights reserved.

Content

1 Purpose. 3

2 Prerequisites. 4

3 Establish Communication in Outbound System. 5

3.1 Create Your Communication System and Outbound User. 5

3.2 Create the Communication Arrangement for UI Integration (SAP_COM_0B25). 6

3.3 Setup Recipient for AIF to Monitor Messages. 7

4 Establish Communication in Inbound System. 8

4.1 Create Your Communication System and Inbound User. 8

4.2 Create the Communication Arrangement for UI Integration (SAP_COM_0173). 9

4.3 Setup Recipient for AIF to Monitor Messages. 10

1 Purpose

This document describes the configuration steps necessary to set up communication of the SAP S/4HANA Cloud Public Edition system to another SAP S/4HANA Cloud Public Edition system for Inbound API SAP_COM_0173 and Outbound API SAP_COM_0B25. Before you start, the individual systems being integrated must already be set up, and the connection between the systems is established and working.

> **Note**
>
> For more information, see the Administration Guide for Credit Management.

The document is intended only as a guide to help you prepare and apply the steps required for successful integration.

2 Prerequisites

To do the configuration in SAP S/4HANA Cloud Public Edition, you need to have the following business catalogs assigned to you:

- Communication Management (SAP_CORE_BC_COM) - Provides access to the following apps: Maintain Communication Users, Communication Arrangements, and Communication Systems
- Enterprise Event Enablement (SAP_CORE_BC_XBE) - Provides access to the following app: Enterprise Event Enablement - Configure Channel Binding
- Communication Management – Message Monitoring Configuration (SAP_CA_BC_COM_CONF_PC): To assign recipients to users

For example, use the business role (Administrator).

3 Establish Communication in Outbound System

In this section, you establish communication within the outbound system so as to transfer data related to SAP Credit Management.

Dedicated communication scenarios are available for Information from other components in other SAP S/4HANA systems: Financial Accounting, Sales, Service, and Delivery.

3.1 Create Your Communication System and Outbound User

Purpose

In this activity, you create a communication system and outbound user in your SAP S/4HANA Cloud system.

Prerequisite

You need the target host ID from your SAP Cloud System. To find this, follow the instructions at Finding Your Cloud Launchpad URL .

Procedure

1. Log on to the SAP Fiori Launchpad as an Administrator.
2. Open *Communication Systems*.
3. On the *Communication Systems* screen, choose *New*.
4. In the *New Communication System* dialog box make the following entries and choose *Create*:
   System ID: **<system ID>**
   System Name: **<system name>**
5. In the *General* area, enter:
   Host Name: **<host name from the activity in Prerequisite above>**
6. Navigate to the *Users for Outbound Communication* section and choose +(*Add*).
7. On the *New Outbound Communication User* dialog box, enter the following, then choose *New User*.
   Authentication Method: **SSL Client Certificate**
   User Name/Client ID: **CREDIT_TESTER/ < Client ID >**
8. In the *New Data* area, enter:
   User Name: **CREDIT_TESTER**

Description: **CREDIT_TESTER**

9. In the *Certificate* area, choose the *Upload* button.
10. In the *Upload Certificate* dialog box, choose the *Certificate* drop down menu and upload your file.
11. Choose *Create*.
12. In the *New Outbound Communication User* dialog box, choose *OK*.
13. Make a note of the ID of the outbound communication system. You need the user ID to complete the following task.
14. Choose *Save* to save the communication system.

3.2 Create the Communication Arrangement for UI Integration (SAP_COM_0B25)

Purpose

In this activity, you will create communication arrangements for UI integration.

Prerequisite

You created your communication system.

Procedure

1. Log on to the SAP Fiori Launchpad as an Administrator.
2. Open *Communication Arrangements*.
3. On the *Maintain Communication Users* view, choose *New*.
4. Select the Scenario ID: *SAP_COM_0B25 (Sales and Finance to Credit Management SOAP Outbound Integration).*
5. Choose *Create*.
6. In the *Common Data* section, enter the *Communication System* you created in the prior step.
7. On the next screen, select the communications system from the previous step and verify that the user has been entered automatically.
8. Select *Use WSRM*, and make sure the *Path* is correctly maintained in all the *Outbound Services*.
9. Choose *Save*.

3.3 Setup Recipient for AIF to Monitor Messages

Purpose

In this activity, you assign recipients to users as a prerequisite to monitor messages transferred by this service.

Procedure

1. Log on to the SAP Fiori Launchpad as an Administrator.
2. Open *Assign Recipients to Users*.
3. On the *Assign Recipients to Users* view, choose *Assign*.
4. On the next screen, enter the following entries for respective services:

Namespace	Recipient Name	Message Type	Over-view	Technical User
/FINCR	*PAYBEHAVIOR_OUT_RECIEVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*CREDIT_CHECK_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*COMMITMENT_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*UPDATE_DCD_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*CR_ACCOUNT_READ_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select

5. Choose *Assign*.

4 Establish Communication in Inbound System

In this section, you establish communication within the inbound system to transfer data related to SAP Credit Management.

Dedicated communication scenarios are available for Information from other components in other SAP S/4HANAsystems: Financial Accounting, Sales, Service, and Delivery.

4.1 Create Your Communication System and Inbound User

Purpose

In this activity, you create the communication system and inbound user in your SAP S/4HANA Cloud system.

Prerequisite

You need the target host ID from your SAP S/4HANA system. To find this, follow the instructions at Finding Your Cloud Launchpad URL .

Procedure

1. Log on to the SAP Fiori launchpad as an Administrator.
2. Open *Communication Systems*.
3. On the *Communication Systems* screen, choose *New*.
4. Make the following entries and choose *Create*:
   System ID: **`<system ID>`**
   System Name: **`<system name>`**
5. Make the following entries:
   Host Name: **`<host name from the activity in Prerequisite above>`**
6. Navigate to the *Users for Inbound Communication* section and choose +(*Add*).
7. In the *New Inbound Communication User* dialog box, enter:
   Authentication Method: **`SSL Client Certificate`**

User Name/Client ID: **`CREDIT_TESTER/ < Client ID >`** then choose *New User*.

8. In the *Create Communication User* view, make the following entries in the *User Data* area and choose *Create*:
   User Name: **`CREDIT_TESTER`**
   Description: **`CREDIT_TESTER`**
9. In the *Certificate* area, choose the *Upload* button.
   In the *Upload Certificate* dialog box, choose the *Certificate* drop down menu and upload your file.
10. Choose *Create*.
11. In the *New Inbound Communication User* dialog box, choose *OK*.
12. Make a note of the user ID of the inbound communication user. You need the user ID to complete the following task.
13. Choose *Save* to save the communication system.
14. In the *New Inbound Communication User* dialog box, choose *OK*.
15. Make a note of the ID of the inbound communication system. You need the communication system ID to complete the following task.
16. Choose *Save* to save the communication system.

4.2 Create the Communication Arrangement for UI Integration (SAP_COM_0173)

Purpose

In this activity, you create communication arrangements for UI integration.

Prerequisite

You created your communication system.

Procedure

1. Log on to the SAP Fiori Launchpad as an Administrator.
2. Open *Communication Arrangements*.
3. On the *Communications Arrangements* view, choose *New*.
4. Select the scenario *SAP_COM_0173* (*SAP S/4HANA Cloud Private Edition Cloud for Credit Integration - UI Integration*).
5. Choose *Create*.
6. In the *Common Data* section, enter the *Communication System* you created in the prior step.

7. On the next screen, select the communications system from the previous step and verify that the user has been entered automatically.
8. Choose *Save*.

4.3 Setup Recipient for AIF to Monitor Messages

Purpose

In this activity, you assign recipients to users as a prerequisite to monitor messages transferred by this service.

Procedure

1. Log on to the SAP Fiori Launchpad as an Administrator.
2. Open *Assign Recipients to Users*.
3. On the *Assign Recipients to Users* view, choose *Assign*.
4. On the next screen, enter the following entries for respective services:

Namespace	Recipient Name	Message Type	Over-view	Technical User
/FINCR	*PAYBEHAVIOR_OUT_RECIEVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*CREDIT_CHECK_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*COMMITMENT_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*UPDATE_DCD_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select
/FINCR	*CR_ACCOUNT_READ_OUT_RECEIVERS*	**Application Error or Technical Error**	Select	Select

5. Choose *Assign*.

Important Disclaimers and Legal Information

Hyperlinks

Some links are classified by an icon and/or a mouseover text. These links provide additional information.
About the icons:

- Links with the icon  : You are entering a Web site that is not hosted by SAP. By using such links, you agree (unless expressly stated otherwise in your agreements with SAP) to this:
  - The content of the linked-to site is not SAP documentation. You may not infer any product claims against SAP based on this information.
  - SAP does not agree or disagree with the content on the linked-to site, nor does SAP warrant the availability and correctness. SAP shall not be liable for any damages caused by the use of such content unless damages have been caused by SAP's gross negligence or willful misconduct.
- Links with the icon  : You are leaving the documentation for that particular SAP product or service and are entering an SAP-hosted Web site. By using such links, you agree that (unless expressly stated otherwise in your agreements with SAP) you may not infer any product claims against SAP based on this information.

Videos Hosted on External Platforms

Some videos may point to third-party video hosting platforms. SAP cannot guarantee the future availability of videos stored on these platforms. Furthermore, any advertisements or other content hosted on these platforms (for example, suggested videos or by navigating to other videos hosted on the same site), are not within the control or responsibility of SAP.

Beta and Other Experimental Features

Experimental features are not part of the officially delivered scope that SAP guarantees for future releases. This means that experimental features may be changed by SAP at any time for any reason without notice. Experimental features are not for productive use. You may not demonstrate, test, examine, evaluate or otherwise use the experimental features in a live operating environment or with data that has not been sufficiently backed up.
The purpose of experimental features is to get feedback early on, allowing customers and partners to influence the future product accordingly. By providing your feedback (e.g. in the SAP Community), you accept that intellectual property rights of the contributions or derivative works shall remain the exclusive property of SAP.

Example Code

Any software coding and/or code snippets are examples. They are not for productive use. The example code is only intended to better explain and visualize the syntax and phrasing rules. SAP does not warrant the correctness and completeness of the example code. SAP shall not be liable for errors or damages caused by the use of example code unless damages have been caused by SAP's gross negligence or willful misconduct.

Bias-Free Language

SAP supports a culture of diversity and inclusion. Whenever possible, we use unbiased language in our documentation to refer to people of all cultures, ethnicities, genders, and abilities.

www.sap.com/contactsap

© 2026 SAP SE or an SAP affiliate company. All rights reserved.

No part of this publication may be reproduced or transmitted in any form or for any purpose without the express permission of SAP SE or an SAP affiliate company. The information contained herein may be changed without prior notice.

Some software products marketed by SAP SE and its distributors contain proprietary software components of other software vendors. National product specifications may vary.

These materials are provided by SAP SE or an SAP affiliate company for informational purposes only, without representation or warranty of any kind, and SAP or its affiliated companies shall not be liable for errors or omissions with respect to the materials. The only warranties for SAP or SAP affiliate company products and services are those that are set forth in the express warranty statements accompanying such products and services, if any. Nothing herein should be construed as constituting an additional warranty.

SAP and other SAP products and services mentioned herein as well as their respective logos are trademarks or registered trademarks of SAP SE (or an SAP affiliate company) in Germany and other countries. All other product and service names mentioned are the trademarks of their respective companies.

Please see https://www.sap.com/about/legal/trademark.html for additional trademark information and notices.

