

Planned Preventive Maintenance (PPM) Schedule

(Frequency: W = Weekly, M = Monthly, Q = Quarterly, SA = Semi-Annually, A = Annually)

Component	Task Description	Frequency	Responsible
VizSens pH (Analog)	Rinse sensor with distilled water	W	Operator
	Clean sensor and soak in buffer (pH 4) if fouled	M	Technician
	Recalibrate with standard buffers	M	Technician
	Replace sensor if drift persists	A	Maintenance
	Verify storage condition (if idle)	W	Operator
VizSens ODO	Inspect membrane condition and clean gently	W	Operator
	Air calibration in saturated air	M	Technician
	Replace membrane cap	A	Technician
	Cross-check reading with reference meter	Q	Technician
VizSens SS Sensor	Inspect for debris or fouling	W	Operator
	Enable/check auto-cleaning cycle	W	Operator
	Manual cleaning (remove sludge, sediment)	M	Technician
	Lab sample comparison and recalibration	Q	QA/Tech
Viz Eco Duo / Multi	Check power & output signals (4-20 mA, RS485)	M	Technician
	Clean screen, buttons	M	Operator
	Inspect housing & tighten wiring	Q	Technician
	Backup data from SD card	Q	Supervisor
	Firmware update if available	A	OEM/Tech

Component	Task Description	Frequency	Responsible
FRP Mounting Panel	Inspect for physical damage, cracks	SA	Maintenance
	Tighten bolts and supports	Q	Technician
	Clean panel surface	M	Operator
SS Flow-through Chamber (EQMS)	Flush with clean water	W	Operator
	Clean with mild acid (descaling)	M	Technician
	Check for flow blockage or leaks	Q	Technician
	Inspect seals, fittings	SA	Maintenance