

1.5T Coil Compatibility

				Platform Compatibility							Notes / Application Compatibility	# of elements	# of channels
Catalog	GE P/N on Label	Coil Description	Supplier	Connector Type	EXCITE II	HDe	HD	HDxt	MR450	MR450w			
Head and NV	-	-	-	-	-	-	-	-	-	-	-	-	-
M3335LG	2416329	Head Neck and Spine (forward production systems)	GE Coils	2 HD (1 16 ch and 1 8 ch)	no	no	no	yes - forward production only	no	no	Mcat now active (formally F7000MR). Compatible with 16 ch systems only. Asset, Bravo, Propeller. T2 Map available.	29	16
M3335LH	2416329	Head Neck and Spine (upgrade systems)	GE Coils	2 HD and 1 Legacy (Bendix)	no	no	no	yes-upgrades only	no	no	Mcat now active (formally F7001MR). Compatible with 16 ch systems only. Asset, Bravo, Propeller. T2 Map available.	29	16
M7000AN	2416329	HD Head Neck and Spine (DV systems)	GE Coils	P-connector	no	no	no	no	yes	yes	Coil is similar to M3335LG, difference is that this coil has P-connector. Asset, Bravo, Propeller.	29	16
M3087JJ	5117092-2	HD 8 ch NV	Medrad	HD	no	yes	yes	yes	Yes, Hypertronix connector	yes	Asset, Propeller, TRICKS. T2 Map available.	12	8
M3335M	5147135-2	HD 8 ch NV Array	Invivo	HD	no	yes	no	yes	Yes, Hypertronix connector	yes	Use Medrad NV (M3087JJ or E8800JN) on CRM, Do not use Invivo NV. Asset, Propeller. T2 Map available. Not compatible on reverse-ramped magnets.		
M3335SN	5145566-2	HD 4 ch NV Array	Invivo	HD	no	yes	no	no	no	no	Propeller		4
M3087JB	2317115-2	8CH NV	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Use Medrad NV (E8800JN) on CRM, Do not use Invivo NV. Asset, Propeller. T2 Map available. Not compatible on reverse-ramped magnets.		
E8800JN	#N/A (E-cat coils do not have GE P/N's)	8CH NV	Medrad	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Use Medrad NV (E8800JN) on CRM, Do not use Invivo NV. Asset, Propeller, TRICKS. T2 Map available.		
M1087NB	2293668-2	4CH NV	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no			4
M1087NC	2330440-2	4CH NV	Medrad	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no			
M3335LZ	5146634-2	HD 8 ch HiRes Brain	Invivo	HD	no	no	no	yes	Yes, Hypertronix connector	no	Asset, Bravo, Propeller. T2 Map available.		
M3087JA	2317112-2	8CH Brain	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Asset, Bravo, Propeller. T2 Map available.		
Spine	-	-	-	-	-	-	-	-	-	-	-	-	-
M3335MA	2415375	HD 8 ch CTL Array	GE Coils	HD	no	yes	no	yes	Yes, Hypertronix connector	yes	TRICKS. T2 Map available. Same coil ID as M3335TC.	12	8
M3335SS	2415369	HD 4 ch CTL	GE Coils	HD	no	yes	no	no	no	no	T2 Map available	12	4
M3087JC	2377426-2	8 ch CTL	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	T2 Map available	12	8

Catalog	GE P/N on Label	Coil Description	Supplier	Connector Type	EXCITE II	HDe	HD	HDxt	MR450	MR450w	Notes / Application Compatibility	# of elements	# of channels
M1087SP	2225545-6	4 ch CTL	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	T2 Map available	12	4
M3335TC	5269130	8 ch CTL	GE Coils Bangalore	HD	no	yes	no	yes	Yes, Hypertronix connector	yes	Same coil ID as M3335MA		
M3335TD	5267681	4 ch CTL	GE Coils	HD	no	yes	no	no	no				
M3335TA	2377426-2	8 ch CTL	GE Coils Bangalore	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no		Same coil ID as M3087JC		
M3335TB	5267924	4 ch CTL	GE Coils Bangalore	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Same coil ID as M1087SP		
Extermity	-	-	-	-	-	-	-	-	-	-	-	-	-
M3087JF	5114356-2	HD 8CH T/R Knee	Invivo	HD	no	yes	yes	yes	Yes, Hypertronix connector	yes	Asset. T2 Map validated.	8	8
M3335ME	5147225-2	HD Quad Extremity (Knee/Foot)	Invivo	HD	no	yes	no	yes	Yes, Hypertronix connector	yes	T2 Map validated		
M1085NA	2383613	Quad Extremity (Knee/Foot)	Invivo	Legacy (Bendix)	yes - coil ID	no	yes - coil ID	yes-upgrades only-coil ID	no	no	T2 Map validated. Cable M1085PA (Legacy connector) is required starting at 11.0.		
M3335MN	2415364	HD 3 ch Shoulder	GE Coils	HD	no	yes	no	yes-forward production only	no	no	T2 Map available	3	3
M7000AT	5344905	DV 3Ch Shoulder Coil	GE Coils	P-Connector	no	no	no	no	yes	yes			
M1087SE	2375136-2	3 ch Shoulder	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	T2 Map available	3	3
M1087SD	2225252-6 (large) 2225252-7 (small)	Shoulder	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	T2 Map available		
M1085AN	46-301058P9	Linear Shoulder	Medrad	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	T2 Map available		
M3335LJ	5160986-2	HD 8 ch Wrist	Invivo	HD	no	no	no	yes	Yes, Hypertronix connector	yes	Asset. T2 Map available.		
E8800KE	#N/A (E-cat coils do not have GE P/N's)	8 ch Wrist	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Same coil as M3335LJ but with bendix connector		
M3335SW	5145565-2	HD 4 ch Wrist Array	Invivo	HD	no	yes	no	yes	no	no			
M1087HW	2293670-2	Hi-Res Wrist	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	T2 Map available		
E8800RA	#N/A (E-cat coils do not have GE P/N's)	Small Extremity Wrist	Mayo	HD	no	no	yes	yes	Yes, Hypertronix connector	yes		quadrature	single
M3340CD	5308342-2	Foot Ankle	Invivo	HD	no	no	yes	yes	Yes, Hypertronix connector	yes			
M3340CE	5308343-2	Shoulder	Neo	HD	no	no	yes	yes	Yes, Hypertronix connector	yes			
Body and Breast	-	-	-	-	-	-	-	-	-	-	-	-	-
M3087JG	2401500	HD 8 ch VIBRANT Breast (with Biopsy package)	GE Coils	HD	no	yes	yes	yes	Yes, Hypertronix connector	yes	medial & lateral biopsy access, biopsy and pads included. Asset, Vibrant, Vibrant XV. T2 Map available.	8	8

Catalog	GE P/N on Label	Coil Description	Supplier	Connector Type	EXCITE II	HDe	HD	HDxt	MR450	MR450w	Notes / Application Compatibility	# of elements	# of channels
M3087JG	2401500	HD 8 ch VIBRANT Breast (without Biopsy package)	GE Coils	HD	no	yes	yes	yes	Yes, Hypertronix connector	yes	medial & lateral biopsy access, biopsy and pads included. Asset, Vibrant, Vibrant XV. T2 Map available.	8	8
M3335SB	5145567-2	HD 4 ch Open Breast Array	Invivo	HD	no	yes	no	yes	no	no	Asset, Vibrant. T2 Map available.	4	4
E8800BA	#N/A (E-cat coils do not have GE P/N's)	7CH Breast	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Medial & lateral biopsy access. Asset, Vibrant. T2 Map available.		
M1087BT	2246360	4CH Breast	Invivo	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Lateral biopsy access only, biopsy not included. Asset, Vibrant. T2 Map available.		
M3335LE	2416616	HD 12 ch Body (forward production systems, single connector)	GE Coils	1 HD	no	no	no	yes - forward production only	no	no	Has 1 HD connector that connects to 16 ch port. Asset, Lava, Lava XV, TRICKS. T2 Map available. Compatible with 16 ch systems only.	12	12
M3335LF	2415561	HD 12 ch Body (upgrade systems, dual connectors)	GE Coils	2 HD	no	no	no	yes-upgrades only	no	no	Has 2 HD connectors that each connect to two 8 ch HD ports. Asset, Lava, Lava XV, TRICKS. T2 Map available. Compatible with 16 ch systems only.	12	12
M7000AR	2146616	12 channel body array	GE Coils	P-connector	no	no	no	no	Yes	yes	Similar to M3335LE and M3335LF. Change is connector type. Asset, Lava, Lava XV, TRICKS. T2 Map available.	12	12
M3335MC	2415366	HD 8 ch Body	GE Coils	HD	no	yes	no	yes	Yes, Hypertronix connector	yes	Asset, Lava, Lava XV, TRICKS. T2 Map available.	12	8
M3335ST	5154817	HD 4 ch Torso Array	GEMS	HD	no	yes	no	no	no	no	Asset, Lava, TRICKS. T2 Map available		
M3087JE	100393	8CH Body	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Asset, Lava, Lava XV, TRICKS. T2 Map available.	12	8
M1087TB	2215261	4CH Torso	GEMS	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Use this torso array with Medrad ATD. Asset, Lava, TRICKS. T2 Map available.		
M1087TP	2298043-2	Torso-Pelvic	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no			
E8800AD	#N/A (E-cat coils do not have GE P/N's)	Auto Tuning Device	Medrad	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Use with 4ch torso array M1087TB		
E8801RG	#N/A (E-cat coils do not have GE P/N's)	Endorectal Interface Device (8ch Body)	Medrad	HD	no	no	no	yes	Yes, Hypertronix connector	yes	Use with HD 8ch Body Array M3335MC. HDx only. Performs same function as Auto Tuning Device.		
E8801R	#N/A (E-cat coils do not have GE P/N's)	Disposable Endorectal-Prostate	Medrad	--	--	--	--	--	no	yes	Auto Tuning Device/Interface Device required. 5 pack of probes		
E8801RC	#N/A (E-cat coils do not have GE P/N's)	Disposable Endorectal-Cervix	Medrad	--	--	--	--	--	no	no	Auto Tuning Device/Interface Device required. 5 pack of probes		
E8801RD	#N/A (E-cat coils do not have GE P/N's)	Disposable Endorectal-Colon	Medrad	--	--	--	--	--	no	no	Auto Tuning Device/Interface Device required. 5 pack of probes		
E8800BD	#N/A (E-cat coils do not have GE P/N's)	Breast Immobilization and Biopsy Positioning Device	Invivo	--	--	--	--	--	no	no	Compatible with M1087BT 4 ch Breast coil		

[illegible]

Catalog	GE P/N on Label	Coil Description	Supplier	Connector Type	EXCITE II	HDe	HD	HDxt	MR450	MR450w	Notes / Application Compatibility	# of elements	# of channels
M3335LY	2415562	HD 16CH Lower Leg (single connector)	GE Coils	HD	no	no	no	yes - forward production only	no	no	Compatible with 16 ch systems only. Has 1 HD connector that connects to 16 ch port. Asset, SWiFT, TRICKS. T2 Map available.	32	16
M3087JH	2405289	HD 16CH Lower Leg (dual connector)	GE Coils	HD	no	no	yes	yes	no	no	Compatible with 8 or 16 ch systems. Must be CXK4 (LCC) system and must have 2 8 ch HD ports. Not compatible with: 1. Non-LCC magnets 2. LCC CRM (Cvi) systems 3. LCC magnet with Salt Box covers Asset, SWiFT, TRICKS. T2 Map available.	32	8 or 16
M1087PR	2293676-2	PV Array CRM	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only			TRICKS		
M1087PW	2192406-12	PV Array BRM	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Preamp Kit M1087CY is required for 4 ch systems. TRICKS		
M3335MD	2415376	HD 8CH Cardiac	GE Coils	HD	no	no	no	yes	Yes, Hypertronix connector	yes	Asset, MR Echo, Lava, TRICKS. T2 Map available.	8	8
M3335SC	5154685	HD 4 ch Cardiac	GEMS	HD	no	yes	no	no	no	no	Asset, TRICKS.		
M3087JD	U1-100391	8CH Cardiac	GE Coils	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	Asset, MR Echo, Lava, TRICKS. T2 Map available.	8	8
M1087CA	2174499	4CH Cardiac	GEMS	Legacy (Bendix)	yes	no	yes	yes-upgrades only	no	no	TRICKS		
M7000LB	Anterior: 5366664-2 Posterior: 5366664-3	32Ch Cardiac	Invivo	P-Connector	no	no	no	no	yes	yes		32	32