MINDBURNER

REVIVE — Quick Start

4-LFO MIDI CC Generator · Hand-built in Belfast

REVIVE is a standalone 4-LFO MIDI CC generator, controlled entirely by a single rotary encoder. Each of its 4 LFOs runs independently, sending modulation over regular 5-pin DIN MIDI.

Connect it

Power	9–12V DC, 2.1mm plug, any polarity — **or** 5V via USB-C. Power supply not supplied
MIDI IN	Optional — only needed if you want clock-synced LFOs. Free-running LFOs need no clock at all
MIDI OUT A–D	Connect any or all to the synths, effects or modules you want to modulate

Controls

Control	Action	Result
Rotate	Turn	Adjust the focused field's value
ENC_BTN	Short press	Move to the next field (same job as C)
ENC_BTN	Hold	Toggle between Graphical view (icons/dials, the default) and Text view
D	Short press	Switch to the next LFO (1→4→1)
D	Hold	Context-sensitive: arms MIDI Learn on Ch/CC · toggles retrigger on Mode · turns the LFO on/off elsewhere
C	Short press	Move to the next field
C	Hold	Go to the Save Slots screen
C + D	Hold together	Global mute — instantly silences all 4 outputs at once

Save your patch

REVIVE boots from **Slot 1** — nothing saves automatically. Hold C to open Save Slots, then tap C twice (within 3s) to save the current patch into the selected slot.

Full manual available for download at www.mindburner.co.uk and eBay listing.