

Back Panel Station — Laser Marking Check

User Guide & Troubleshooting

/backpanel/laser

Step 1 — Enter Work Order & Lookup

Scan or type the Work Order, then click **Lookup** (or press Enter). The expected Color and quantity are pulled from Odoo.

Save — remember this Work Order for next time.

Reset — clear everything to start a new Work Order.

Step 2 — Scan Serial Number

Scan the panel's serial number. The system runs 4 checks automatically: **1** Scan Color Check, **2.1** Check Serial Not Already Entered, **2.2** Enter Production Result, **3** Print Laser (marks the panel on this machine's printer via the local bridge).

Step 3 — Watch the result circle

PASS (green) — all 4 checks passed, the laser mark was printed, continue to the next serial.

FAIL (red) — check the process list on the right for which step failed, and the message under the Serial Number field.

A fail at step **1** or **2.1** does not lock the input — just scan the correct serial next.

A fail at step **2.2** or **3** locks the field — click **Try Again** to retry, or **Skip** to move on.

Step 4 — Work Order complete

Watch the progress count (done/total) next to **Save** / **Reset** . When it reaches the total quantity, switch to a new Work Order and continue from Step 1.

Use **View History** (bottom-left link) to search past scans by Work Order or Serial Number.

Troubleshooting

"Enter a Work Order first." / "Enter a Serial Number first."

Cause: the field was left empty when you clicked the button.

Fix: type or scan the value, then try again.

"Work Order 'X' not found on Odoo."

Cause: the Work Order code is wrong or doesn't exist in Odoo.

Fix: double-check the code; confirm with planning that it exists in Odoo.

"Could not determine the color for Work Order 'X'."

Cause: the Work Order record in Odoo has no color set.

Fix: ask planning/admin to set the color in Odoo, then look it up again.

"Scan a Work Order first."

Cause: a Serial Number was scanned before a Work Order was looked up.

Fix: look up the Work Order first, then scan the serial.

FAIL at Step 1 (Scan Color Check)

Cause: the scanned panel's color differs from the Work Order's expected color.

Fix: verify you're scanning the correct panel for this Work Order, then rescan.

"Serial 'X' has an invalid format."

Cause: the wrong barcode was scanned (not a Back Panel serial label).

Fix: rescan the correct serial label on the panel.

FAIL at Step 2.1 – "Serial/Lot X has already been entered for WO Y."

Cause: this serial was already recorded for this Work Order (duplicate scan).

Fix: do not rescan it; check View History if you're unsure it was really counted.

FAIL at Step 2.2 – "Could not enter production result" / "Could not check production result status"

Cause: a temporary connection issue to the production system or database.

Fix: click **Try Again** . If it keeps failing, click **Skip** and report it to IT/admin — this serial's result was not saved.

FAIL at Step 3 – "Could not connect to localhost:8021 – make sure the print bridge is running on this machine."

Cause: the local print bridge app is not running (or was closed) on this computer.

Fix: start the print bridge app on this machine, then click **Try Again** . The production result was already saved — only the laser print is retried.

FAIL at Step 3 – "Could not write file for laser – SN was not sent to print."

Cause: the bridge is running but failed to write the SN file for the laser marker.

Fix: check the laser marker / bridge machine is on and not busy, then click **Try Again** . If it keeps failing, report it to IT/admin.

Nothing happens after clicking Lookup / scanning a serial

Cause: the browser cannot reach the server (network issue).

Fix: check your network connection; contact IT if it persists.