

$x_{SSB}(t) = m(t) \cdot \cos(\omega_c t) \mp \hat{m}(t) \cdot \sin(\omega_c t)$	$\circ \text{---} \bullet$	$M_{\pm}(\omega - \omega_c) + M_{\mp}(\omega + \omega_c)$
--	----------------------------	---

$m(t)$	$\circ \text{---} \bullet$	$M(\omega)$
$\hat{m}(t)$	$\circ \text{---} \bullet$	$-j \text{sgn}(\omega) \cdot M(\omega) = -jM_+(\omega) + jM_-(\omega)$
$m(t) \cdot \cos(\omega_c t)$	$\circ \text{---} \bullet$	$\frac{1}{2}[M(\omega - \omega_c) + M(\omega + \omega_c)]$
$\hat{m}(t) \cdot \sin(\omega_c t)$	$\circ \text{---} \bullet$	$\frac{1}{2j}(-j)[M_+(\omega - \omega_c) - M_+(\omega + \omega_c)] + \frac{1}{2j}(j)[M_-(\omega - \omega_c) - M_-(\omega + \omega_c)]$ $= \frac{1}{2}[-M_+(\omega - \omega_c) + M_-(\omega - \omega_c) + M_+(\omega + \omega_c) - M_-(\omega + \omega_c)]$
$x_{USB}(t)$	$\circ \text{---} \bullet$	$M_+(\omega - \omega_c) + M_-(\omega + \omega_c)$
$x_{LSB}(t)$	$\circ \text{---} \bullet$	$M_-(\omega - \omega_c) + M_+(\omega + \omega_c)$